

[illegible][illegible]

BT1/BT2 in parallel, lying flat on the back.
 Q1 connects them to everything else. USB (Q2) turns it on, the supervisor (Q3) keeps it on; below the cut-off it opens and stays open until USB returns.

$Cut-off = 0.405\text{ V} \times (1 + 1.8\text{ M} / R13)$
 $UIC = 2.61\text{ V} (R13 = 330k) / EDIC = 1.96\text{ V} (470k)$
 $SHIP \text{ high pulse} / MR \text{ (low: Q1 opens (storage mode))}$

Q5 feeds V5SYS while EN_SYS is high; button (SW1), RTC alarm, WAKE, USB (JP1, default on), HOLD from firmware, or JP2 (always on). C8 holds EN_SYS ~4-6 s after a press to firmware can raise HOLD. Q8 (supervisor) sits under Q6; below the cut-off nothing turns it on.

1.8–5.5 V in, 3.3 V out, -500 mA from a 2.6 V capacitor.
 $V_{SENSE} = V_{SYS} / 2$ for the RP2040's ADC (GP27).

Runs from VAON. Its alarm pulls WAKE_N low to start the gadget. I2C address 0x51.

I2S from GP18-20. AMP_EN (GP21) high = on, mono (L+R)/2 mix;
low = shut down. 9 dB gain; use an 8 ohm speaker.

[illegible]

Power flags (ERC only)

Title: <i>TrinketCore – supercapacitor trinket board</i>		
Size: A2	Date: 2026-09-26	Rev: 1.0
KICad E.D.A. kicad-cli 7.0.11+dfsg-1build4		Id: 1/1