

Power Source (on Endpoint 5)

Description: "Mains"
Order: 1

11.7.9.3. Example: Mains Power with Battery Back-up

This example describes a design where the system always runs from the a mains power source and the back-up battery is out-of-circuit until mains power fails at which point the back-up battery powers the system. The Node must define two Power Source Clusters, one for the mains and another for the battery. Since the mains source is primary, it must have a lower Order than the battery source.

Power Source (on Endpoint 2)

Description: "Mains"
Order: 0

Power Source (on Endpoint 5)

Description: "Battery Back-up"
Order: 1

11.7.9.4. Example: Battery with Dual Back-up

This example describes a design with a built-in battery as the primary source, and where two wired sources, USB and a DC adapter, redundantly serve to keep the battery charged and act as back-up if the battery fails. The Node must define three Power Source Clusters, one for each of the battery, the USB source, and the DC adapter. Since the battery is primary, the battery source must have a lower Order than the other sources. This system has no preference between the DC Adapter and USB sources, so these sources will have the same Order.

Power Source (on Endpoint 2)

Description: "Primary Battery"
Order: 0

Power Source (on Endpoint 5)

Description: "DC Adapter"
Order: 1

Power Source (on Endpoint 7)

Description: "USB Power"
Order: 1