

11.7.9.5. Example: Mains Power with Battery Powered Peripheral

This example describes a design with a mains powered core and battery powered peripheral. In this example both power sources are required for proper operation. The Node must define two Power Source Clusters, one for the wired source and one for the battery. Since both sources are required, both sources will have the same Order. We will use Endpoint 2 for the mains power and Endpoint 7 for the battery.

Power Source (on Endpoint 2)

Description: "Mains Power"
Order: 0

Power Source (on Endpoint 7)

Description: "Peripheral Battery"
Order: 0

11.8. Power Topology Cluster

The Power Topology Cluster provides a mechanism for expressing how power is flowing between endpoints.

11.8.1. Revision History

The global ClusterRevision attribute value SHALL be the highest revision number in the table below.

Revision	Description
1	Initial revision

11.8.2. Classification

Hierarchy	Role	Scope	PICS Code
Base	Application	Endpoint	PWRTL

11.8.3. Cluster ID

ID	Name
0x009C	Power Topology

11.8.4. Features

This cluster SHALL support the FeatureMap bitmap attribute as defined below.