

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Current	list[BatChargeFaultEnum]	max 16		empty	M
1	Previous	list[BatChargeFaultEnum]	max 16		empty	M

Current Field

This field SHALL represent the set of faults currently detected, as per [ActiveBatChargeFaults](#).

Previous Field

This field SHALL represent the set of faults detected prior to this change event, as per [Active-BatChargeFaults](#).

11.7.9. Configuration Examples

The following examples illustrate use of the Order attribute in the Power Source Cluster.

11.7.9.1. Example: Redundant Mains Power Sources

This example describes a design with symmetric, dual-redundant mains power sources, where the system is powered by either one of the power sources. The Node must define two Power Source Clusters, one for each mains source. The system indicates no preference for either source, so the sources have the same Order.

Power Source (on Endpoint 2)

Description: "Mains A"
Order: 0

Power Source (on Endpoint 5)

Description: "Mains B"
Order: 0

11.7.9.2. Example: Battery with Mains Power Back-up

This example describes a design with a built-in battery as the primary source, where the mains power serves to keep the battery charged and act as back-up if the battery fails. The Node must define two Power Source Clusters, one for the battery and another for the mains. Since the battery is primary, it must have a lower Order than the mains source.

Power Source (on Endpoint 2)

Description: "Primary Battery"
Order: 0