




Figure 9. Rotary switch device with 8 positions and wraparound

1.13.10.2. Latching Switch with N stable positions (N>2) with random sequence (example: radio buttons)

With such a device, the user can press any of the available buttons, so this switch does not show the incrementing or decrementing behavior of `NewPosition` which we discussed for the latching switch with fixed sequence. In the example in the figure below, the 5 buttons are labeled "A" through "E" for the user and are associated with values 0 through 4. The user first presses the "A" button, and the switch device generates a `SwitchLatched` event with `NewPosition` set to 0. Then the user first presses the "D" button, and the switch device generates a `SwitchLatched` event with `NewPosition` set to 4.



Figure 10. Switch device with radio buttons

1.13.10.3. Momentary Switch with 2 or more non-stable positions

For a Momentary Switch with more than 1 stable position, it depends on the physics of the switch device which sequence of events will be generated.

NOTE

In this section we will mention only the `InitialPress` and `ShortRelease` events. The switch device could also generate the other events defined above for a momentary switch, depending on the capabilities of the switch device and the interaction with the switch device.

The first variant (figure below, example: up/down control for window blinds) shows a switch in neutral position (left figure) which corresponds to `CurrentPosition=0`. The user can press the top