

```
1 package designpatternsandprinciple.ques9;
2
3 public interface Command {
4     void execute();
5 }
```

```
1 package designpatternsandprinciple.ques9;
2
3
4 public class Light {
5
6     public void turnOn() {
7         System.out.println("Light is ON");
8     }
9
10    public void turnOff() {
11        System.out.println("Light is OFF");
12    }
13 }
```

```
1 package designpatternsandprinciple.ques9;
2
3 public class LightOnCommand implements Command {
4
5     private Light light;
6
7     public LightOnCommand(Light light) {
8         this.light = light;
9     }
10
11     @Override
12     public void execute() {
13         light.turnOn();
14     }
15 }
```

```
1 package designpatternsandprinciple.ques9;
2
3
4 public class LightOffCommand implements Command {
5
6     private Light light;
7
8     public LightOffCommand(Light light) {
9         this.light = light;
10    }
11
12    @Override
13    public void execute() {
14        light.turnOff();
15    }
16 }
```

```
1 package designpatternsandprinciple.ques9;
2
3 public class RemoteControl {
4
5     private Command command;
6
7     public void setCommand(Command command) {
8         this.command = command;
9     }
10
11     public void pressButton() {
12         command.execute();
13     }
14 }
```

```
1 package designpatternsandprinciple.ques9;
2
3 public class CommandTest {
4
5     public static void main(String[] args) {
6
7         Light light = new Light();
8
9         Command lightOn = new LightOnCommand(light);
10        Command lightOff = new LightOffCommand(light);
11
12        RemoteControl remote = new RemoteControl();
13
14        remote.setCommand(lightOn);
15        remote.pressButton();
16
17        remote.setCommand(lightOff);
18        remote.pressButton();
19    }
20 }
```

Light is ON

Light is OFF