Casino Open Sign V2 - parts list (partco.fi)

Prices, stock status and links are a snapshot from 2026-11-02. They are not updated unless the user explicitly asks for it, so check them before ordering.

Prices include VAT 25.5 %. Rows without a price: not sold at partco.fi or not looked up. Links: see parts-list.csv.

Qty	Part	Used for	Unit	EUR each	EUR line	In total	Certainty	SKU
Control and display								
1	**Arduino Mega 2560**	the controller	pcs	58.00	58.00	Yes	sure	ARD-A000067
1	**LCD 2x16, I2C**	shows mode, speeds, casino state, arrow	pcs	13.40	13.40	Yes	probable	LCD-2X16-I2C
2	**Hex rotary switch 0-F**	SW3 and SW4: speed of frame + arrow, speed of letters	pcs	3.43	6.86	Yes	probable	KIERTOKYTKIN-216
2	**Slide switch DPDT, long knob**	SW1 arrow direction, SW5 casino closed (one pole used)	pcs	0.90	1.80	Yes	probable	KYT-LIU19-B
1	**Push button, panel mount**	SW2: next letter mode, skips the power-on test	pcs	6.53	6.53	Yes	probable	KYT-DS102-MUS
1	**USB cable A-B**	programming and power of the Arduino	pcs	3.90	3.90	Yes	probable	DK-USB-VJ2-1M
Power								
1	**5 V power supply 10 A (PSU1)**	feeds the Mega 5V pins, the Grove shield, the 11 sticks and the LCD	pcs	23.79	23.79	Yes	sure	LRS-50-5
1	**Blade fuse 10 A**	F1 right after PSU1 (the Mega 5V pins carry the stick current)	pcs	0.31	0.31	Yes	sure	SUA-10A
1	**12 V power supply 4.2 A (PSU2)**	powers ONLY the two 12 V strips (28 pixels peak about 1-2 A at the brightness limit)	pcs	23.79	23.79	Yes	probable	LRS-50-12
2	**Fuse holder**	fuse holders for F1 (5 V line) and F2 (+12 V line)	pcs	3.56	7.12	Yes	sure	SULPES-APUR
1	**Blade fuse 5 A**	F2 in the +12 V line (the two strips need about 2 A at most)	pcs	0.33	0.33	Yes	probable	SUA-5A
2	**Capacitor 1000 uF 25 V**	C1 across the 5 V supply (16 V or more) and C2 across +12 V at the strips (25 V)	pcs	1.73	3.46	Yes	sure	ELKO105-1000U-25V
2	**Mains cord, Schuko plug, free end**	230 V into PSU1 and PSU2	pcs	5.20	10.40	Yes	sure	LAITEJOHTO-2V-KULM
1	**Plastic enclosure with cable glands**	encloses both power supplies and the mains wiring (check the size: two supplies)	pcs	12.70	12.70	Yes	probable	KOTEV-171
LED strip								
1	**RGB LED strip, 12 V, WS2811, 30 LEDs/m, 5 m**	frame (18 pixels) + letters (10 pixels): 28 pixels = 2.8 m, one reel is enough	reel	70.37	70.37	Yes	uncertain	LED-N-RGB-W2812X15
11	**Grove RGB LED stick (10x WS2813 mini)**	10 arrow sticks + the CLOSED light stick	pcs	-	-	Yes	probable	-
1	**Grove Base Shield for Arduino Mega**	the 11 sticks plug into its connectors D2-D8 and A0-A3	pcs	-	-	Yes	probable	-
Wiring and assembly								
2	**Resistor 330 ohm**	R1, R2: data lines of the frame (D12) and the letters (D10) strips; the sticks have none	pcs	0.45	0.90	Yes	sure	VASTUS-2W-330R
1	**Perfboard 200 x 100 mm**	resistors, capacitors, fuse holders, hex switches, connections	pcs	6.50	6.50	Yes	sure	KL-PL200
1	**Heat-shrink tubing set**	insulates soldered joints	set	10.50	10.50	Yes	sure	K-SARJA-86271
10	**Hook-up wire 0.75 mm2, red**	+12 V feeds and data wires (length is an estimate)	m	-	-	Yes	probable	KAA-AJ-1X0.75-PUN
10	**Hook-up wire 0.75 mm2, black**	GND feeds (length is an estimate)	m	-	-	Yes	probable	KAA-AJ-1X0.75-MUS
1	**Solder wire**	soldering	roll	-	-	Yes	probable	-
Plate and letters (not at partco.fi)								
1	**Black plate 60 x 30 cm**	the sign plate 60 x 30 cm (with the CLOSED hole text and the arrow stick holes)	pcs	-	-	Yes	sure	-
1	**Red plexiglass letters**	CASINO and OPEN	set	-	-	Yes	sure	-
1	**Frosted plastic**	behind the CLOSED hole text, so the light does not show as dots	pcs	-	-	Yes	sure	-
1	**Mounting hardware**	fixing the strips, board, display and letters to the plate	set	-	-	Yes	sure	-
Insurance for the uncertain parts								
2	**Spare resistors 330 ohm**	in case a data line needs more or one is damaged	pcs	0.45	0.90	Insurance	sure	VASTUS-2W-330R
2	**Spare blade fuse 5 A**	a blown fuse is the usual first mishap	pcs	0.33	0.66	Insurance	sure	SUA-5A
1	**Logic buffer 74HCT125 (DIP14)**	cleans up the 5 V data signal if the strip is fussy about it	pcs	1.05	1.05	Insurance	uncertain	74HCT125
Alternatives and options (not in any total)								
1	**Alternative: Seeeduino Mega**	instead of the Arduino Mega	pcs	46.70	46.70	No	sure	SEEED-102010007
1	**Old design: 5 V strip, 60 LEDs/m, 5 m**	the strip of the earlier 5 V design	reel	136.00	136.00	No	sure	LED-N-RGB-W2812X30
1	**White strip, 12 V, 60 LEDs/m, 5 m (not addressable)**	only on/off and dimming of whole zones	reel	35.14	35.14	No	sure	LEDN-24W-VAL
2	**Option: knob for the hex switches**	SW3 and SW4 (pin 3.8 mm; a standard knob may not fit)	pcs	-	-	No	uncertain	-
1	**Option: screw terminal block 2-pole**	removable connections for the strip pieces	pcs	0.79	0.79	No	sure	TBW5-2P

Total of the rows marked Yes that have a price: 260.66 EUR (9 counted rows have no price). Insurance rows: 2.61 EUR.

Not in the list: your own Grove sticks if you already have them, the plate material, the letters, the frosted plastic, tools.

Strip pixels: frame 18 + letters 10 = 28 pixels of one 5 m reel (50 pixels); the 11 sticks and the Grove shield are listed without price.