

Program - 1

Write and assemble an 8051 program to add the following data and then use the simulator to examine the CY flag. (92H, 23H, 66H, 87H, 0F5H)

```
ORG 0000H

MOV A,#92H

MOV R0,#23H

ADD A,R0

JNC L1

INC R7

L1: MOV R1,#66H

ADD A,R1

JNC L2

INC R7

L2: MOV R2,#87H

ADD A,R2

JNC L3

INC R7

L3: MOV R3,#0F5H

ADD A,R3

JNC L4

INC R7

L4: SJMP L4

END
```