

G01 / PROTECTED ANSWERS

G01 REVIEW B

Standalone Zero-to-Job-Ready Data Engineer 2026

Study, practise, check and explain.

A complete learning route

Start with the lesson video. Read the worked explanation beside it, pause to reproduce the example, then solve the supplied task. The books contain your study notes; keep your own work and results as evidence.

Use the protected answers after saving your first attempt. A changed retry shows what you can now do independently. There is no forced timer during learning.

One course. M00-M19. 264 lessons and 50 project phases.

Contents

Tap a topic or use the PDF bookmarks. These numbers are the actual pages in this edition.

Read this first 3

YOUR STANDALONE GATE BOOK 3

Open only after Gate B attempt is saved 3

Source contract and quality 3

Row calculations 3

Category summary 3

Validation 3

Repair route 4

Read this first

Open this book after saving your own attempt. Compare the reasoning and result, repair the cause of a mistake, then close the answer and try changed inputs.

YOUR STANDALONE GATE BOOK

Open only after Gate B attempt is saved

Assessment rule: Save the current attempt before opening its review. Fresh Gate B stays closed until explicitly assigned after repair.

Source contract and quality

There are six order rows and six fields. `order_id` is the intended unique key; no supplied ID is missing or repeated. B103 has the only unknown payment status. The separate text Cable may become Cable by trimming the known spaces while the original is preserved. That cleaning step does not justify changing B103's missing payment state.

Row calculations

Order	Calculation	Amount	Payment group
B101	3 x 120	360.00	Paid
B102	2 x 350	700.00	Unpaid
B103	4 x 55	220.00	Unknown
B104	3 x 80	240.00	Paid
B105	5 x 35	175.00	Unpaid
B106	1 x 120	120.00	Paid

Whole amount is 1815.00. Paid is 720.00 across 3 orders. Unpaid is 875.00 across 2 orders. Unknown is 220.00 across 1 order. Known-status amount is 1595.00 across 5 orders. Paid alone is not the same question as known status.

Category summary

Electronics = Cable 480 + Adapter 700 = 1180. Paper = Notebook 220 + Folder 175 = 395. Writing = Pen Set 240. The category totals reconcile to 1815. The chart therefore may support that Electronics has the largest amount in this supplied batch, but it cannot establish profit, typical demand or future sales.

Validation

Payment counts reconcile $3 + 2 + 1 = 6$. Payment amounts reconcile $720 + 875 + 220 = 1815$. Category amounts reconcile $1180 + 395 + 240 = 1815$. A source-row/ID comparison helps detect a dropped order; a separate three-state payment classification check helps detect unknown being relabelled as unpaid.

For a temporary input-change test, any single controlled change is valid if the predicted delta matches the formula output and the original source value is restored. For example, changing B106 quantity from 1 to 2 should add exactly 120, temporarily raising the whole amount to 1935.

Repair route

Do not copy this review into the workbook and call Gate B passed. Identify the exact weak dimension, close this review, make a fresh changed micro-proof for that dimension and preserve both the original failed attempt and the repair. If several dimensions remain dependent on the review, return to the relevant M01 lesson practice before another full assessment.