

Assignment 4

✚ Determined Type of Addressing mode for all question then calculate physical address:

1. Suppose that **DS = 1000H**, **SS = 2000H**, **BP = 1000H**, and **DI = 0100H**. Determine the memory address accessed by each of the following instructions, assuming real mode operation:
 - a. MOV AL, [BP+DI]
 - b. MOV CX, [DI+100 H]
 - c. MOV EDX, [BP - 0200 H]
2. Suppose that **DS = 1100H**, **BX = 0200H**, **LIST = 0250H**, and **SI = 0500H**. Determine the address accessed by each of the following instructions, assuming real mode operation:
 - a. MOV LIST[SI], EDX
 - b. MOV CL, LIST[BX+SI]
 - c. MOV CH, [BX+SI]
3. Suppose that **DS = 1300H**, **SS = 1400H**, **BP = 1500H**, and **SI = 0100H**. Determine the address accessed by each of the following instructions, assuming real mode operation:
 - a. MOV EAX,[BP+200H]
 - b. MOV AL, [BP+SI-200H]
 - c. MOV AL,[SI-0100H].