INDEX

Exp. No.	Date	Name of the Experiment	Page no.	Marks	Signature
1.		**8051 ALP to apply various addressing modes for arithmetic and logical functions**			
a.	10.07.2026	Addition & Subtraction of two 8 bit numbers	1		
b.	10.07.2026	Multiplication & Division of two 8 bit numbers	3		
c.	10.07.2026	Logical AND & OR of two 8 bit numbers	5		
d.	10.07.2026	Logical NOT & XOR of two 8 bit numbers	7		
2.		**8051 ALP for data transfer between memory blocks**			
a.	17.07.2026	Transfer the block of data between two Memory locations	9		
b.	17.07.2026	Exchange the block of data between locations	10		
3.		**8051 ALP to find the Largest / Smallest in a given array**			
a.	24.07.2026	ALP Program for finding largest number of given N numbers	11		
b.	24.07.2026	ALP Program for finding smallest number of given N numbers	12		
4.		**8051 C programming for delay timer**			
a.	31.07.2026	8051 programming for timer mode 1 and enable/disable a port pin with a delay	13		
b.	31.07.2026	8051 programming with timer-based interrupt to toggle an output pin at a fixed time interval	14		
c.	31.07.2026	Universal Asynchronous Receiver Transmitter (UART) programming using 8051	15		
5.		**8051 C programming for port handling operations**			
a.	07.08.2026	To display ASCII number in a port	16		
b.	07.08.2026	I/O port programming with delay	17		
c.	07.08.2026	I/O port programming to toggle between two or more ports	18		
6.		**8051 C programming for interfacing actuators and sensors**			
a.	14.08.2026	Blinking the LED with some delay	19		
b.	14.08.2026	8051 programming to interface with LED with switch control	20		
7.		**8051 C programming for interfacing output unit**			

Exp. No.	Date	Name of the Experiment	Page no.	Marks	Signature
a.	21.08.2026	Display the input text in LCD	23		
b.	21.08.2026	LCD with switch control	25		
8.	28.08.2026	ARM7 programming to interface LED and LCD	29		
9.	11.09.2026	ARM7 programming for buzzer interface	34		
10.	25.09.2026	ARM7 programming for Timer controlling operation	36		
Content Beyond the Syllabus					
CBS	27.06.2026	Virtual Lab Programming for Delay Generation and Effect of CPU Clock	38		
	03.07.2026	Virtual Lab Programming for I/O Interfacing (LED and Switch Interfacing) Programming with On-Chip Timers/Counters	41, 44		
			Average		

EXP NO.1a	ADDITION AND SUBTRACTION OF TWO 8 BIT NUMBERS
DATE: 10.07.26	

AIM:

To develop and simulate 8051 Assembly language programs for the addition and subtraction of two 8 bit numbers using Keil µVision IDE.

DESCRIPTION:

Keil µVision is a software development environment used for programming and simulating 8051 microcontrollers. It provides tools for writing Assembly language programs, assembling source code, debugging errors, and observing register as well as memory contents through simulation.

In this experiment, the ADD and SUBB instructions of the 8051 were used to add and subtract two 8 bit hexadecimal numbers, with and without carry or borrow. The simulator was used to verify the results by monitoring the accumulator, registers and the carry flag.


ARITHMETIC OPERATIONS

(i) Addition without Carry

Objective: To add two hexadecimal numbers without generating a carry.

Input	Calculation	Result
18H = 24 25H = 37	24 + 37 = 61	3DH = 61 Carry = 0

Program	Output


`CLR C`
`MOV A,#18H`
`ADD A,#25H`
`MOV R0,A`
	

(ii) Addition with Carry

Objective: To perform addition of two hexadecimal numbers that produces a carry.

Input	Calculation	Result
B2H = 178 5AH = 90	178 + 90 = 268	R1 = 0CH Carry = 1

Program	Output


`CLR C`
`MOV A,#0B2H`
`ADD A,#5AH`
`MOV R1,A`
	

(iii) Subtraction without Borrow

Objective: To subtract one hexadecimal number from another without borrow.

Input	Calculation	Result
58H = 88 1EH = 30	88 − 30 = 58	3AH = 58 Borrow(Carry)=0

Program	Output


`CLR C`
`MOV A,#58H`
`SUBB A,#1EH`
`MOV R2,A`
	

(iv) Subtraction with Borrow

Objective: To subtract a greater hexadecimal value from a smaller one.

Input	Calculation	Result
2AH = 42 45H = 69	42 − 69 = −27	E5H Borrow(Carry)=1

Program	Output

`CLR C`
`MOV A,#2AH`
`SUBB A,#45H`
`MOV R3,A`
	

RESULT:

Thus, the addition and subtraction of two 8 bit numbers were successfully implemented and verified using 8051 Assembly Language in Keil µVision IDE.

EXP NO.1b	MULTIPLICATION AND DIVISION OF TWO 8 BIT NUMBERS
DATE: 10.07.26	

AIM:

To develop and simulate 8051 Assembly language programs for the multiplication and division of two 8 bit numbers using Keil µVision IDE.

DESCRIPTION:

Keil µVision is a software development environment used for programming and simulating 8051 microcontrollers. It provides tools for writing Assembly language programs, assembling source code, debugging errors, and observing register as well as memory contents through simulation.

In this experiment, the MUL AB and DIV AB instructions of the 8051 were used to multiply and divide two 8 bit hexadecimal numbers. The product is obtained as a 16-bit result in registers B and A, while division gives the quotient in the accumulator and the remainder in register B. The simulator was used to verify the results.


ARITHMETIC OPERATIONS

(i) Multiplication without Overflow

Objective: To multiply two hexadecimal numbers without overflow.

Input	Calculation	Result
08H = 8 06H = 6	8 × 6 = 48	A = 30H B = 00H

Program	Output


`MOV A,#08H`
`MOV B,#06H`
`MUL AB`
`MOV R4,A`
	

(ii) Multiplication with Overflow

Objective: To multiply two hexadecimal numbers producing a 16-bit result.

Input	Calculation	Result
28H = 40 14H = 20	40 × 20 = 800	A = 20H B = 03H

Program	Output


`MOV A,#28H`
`MOV B,#14H`
`MUL AB`
`MOV R5,A`
`MOV R6,B`
	

(iii) Division without Remainder

Objective: To divide two hexadecimal numbers exactly without remainder.

Input	Calculation	Result
40H = 64 08H = 8	64 ÷ 8 = 8	Quotient = 08H Remainder = 00H

Program	Output


`MOV A,#40H`
`MOV B,#08H`
`DIV AB`
`MOV R7,A`
	

(iv) Division with Remainder

Objective: To divide two hexadecimal numbers producing quotient and remainder.

Input	Calculation	Result
3BH = 59 08H = 8	59 ÷ 8 = 7 Remainder = 3	Quotient = 07H Remainder = 03H

Program	Output

`MOV A,#3BH`
`MOV B,#08H`
`DIV AB`
`MOV R0,A`
`MOV R1,B`
	

RESULT:

Thus, the multiplication and division of two 8 bit numbers were successfully implemented and verified using 8051 Assembly Language in Keil µVision IDE.

EXP NO.1c	LOGICAL AND & OR OF TWO 8 BIT NUMBERS
DATE: 10.07.26	

AIM:

To develop and simulate 8051 Assembly language programs for the logical AND and OR operations on two 8 bit numbers using Keil µVision IDE.

DESCRIPTION:

Keil µVision is a software development environment used for programming and simulating 8051 microcontrollers. It provides tools for writing Assembly language programs, assembling source code, debugging errors, and observing register as well as memory contents through simulation.

In this experiment, the ANL and ORL instructions of the 8051 were used to perform the bitwise AND and OR operations on two 8 bit hexadecimal numbers. The simulator was used to verify the results by monitoring the accumulator and registers.


LOGICAL OPERATIONS

(i) Logical AND

Objective: To perform a bitwise AND operation.

Input	Calculation	Result
5AH = 90 3CH = 60	01011010 00111100 ——————— 00011000	18H = 24

Program	Output


`MOV A,#5AH`
`ANL A,#3CH`
`MOV R2,A`
	

(ii) Logical OR

Objective: To perform a bitwise OR operation.

Input	Calculation	Result
44H = 68 13H = 19	01000100 00010011 ———————— 01010111	57H = 87

Program	Output

`MOV A,#44H`
`ORL A,#13H`
`MOV R3,A`
	

RESULT:

Thus, the logical AND and OR operations on two 8 bit numbers were successfully implemented and verified using 8051 Assembly Language in Keil µVision IDE.

EXP NO.1d	LOGICAL NOT & XOR OF TWO 8 BIT NUMBERS
DATE: 10.07.26	

AIM:

To develop and simulate 8051 Assembly language programs for the logical NOT and XOR operations on 8 bit numbers using Keil µVision IDE.

DESCRIPTION:

Keil µVision is a software development environment used for programming and simulating 8051 microcontrollers. It provides tools for writing Assembly language programs, assembling source code, debugging errors, and observing register as well as memory contents through simulation.

In this experiment, the CPL instruction of the 8051 was used to find the complement (NOT) of an 8 bit number, and the XRL instruction was used to perform the bitwise XOR operation on two 8 bit hexadecimal numbers. The simulator was used to verify the results by monitoring the accumulator and registers.


LOGICAL OPERATIONS

(i) Logical NOT (Complement)

Objective: To complement every bit of the accumulator.

Input	Calculation	Result
55H = 85	01010101 ↓ 10101010	AAH = 170

Program	Output


`MOV A,#55H`
`CPL A`
`MOV R5,A`
	

(ii) Logical XOR

Objective: To perform a bitwise Exclusive-OR operation.

Input	Calculation	Result
5AH = 90 33H = 51	01011010 00110011 ———————— 01101001	69H = 105

Program	Output

`MOV A,#5AH`
`XRL A,#33H`
`MOV R4,A`
	

RESULT:

Thus, the logical NOT and XOR operations on 8 bit numbers were successfully implemented and verified using 8051 Assembly Language in Keil µVision IDE.

EXP NO.2	8051 ALP FOR DATA TRANSFER BETWEEN MEMORY BLOCKS
DATE: 17.07.26	

A) Transfer the Block of Data between two Memory Locations

AIM:

To write an Assembly Language Program (ALP) to transfer a block of data from one internal memory location to another.

ALGORITHM:


1. Initialize the source memory address.
2. Initialize the destination memory address.
3. Load the counter with the number of bytes to be transferred.
4. Read one byte from the source location.
5. Store the byte in the destination location.
6. Increment both source and destination pointers.
7. Decrement the counter.
8. Repeat until the counter becomes zero.
9. Stop the program.

PROGRAM:


```
ORG 00H
MOV R0,#60H
MOV R1,#70H
MOV R2,#04H
L1: MOV A,@R0
MOV @R1,A
INC R0
INC R1
DJNZ R2,L1
END
```

OUTPUT:

Memory window before execution



Memory window after execution



RESULT:

Thus, the block of data was successfully transferred from one internal memory location to another and verified successfully.

B) Exchange (Swap) the Block of Data Between Two Memory Locations

AIM:

To write an Assembly Language Program (ALP) to exchange (swap) the contents of a block of data between two internal memory locations.

ALGORITHM:


1. Initialize the starting address of Block 1.
2. Initialize the starting address of Block 2.
3. Load the counter with the number of bytes.
4. Read one byte from Block 1 into the Accumulator.
5. Store it temporarily in Register B.
6. Read one byte from Block 2 into the Accumulator.
7. Move the contents of Register B to Block 2.
8. Move the Accumulator contents to Block 1.
9. Increment both memory pointers.
10. Decrement the counter.
11. Repeat until all bytes are exchanged.
12. Stop the program.

PROGRAM:


```
ORG 00H
MOV R0,#50H
MOV R1,#80H
MOV R2,#04H
L1: MOV A,@R0
MOV B,A
MOV A,@R1
MOV @R0,A
MOV A,B
MOV @R1,A
INC R0
INC R1
DJNZ R2,L1
END
```

OUTPUT:

Memory window before execution



Memory window after execution



RESULT:

Thus, the contents of the two memory blocks were successfully exchanged and verified successfully.

EXP NO.3	8051 ALP TO FIND THE LARGEST / SMALLEST IN A GIVEN ARRAY
DATE: 24.07.26	

(a) Largest Number in an Array

AIM:

To write and execute an 8051 Assembly Language program to find the largest and smallest numbers in an array and store the results in the specified memory location.


ALGORITHM:

1. Start the program.
2. Load the number of array elements into register R2.
3. Initialize R0 with the starting address of the array.
4. Move the first array element into accumulator A.
5. Initialize R1 with the address of the next element.
6. Compare the current largest value in A with the next array element.
7. If the next element is larger, move it into A.
8. Increment the array pointer.
9. Repeat the comparison until all elements are checked.
10. Store the largest value from A into memory location 70H.
11. Stop.

PROGRAM:

Program	Output

```
ORG 00H
MOV R2,50H
DEC R2
MOV R0,#60H
MOV A,@R0
MOV R1,#61H
L1: MOV 00H,@R1
CJNE A,00H,L2
L2: JNC L3
MOV A,@R1
L3: INC R1
DJNZ R2,L1
MOV 70H,A
END
```



(b) Smallest Number in an Array


AIM:

To write and execute an 8051 Assembly Language program to find the smallest number in an array stored in the specified memory location.

ALGORITHM:

1. Start the program.
2. Load the number of array elements into register R2.
3. Initialize R0 with the starting address of the array.
4. Move the first array element into accumulator A.
5. Initialize R1 with the address of the next element.
6. Compare the current smallest value in A with the next array element.
7. If the next element is smaller, move it into A.
8. Increment the array pointer.
9. Repeat the comparison until all elements are checked.
10. Store the smallest value from A into memory location 70H.
11. Stop.

PROGRAM:

Program	Output
ORG 00H MOV R2,50H DEC R2 MOV R0,#60H MOV A,@R0 MOV R1,#61H L1: MOV 00H,@R1 CJNE A,00H,L2 L2: JNC L3 MOV A,@R1 L3: INC R1 DJNZ R2,L1 MOV 70H,A END	

RESULT:

Thus, the 8051 Assembly Language programs for finding the largest and smallest numbers in an array were executed successfully.

EXP NO.4	8051 C PROGRAMMING FOR DELAY TIMER
DATE: 31.07.26	

(a) 8051 Timer Mode 1 with Delay

AIM:

To write and execute an 8051 C program using Timer 0 in Mode 1 to generate a delay and enable/disable a port pin.


ALGORITHM:

1. Start the program.
2. Define the port pin P1.0 as the test pin.
3. Configure Timer 0 in Mode 1 (16-bit timer mode).
4. Load the initial values into TH0 and TL0.
5. Start Timer 0.
6. Wait until the Timer 0 overflow flag TF0 is set.
7. Stop the timer and clear TF0.
8. Toggle the P1.0 pin.
9. Repeat the process continuously.

PROGRAM:

Program	Output

```
#include <reg51.h>
sbit test = P1^0;
void timer_delay()
{
  TH0 = 0xFC;
  TL0 = 0x74;
  TR0 = 1;
  while(TF0 == 0);
  TR0 = 0;
  TF0 = 0;
}
void main()
{
  TMOD = 0x01;
  while(1)
  {
    test = ~test;
    timer_delay();
  }
}
```



(b) Timer-Based Interrupt to Toggle Output Pin

AIM:

To write and execute an 8051 C program using a timer-based interrupt to toggle an output pin at a fixed time interval.


ALGORITHM:

1. Start the program.
2. Define P1.0 as the output/test pin.
3. Configure Timer 0 in Mode 1.
4. Load TH0 and TL0 with the required initial values.
5. Enable the global interrupt.
6. Enable Timer 0 interrupt.
7. Start Timer 0.
8. When Timer 0 overflows, execute the interrupt service routine.
9. Toggle P1.0.
10. Reload TH0 and TL0.
11. Repeat the process continuously.

PROGRAM:

Program	Output

```
#include <reg51.h>
sbit test = P1^0;
void Timer_init(void)
{
  TMOD = 0x01;
  TH0 = 0x4C;
  TL0 = 0x00;
  TR0 = 1;
}
void Timer0_ISR(void) interrupt 1
{
  test = ~test;
  TH0 = 0x4C;
  TL0 = 0x00;
}
int main(void)
{
  EA = 1;
  ET0 = 1;
  Timer_init();
  while(1);
}
```



(c) UART Programming Using 8051

AIM:

To write and execute an 8051 C program for Universal Asynchronous Receiver Transmitter (UART) to transmit a character serially.


ALGORITHM:

1. Start the program.
2. Configure Timer 1 in Mode 2 for baud-rate generation.
3. Load the required value into TH1.
4. Configure the serial control register SCON.
5. Start Timer 1.
6. Load the character to be transmitted into SBUF.
7. Wait until the transmission interrupt flag TI is set.
8. Clear the TI flag.
9. Repeat the transmission continuously.

PROGRAM:

Program	Output

```
#include <reg51.h>
void main(void)
{
  TMOD = 0x20;
  TH1 = 0xFA;
  SCON = 0x50;
  TR1 = 1;
  while(1)
  {
    SBUF = 'B';
    while(TI == 0);
    TI = 0;
  }
}
```



RESULT:

Thus, the 8051 C programs were successfully implemented for timer delay and port toggling, timer-based interrupt, and UART serial data transmission.

EXP NO.5	8051 C PROGRAMMING FOR PORT HANDLING OPERATIONS
DATE: 07.08.26	

(a) To Display ASCII Number in a Port

AIM:


To write and execute 8051 C programs that display an ASCII number through a port, perform I/O port programming with a delay, and toggle between two or more I/O ports.

ALGORITHM:

1. Begin the program.
2. Include the header file REG51.H.
3. Declare the variables x and y.
4. Load the hexadecimal number 29H into the variable mb.
5. Separate the lower nibble using mb & 0x0F.
6. Add 30H to change the lower nibble into its ASCII value.
7. Send the result to Port 1.
8. Separate the upper nibble using mb & 0xF0.
9. Shift the upper nibble four bits to the right.
10. Add 30H to get its ASCII value.
11. Send the result to Port 1.
12. Repeat the steps continuously.

PROGRAM:

Program	Output

`#include<reg51.h>`
`void main(void){`
`  while(1){`
`  unsigned char x,y;`
`  unsigned char mb = 0x29 ;`
`  x = mb &0x0F;`
`  P1 = x|0x30;`
`  y = mb & 0xF0;`
`  y = y >>4;`
`  P1 = y|0x30;}}`
	


(b) I/O Port Programming with Delay

ALGORITHM:

1. Begin the program.
2. Include the header file REG51.H.
3. Define P1.7 as the bit mybit.
4. Write a delay function.
5. Clear mybit to 0.
6. Call the delay function.
7. Make mybit equal to 1.
8. Call the delay function once more.
9. Repeat this process in an endless loop.
10. Watch Port 1 bit 7 toggle in the simulator.

PROGRAM:

Program	Output

`#include <reg51.h>`
`sbit mybit = P1^7;`
`void delay(unsigned int a);`
`void main(void)`
`{`
`  while(1)`
`  {`
`  mybit = 0;`
`  delay(20);`
`  mybit = 1;`
`  delay(20);`
`  }`
`}`
`void delay(unsigned int a)`
`{`
`  unsigned int i, j;`
`  for(i = 0; i < a; i++)`
`  for(j = 0; j < 50; j++);`
`}`
	


(c) 8051 I/O Port Programming to Toggle Between Two or More Ports

ALGORITHM:

1. Begin the program.
2. Include the header file REG51.H.
3. Initialize Port 0, Port 1, Port 2 and Port 3 with 33H.
4. Invert the contents of Port 0.
5. Invert the contents of Port 1.
6. Invert the contents of Port 2.
7. Invert the contents of Port 3.
8. Add a short delay.
9. Repeat this process in an endless loop.
10. Observe that the ports alternate between 33H and CCH.

PROGRAM:

Program	Output

`#include <reg51.h>`
`void MsDelay(unsigned int);`
`void main()`
`{`
`  P0 = P1 = P2 = P3 = 0x33;`
`  while(1)`
`  {`
`  P0 = ~P0;`
`  P1 = ~P1;`
`  P2 = ~P2;`
`  P3 = ~P3;`
`  MsDelay(1);`
`  }`
`}`
`void MsDelay(unsigned int itime)`
`{`
`  unsigned int i, j;`
`  for(i = 0; i < itime; i++)`
`  for(j = 0; j < 3; j++);`
`}`
	

RESULT:

Thus, the 8051 C programs for displaying an ASCII number, I/O port programming with delay and toggling of multiple I/O ports were executed successfully and the expected port outputs were obtained.

EXP NO.6	8051 C PROGRAMMING FOR INTERFACING ACTUATORS AND SENSORS
DATE: 14.08.26	

A. 8051 Programming to Blink the LED with Delay

AIM:

To interface LEDs with the 8051 microcontroller and blink them with a time delay.

PROCEDURE:


1. Create a new project.
2. Select the microcontroller Atmel → AT89C52.
3. Enter the source code.
4. Save the program.
5. Add the HEX file to the output.
6. Compile the program using Project → Build Target / F7.
7. The HEX file will be generated in the project folder.

PROGRAM:


```
#include <REGX52.H>
#define LED1 P1_5
#define LED2 P1_4
#define LED3 P1_3
void delay(unsigned int count);
void main()
{
   while(1)
   {
      LED1 = 0;
      LED2 = 1;
      LED3 = 0;
      delay(50);
      LED1 = 1;
      LED2 = 0;
      LED3 = 0;
      delay(50);
   }
}
void delay(unsigned int count)
{
   int x, y;
   for(x = 0; x < count; x++)
      for(y = 0; y < 1275; y++);
}
```

OUTPUT:

BEFORE EXECUTION:



AFTER EXECUTION:



B. LED with Switch Control

AIM:

To operate the LEDs through switches connected to the 8051 microcontroller and produce a beep whenever a switch is pressed.

ALGORITHM:

1. Start the program.
2. Include the required header file and define the ports for LEDs, switches and beep.
3. Run an infinite while loop for continuous switch monitoring.
4. Check whether a particular switch is pressed.
5. When a switch is pressed, produce a beep for a short delay and switch ON the corresponding LED.
6.

PROGRAM:

```
#include <REGX52.H>
#define EN P1_0
#define RS P1_2
```

```
#define SW1 P2_0
#define SW2 P2_1
#define SW3 P2_2
#define beep P1_6
#define LED0 P1_5
#define LED1 P1_4
#define LED2 P1_3
void delay(unsigned int count);
void main()
{
   while(1)
   {
      if(SW1 == 0)
      {
         while(!SW1);
         beep = 0;
         delay(25);
         beep = 1;
         LED0 = 0;
         LED1 = 1;
         LED2 = 1;
      }
      if(SW2 == 0)
      {
         while(!SW2);
         beep = 0;
         delay(25);
         beep = 1;
         LED0 = 1;
         LED1 = 0;
         LED2 = 1;
      }
      if(SW3 == 0)
      {
         while(!SW3);
         beep = 0;
         delay(25);
         beep = 1;
         LED2 = 0;
         LED1 = 1;
         LED0 = 1;

               }
      }
}
void delay(unsigned int count)
{
```

```
    int x, y;
    for(x = 0; x < count; x++)
       for(y = 0; y < 1275; y++);
}
```

OUTPUT:



LED1



LED2



LED3

RESULT

Thus, the 8051 C program for LED interfacing was executed and verified successfully.

EXP NO.7	8051 C PROGRAMMING FOR INTERFACING OUTPUT UNIT
DATE: 21.08.26	

A. 8051 C programming to interface with LCD and display the given input

AIM:

To interface an LCD with the 8051 microcontroller, display the given text, and show different messages on the LCD according to the switch pressed.

ALGORITHM:

1. Start the program.
2. Include the required header file and define the LCD data port, EN, RS and RW pins.
3. Initialize the LCD using the required commands.
4. Send the required text to the LCD.
5. Run the program continuously.
6. Stop the program.

HEXCODE COMMANDS:


30 1 Line, 5x7 matrix
38 2 lines and 5×7 matrix
01 Clear display screen
06 Increment cursor (shift cursor to right)
0C Display on, cursor off
80 Force cursor to beginning (1st line)
C0 Force cursor to beginning (2nd line)

PROGRAM:

```
#include <REGX52.H>
#define LCD_PORT P0
#define EN P1_0
#define RS P1_2
#define RW P1_1
void lcd_initial(void);
void lcd_command(char);
void lcd_data(char);
void lcd_display(unsigned char, const char *);
void delay(unsigned int);
void main()
{
   lcd_initial();
   lcd_display(0x80, "AJAY.I");
   lcd_display(0xC0, "3rd Year");
   while(1);
}
void lcd_initial(void)
{
   lcd_command(0x30);
   lcd_command(0x30);
```

```
    lcd_command(0x30);
    lcd_command(0x38);
    lcd_command(0x01);
    lcd_command(0x06);
    lcd_command(0x0C);
    lcd_command(0x80);
}
void lcd_command(char value)
{
    RW = 0;
    RS = 0;
    EN = 1;
    LCD_PORT = value;
    delay(1);
    EN = 0;
}
void lcd_data(char value)
{
    RW = 0;
    RS = 1;
    EN = 1;
    LCD_PORT = value;
    delay(1);
    EN = 0;
}
void lcd_display(unsigned char locn, const char *dat)
{
    lcd_command(locn);
    while(*dat != '\0')
    {
        lcd_data(*dat);
        dat++;
    }
}
void delay(unsigned int count)
{
    int x, y;
    for(x = 0; x < count; x++)
        for(y = 0; y < 1275; y++);
}
```

OUTPUT:



B. LCD WITH SWITCH CONTROL

AIM:

To interface an LCD with the 8051 microcontroller and show a different message for each switch that is pressed.

ALGORITHM:

1. Start the program.
2. Include the required header file and define LCD, switch, EN, RS, RW and buzzer pins.
3. Initialize the LCD.
4. Display “Press Any Switch” initially.
5. Continuously check the switches.
6. If SW1 is pressed, display “Pressed Switch 1”.
7. If SW2 is pressed, display “Pressed Switch 2”.
8. If SW3 is pressed, display “Pressed Switch 3”.
9. Stop the program.

PROGRAM:


```
#include <REGX52.H>
#define LCD_PORT P0
#define EN P1_0
#define RS P1_2
#define RW P1_1
#define SW1 P2_0
#define SW2 P2_1
#define SW3 P2_2
#define beep P1_6
void Lcd_Initial(void);
void lcd_command(char);
void lcd_data(char);
void lcd_display(unsigned char, const char *);

void delay(unsigned int);
void main()
{
   P2 = 0x07;
   Lcd_Initial();
```


```
    lcd_display(0x80, "Press Any Switch");
    delay(100);
    while(1)
    {
      if(SW1 == 0)
      {
        while(!SW1);
        beep = 0;
        delay(25);
        beep = 1;
        lcd_display(0x80, "Pressed Switch 1");
      }
      if(SW2 == 0)
      {
        while(!SW2);
        beep = 0;
        delay(25);
        beep = 1;
        lcd_display(0x80, "Pressed Switch 2");
      }
      if(SW3 == 0)
      {
        while(!SW3);
        beep = 0;
        delay(25);
        beep = 1;
        lcd_display(0x80, "Pressed Switch 3");
      }
    }
}
void Lcd_Initial(void)
{
    lcd_command(0x30);
    lcd_command(0x30);
    lcd_command(0x30);
    lcd_command(0x38);
    lcd_command(0x01);
    lcd_command(0x06);
    lcd_command(0x0C);
}
void lcd_command(char value)
{
    RW = 0;
    RS = 0;
    EN = 1;
    LCD_PORT = value;
    delay(1);
```

```
    EN = 0;
}
void lcd_data(char value)
{
    RW = 0;
    RS = 1;
    EN = 1;
    LCD_PORT = value;
    delay(1);
    EN = 0;
}
void lcd_display(unsigned char locn, const char *dat)
{
    lcd_command(locn);
    while(*dat != '\0')
    {
        lcd_data(*dat);
        dat++;
    }
}
void delay(unsigned int count)
{
    int x, y;
    for(x = 0; x < count; x++)
        for(y = 0; y < 1275; y++);
}
```

OUTPUT:







RESULT:

Thus, the 8051 C programs for LCD interfacing and for LCD with switch control were executed and verified successfully.

EXP NO.8	ARM7 PROGRAMMING TO INTERFACE LED AND LCD
DATE: 28.08.26	

A. Interfacing ARM7 with LED using LPC2148.

AIM:

To demonstrate the interfacing of an LED and an LCD with the ARM7 LPC2148 processor, to control the LED and to display the given text on the LCD.

PROCEDURE:

1. Create a new project.
2. Select ARM → ARM7.
3. Enter the source code.
4. Save the program.
5. Add the source code to the target.
6. Compile and build the target.
7. Generate the HEX file.
8. Add the HEX file to the LPC2000 Flash Utility.
9. Transfer the HEX file to the ARM processor.
10. End the program.

PROGRAM:

```
#include <lpc21xx.h>

void delay(unsigned long val);


int main()
{
   IO1DIR = 0x00FF0000;

   while(1)
   {
      IO1SET = 0x00FF0000;
      delay(1000000);


      IO1CLR = 0x00FF0000;
      delay(1000000);
   }
}

void delay(unsigned long val)
{
   while(val > 0)
      val--;
}
```

PHILIPS LPC2000 FLASH UTILITY



OUTPUT:





B. ARM7 Programming for LCD Interface

AIM:

To interface an LCD with the ARM7 LPC2148 processor and display the given text on it.

PROCEDURE:

1. Create a new project.
2. Select ARM → ARM7.

3. Enter the source code.
4. Save the program.
5. Add the source code to the target.
6. Compile and build the target.
7. Generate the HEX file.
8. Add the HEX file to the LPC2000 Flash Utility.
9. Transfer the HEX file to the ARM processor.
10. End the program.


PROGRAM:

```
#include <LPC21xx.h>
#include "lcd4bit.h"
void Delay(unsigned long b)
{
   while(--b != 0);
}
void write_command(int cmd)
{
   IO1CLR |= 0x00f00000;
   IO1CLR |= 0x00040000;
   IO1CLR |= 0x00020000;
   IO1SET |= 0x00f00000 & cmd;
   IO1SET |= 0x00080000;
   Delay(30000);
   IO1CLR |= 0x00080000;
}
void write_data(int dat)
{
   IO1CLR |= 0x00f00000;
   IO1CLR |= 0x00040000;
   IO1SET |= 0x00020000;
   IO1SET |= 0x00f00000 & dat;
   IO1SET |= 0x00080000;
   Delay(30000);
   IO1CLR |= 0x00080000;
}
void lcd_data(char dat)
{
   write_data(dat << 16);
   write_data(dat << 20);
}
void lcd_command(char cmd)
{
   write_command(cmd << 16);
   write_command(cmd << 20);
}
void printlcd(char *CPtr)
```


```
{
   while(*CPtr != '\0')
   {
      lcd_data(*CPtr);
      CPtr++;
      Delay(20000);
   }
}
void init_lcd(void)
{
   IO1DIR |= 0x00FE0000;
   Delay(200000);
   write_command(0x30 << 16);
   Delay(100000);
   write_command(0x30 << 16);
   Delay(100000);
   write_command(0x30 << 16);
   Delay(100000);
   write_command(0x20 << 16);
   lcd_command(0x01);
   lcd_command(0x06);
   lcd_command(0x0c);
   lcd_command(0x80);
}

int main(void)
{
   init_lcd();
   printlcd("eCee LPC2148 DLB");
   lcd_command(0xC0);
   printlcd(" rhydolabz.com ");
   while(1);
}
```

PHILIPS LPC2000 FLASH UTILITY:



OUTPUT:



RESULT:

Thus, the ARM7 programs for LED and LCD interfacing were executed and verified successfully.

EXP NO.9	ARM7 PROGRAMMING FOR BUZZER INTERFACE
DATE: 11.09.26	

AIM:

To demonstrate how a buzzer is interfaced with the ARM7 processor.


PROCEDURE:

1. Create a new project.
2. Select ARM → ARM7.
3. Enter the source code.
4. Save the program.
5. Add the source code to the target.
6. Compile and build the target.
7. Generate the HEX file.
8. Add the HEX file to the LPC2000 Flash Utility.
9. Transfer the HEX file to the ARM processor.
10. End the program.


PROGRAM:

```
#include <lpc21xx.h>
void ext_interrupt(void) irq
{
   EXTINT = 0X02;
   IO0PIN = (IO0PIN ^ 0X00010080) & 0X00010080;
   VICVectAddr = 0x00000000;
}
void init_ext(void)
{
   PINSEL0 |= 0X20000000;
   EXTMODE = 0X02;
   EXTPOLAR = 0X02;
   VICVectAddr0 = (unsigned int)ext_interrupt;
   VICVectCntl0 = 0x0000002F;
   VICIntEnable = 0x00008000;
}
int main(void)
{
   IO0DIR = 0X00010080;
   init_ext();
   while(1);
}
```

PHILIPS LPC2000 FLASH UTILITY



OUTPUT:



RESULT:

Thus, the ARM7 program for buzzer interfacing was executed and verified successfully.

EXP NO.10	ARM7 PROGRAMMING FOR TIMER CONTROLLING OPERATION
DATE: 25.09.26	

AIM:

To demonstrate LED blinking with the help of a Timer of the ARM7 processor.


PROCEDURE:

1. Create a new project.
2. Select ARM → ARM7.
3. Enter the source code.
4. Save the program.
5. Add the source code to the target.
6. Compile and build the target.
7. Generate the HEX file.
8. Add the HEX file to the LPC2000 Flash Utility.
9. Transfer the HEX file to the ARM processor.
10. End the program.


PROGRAM:


```
#include <lpc21xx.h>
void timer0_delay_ms(unsigned int ms)
{
 T0TCR = 0x02;
 T0PR  = 14999;
 T0TCR = 0x01;
 while (T0TC < ms);
 T0TCR = 0x00;
}
int main(void)
{
 IO0DIR = 0x00000080;
 while (1)
 {
  IO0SET = 0x00000080;
  timer0_delay_ms(500);
  IO0CLR = 0x00000080;
  timer0_delay_ms(500);
 }
}
```

PHILIPS LPC2000 FLASH UTILITY:



OUTPUT:





RESULT:

Thus, the ARM7 program for LED blinking using the Timer was executed and verified successfully.

EXP NO.CBS-1	VIRTUAL LABS PROGRAMMING FOR DELAY GENERATION AND EFFECT OF CPU CLOCK
DATE: 27.06.26	

AIM

To study the effect of CPU clock on Microcontroller operations.

OBJECTIVE

To investigate the impact of varying the clock speed of a PIC18F4550 series microcontroller on the execution speed of instructions and to understand how CPU clock frequency affects the overall performance of the microcontroller.

PROCEDURE

1. Open the Virtual Labs simulator.
2. Select the required CPU Clock Frequency.
3. Enter the Total Delay between **1 ms and 1000 ms**.
4. Enter the ON Delay and OFF Delay such that:


$$\text{Total Delay} = \text{ON Delay} + \text{OFF Delay}$$


5. Click **SUBMIT**.
6. Select the required output pin.
7. Select the LED Configuration.
8. Click **GENERATE CODE**.
9. Click **COMPILE CODE**.
10. Click **EXECUTE CODE**.
11. The MIMIC window opens.
12. Connect the selected pin to the LED anode.
13. Connect the LED cathode to the resistor.
14. Click **Check Connection**.
15. If the connection is incorrect, click **Reset Connection** and reconnect.
16. Click **Run**.
17. Observe the LED blinking and square wave output.
18. Repeat the experiment with different clock frequencies.


SIMULATIONS:

SCENARIO – 1

INPUT PARAMETERS:









SCENARIO – 2

INPUT PARAMETERS:









SCENARIO – 3

INPUT PARAMETERS:










SCENARIO – 4

INPUT PARAMETERS:









SCENARIO – 5

INPUT PARAMETERS:







RESULT:

Thus, the effect of CPU clock frequency on the operation of the PIC18F4550 microcontroller was studied successfully. It was observed that increasing the clock frequency decreases instruction execution time, resulting in faster LED blinking and quicker program execution.

EXP NO.CBS-2	VIRTUAL LABS PROGRAMMING FOR I/O INTERFACING (LED AND SWITCH INTERFACING)
DATE: 03.07.26	

AIM

To write a program for LED blinking through a push button using the PIC18F4550 series microcontroller.

OBJECTIVE

To demonstrate the use of the PIC18F4550 microcontroller's GPIO (General Purpose Input Output) pins for interfacing an input device (push button switch) and an output device (LED). The experiment aims to understand how the microcontroller reads the state of a push button and controls the LED accordingly.


PROCEDURE


1. Open the Virtual Labs simulator.
2. Select the **Input Pin** for the Switch.
3. Select the **Output Pin** for the LED.
4. Select the **Switch Configuration**.
5. Select the **LED Configuration**.
6. Click **GENERATE CODE**.
7. Click **COMPILE CODE**.
8. Click **EXECUTE CODE**.
9. The MIMIC window opens.
10. Connect the selected Output Pin to the LED Anode.
11. Connect the LED Cathode to the resistor.
12. Connect the selected Input Pin to the Switch.
13. Click **Check Connection**.
14. If the connection is incorrect, click **Reset Connection** and reconnect.
15. Press and hold the Switch.
16. Observe the LED and square wave output.
17. Repeat the experiment with different pin configurations.


SIMULATIONS:

SCENARIO – 1

INPUT PARAMETERS:










SCENARIO – 2

INPUT PARAMETERS:










SCENARIO – 3

INPUT PARAMETERS:










SCENARIO – 4

INPUT PARAMETERS:









SCENARIO – 5

INPUT PARAMETERS:





RESULT:

Thus, the interfacing of a push button switch and an LED using the PIC18F4550 microcontroller was successfully studied. The GPIO pins correctly detected the switch input and controlled the LED output.

EXP NO.CBS-3	VIRTUAL LABS PROGRAMMING WITH ON-CHIP TIMERS/COUNTERS
DATE: 03.07.26	

AIM

To study programming with on-chip Timers/Counters using the PIC18F4550 microcontroller.

OBJECTIVE

- To understand the basic concepts of Timer and Counter.
- To study Timer0 of the PIC18F4550 microcontroller.
- To understand the interrupt structure of the PIC18F4550.
- To generate accurate delays using Timer0 and interrupts.


PROCEDURE


1. Select the Operating Frequency.
2. Select the Timer.
3. Select the Prescaler.
4. Select Enable Interrupt.
5. Enter ON Delay (in ms).
6. Enter OFF Delay (in ms).
7. Click GENERATE CODE.
8. Click COMPILE CODE.
9. Click EXECUTE CODE.
10. The MIMIC window opens.
11. Connect the output pin to the LED anode.
12. Connect the LED cathode to the resistor.
13. Click CHECK CONNECTION.
14. If the connection is incorrect, click RESET CONNECTION and reconnect.
15. Click RUN.
16. Observe the LED blinking and square wave output.
17. Click REFRESH to repeat the experimentSIMULATIONS


SIMULATIONS:

SCENARIO – 1

INPUT PARAMETERS:









SCENARIO – 2

INPUT PARAMETERS:









SCENARIO – 3

INPUT PARAMETERS:










SCENARIO – 4

INPUT PARAMETERS:










SCENARIO – 5

INPUT PARAMETERS:







RESULT:

Thus, programming with on-chip Timers/Counters using the PIC18F4550 microcontroller was studied successfully.