AURA | VISIBLE BREADBOARD WIRING | EXACT LABELED MODULE PADS

M1 ShillehTek INMP441 | M2 Adafruit PCM5102 #6250 | M3 MAX97220AEVKIT+

X symbols mark physical pads/contacts; green wires join them. Local V3V3/GND labels are common rails.

Nucleo CN7-16 3V3
V3V3
M1 VDD
M2 VIN
M2 FIL
M2 MU
M3 VDD
C1
100n
Nucleo CN7-20
GND
Nucleo CN10-20
M1 GND
M1 L/R
M2 GND
M2 G
M2 FM
GND
M2 DE
M3 GND
M3 INL+
M3 INR+
Nucleo CN10-30 PB13
I2S_BCK
M1 SCK
M2 BCK
Nucleo CN10-16 PB12
I2S_WS
M1 WS
M2 WSEL
M1 SD
MIC_SD
Nucleo CN10-28 PB14
R5
10k
GND
Nucleo CN10-26 PB15
DAC_DIN
M2 DIN
Nucleo CN10-23 PA8
AMP_EN
SW6
LATCHING MUTE
AMP_SHDN
M3 JU1 SHDN SIDE
M2 Lout
DAC_L
R1
47k
AMP_L_IN
M3 INL-
R2
10k
GND
M2 Rout
DAC_R
R3
47k
AMP_R_IN
M3 INR-
R4
10k
GND
V3V3
R6
10k
Nucleo CN7-28 PA0
ENC_A
SW1
ENCODER A
GND
COMMON GND
V3V3
R7
10k
Nucleo CN7-30 PA1
ENC_B
SW2
ENCODER B
GND
COMMON GND
V3V3
R8
10k
Nucleo CN7-32 PA4
ENC_SW
SW3
ENCODER PUSH
GND
COMMON GND
V3V3
R9
10k
Nucleo CN7-34 PB0
BTN1
SW4
BUTTON 1
GND
COMMON GND
V3V3
R10
10k
Nucleo CN10-24 PB1
BTN2
SW5
BUTTON 2
GND
COMMON GND

M3 HP_OUT is the jack. Dummy loads first. JU1 SHDN-side continuity and measured output are mandatory.

Conditional: only exact documented modules shown

Sheet: /
File: AURA_breadboard.kicad_sch

Title: AURA Breadboard Visible Wiring

Size: User	Date:	Rev: B
KiCad E.D.A. 9.0.8		Id: 1/1