

Table 35. Current consumption of peripherals (continued)

Peripheral	Bus	Consumption in $\mu\text{A}/\text{MHz}$
All APB peripherals	APB	39.1
AHB to APB bridge (2)		0.3
TIM3		3.6
RTCAPB		1.2
CRS		0.5
WWDG1		0.4
USART2		1.9
I2C1		0.9
I2C1 independent clock domain		2.5
I2C2		0.8
DBGMCU1		0.1
PWR		0.3
SYSCFG		0.5
TIM1		6.0
TIM2		4.8
SPI1		2.2
SPI1 independent clock domain		0.7
SPI2		1.7
USART1		2.4
USART1 independent clock domain		5.2
TIM14		1.4
TIM16		2.8
TIM17		2.7
ADC1		1.4
ADC1 independent clock domain		0.1
USB		4.0
All peripherals		65.4