



Table 17. Port C alternate function mapping (AF0 to AF7)

Port	AF0	AF1	AF2	AF3	AF4	AF5	AF6	AF7
PC0	-	USART4_RX	-	-	USART3_TX	-	-	-
PC1	-	USART4_TX	TIM15_CH1	-	USART3_RX	-	-	-
PC2	SPI2_MISO	-	TIM15_CH2	-	FDCAN1_RX	-	-	-
PC3	SPI2_MOSI	-	-	-	FDCAN1_TX	-	-	-
PC4	USART3_TX	USART1_TX	-	TIM2_ETR/ TIM2_CH1	FDCAN1_RX	-	-	-
PC5	USART3_RX	USART1_RX	-	TIM2_CH2	FDCAN1_TX	-	-	-
PC6	-	TIM3_CH1	-	TIM2_CH3	-	-	-	-
PC7	-	TIM3_CH2	-	TIM2_CH4	-	-	-	-
PC8	-	TIM3_CH3	TIM1_CH1	-	-	-	-	-
PC9	-	TIM3_CH4	TIM1_CH2	-	-	I2S_CKIN	-	-
PC10	USART3_TX	USART4_TX	TIM1_CH3	-	-	-	-	-
PC11	USART3_RX	USART4_RX	TIM1_CH4	-	-	-	-	-
PC12	TIM14_CH1	-	-	-	-	-	-	-
PC13	-	TIM1_ETR	TIM1_BKIN	-	-	-	-	-
PC14	USART1_TX	TIM1_ETR	TIM1_BKIN2	-	-	-	-	USART3_TX
PC15	OSC32_EN	OSC_EN	TIM1_ETR	TIM3_CH3	TIM15_BKIN	-	-	-

Table 18. Port C alternate function mapping (AF8 to AF15)

Port	AF8	AF9	AF10	AF11	AF12	AF13	AF14	AF15
PC0	-	-	-	-	-	-	-	-
PC1	-	-	-	-	-	-	-	-
PC2	-	-	-	-	-	-	-	-
PC3	-	-	-	-	-	-	-	-
PC4	-	-	-	-	-	-	-	-