

EE5203 L10 Lab Guide

UART — make the board talk, and listen - Basri Erdogan

Mission: Stream timestamped ADC readings to your PC at 10 Hz over the ST-LINK virtual COM port, then accept typed commands that change the LED duty — with the tick, the PWM, and the ADC all still running underneath.

Prepare before class

- ☐ Re-read the theory slides through “Assembling a command.”
- ☐ Bring your working L09 project (tick + PWM + ADC).
- ☐ Compute by hand: BRR for 115 200 baud with PCLK1 = 16 MHz.
- ☐ Know what `\r\n` is for, and what TXE means that TC does not.

Learning objectives

By checkoff time, you can:

1. configure USART2 for 8N1 and verify BRR against your own arithmetic;
2. transmit formatted telemetry paced by the L07 tick, without blocking;
3. receive by interrupt, re-arm correctly, and act in `main()`;
4. explain TXE, TC, RXNE, and ORE from the SFR view.

Hardware and files

Item	Required value
Board	Nucleo-F401RE — start from a copy of the L09 project, saved as L10_UART
Wiring	none — PA2/PA3 are wired to the ST-LINK virtual COM port on the board
USART2	115 200 baud, 8 data bits, no parity, 1 stop, TX and RX
Monitor	VS Code Serial Monitor, 115 200 baud, line ending <code>\r\n</code>

Close the Serial Monitor before flashing. An open port blocks the programmer, and the error message does not mention the monitor.

Configure in CubeMX

1. **Connectivity** → **USART2**: Mode **Asynchronous**; 115 200 / 8 / None / 1.
2. Confirm PA2 and PA3 turn green — alternate function **AF7**.
3. **System Core** → **NVIC**: enable **USART2 global interrupt**.
4. Generate, then find the AFR assignment for PA2/PA3 in the generated GPIO init before writing any code of your own.

Checkpoint A - The board speaks

In USER CODE BEGIN 2, after `MX_USART2_UART_Init()`:

```
const char *banner = "EE5203 L10 ready\r\n";
HAL_UART_Transmit(&huart2, (uint8_t *)banner, strlen(banner), 100);
```

Evidence for Checkpoint A: the banner appears in the Serial Monitor at 115 200 baud — and turns to garbage if you reopen the monitor at 9600. Show both. Then, in the SFR view, read `USART2->BRR` and compare it against the value you computed before class.

Checkpoint B - Telemetry at 10 Hz

No `HAL_Delay()`. Schedule from the L07 tick:

```
if ((g_ms - t_tx) >= 100U) {
    t_tx = g_ms;
    uint16_t raw = adc_read(ADC_CHANNEL_0);
    uint32_t mv = (raw * 3300u) / 4095u;

    char buf[48];
    int n = snprintf(buf, sizeof buf, "%lu,%u,%lu\r\n",
                     (unsigned long)g_ms, (unsigned)raw, (unsigned long)mv);
    HAL_UART_Transmit(&huart2, (uint8_t *)buf, (uint16_t)n, 100);
}
```

Evidence for Checkpoint B: ten lines per second, timestamps 100 ms apart, values tracking the knob. The LED keeps breathing and the servo keeps responding throughout — the telemetry is not stealing the loop. Copy thirty lines into a spreadsheet and plot raw against time.

Checkpoint C - The board listens

Arm the receiver once, then re-arm inside the callback:

```
volatile uint8_t rx_byte;
volatile char    rx_ring[64];
volatile uint8_t head = 0, tail = 0;

HAL_UART_Receive_IT(&huart2, (uint8_t *)&rx_byte, 1);    /* arm once */

void HAL_UART_RxCpltCallback(UART_HandleTypeDef *huart)
{
    if (huart->Instance == USART2) {
        rx_ring[head] = (char)rx_byte;
        head = (uint8_t)((head + 1) % 64);
        HAL_UART_Receive_IT(&huart2, (uint8_t *)&rx_byte, 1);    /* re-arm */
    }
}
```

Drain the ring in `main()`, assemble a line on `\r` or `\n`, and act:

Command	Effect
led on / led off	force the LED on or off
duty N	set the PWM duty, N in 0...999
anything else	reply ? unknown

Evidence for Checkpoint C: typed commands take effect immediately, a bad command is refused with a message, and telemetry keeps flowing while you type.

Checkpoint D - Break it on purpose

Evidence for Checkpoint D: set a breakpoint in `main()`, type several characters quickly while the core is halted, then resume. Show ORE set in `USART2->SR`, explain exactly which bytes were lost, and describe what the program must do to recover.

Individual extension

Pick one, predict first:

- **Non-blocking transmit:** replace `HAL_UART_Transmit` with `HAL_UART_Transmit_IT` and measure the difference with a GPIO pin toggled around the call.
- **Command with a reply:** add `get` which returns the current raw, mV, and duty on one line.
- **Baud sweep:** reconfigure to 9600 and to 230400, and record `BRR`, the actual baud, and the error at each. At which one does the telemetry rate stop fitting in the budget?

Acceptance checklist

- ☐ `.ioc`: USART2 asynchronous 8N1 at 115 200; PA2/PA3 AF7; USART2 NVIC on.
- ☐ `BRR` read from the SFR view matches your hand-computed value.
- ☐ Telemetry at a measured 10 Hz, `snprintf` (not `sprintf`), `\r\n` endings.
- ☐ Tick, PWM, and ADC all still working while telemetry streams.
- ☐ Receive is interrupt-driven and correctly re-armed; commands act in `main()`.
- ☐ A bad command is answered, not ignored.
- ☐ ORE demonstrated deliberately and explained.

Individual oral check

- What is `BRR` for your baud, and what actual rate does it produce?
- Why 10 bit times for one byte, not 8?
- What is the difference between `TXE` and `TC`, and when does it matter?
- Why must `HAL_UART_Receive_IT` be called again inside the callback?
- Why is `HAL_UART_Transmit` acceptable in `main()` but not in a callback?
- Your monitor shows consistent garbage. Give the two most likely causes.

Submit

Submit `main.c`, thirty captured telemetry lines, and one SFR-view screenshot showing `USART2->BRR` and `USART2->SR` with `ORE` set — plus your hand computation of `BRR` alongside the register value.

If you are stuck

Nothing at all: monitor on the right COM port? Right baud? Was the monitor open while flashing? **Consistent garbage:** baud mismatch — check both ends. **Exactly one byte then silence:** the receive interrupt was never re-armed. **Everything freezes when you type:** you used blocking `HAL_UART_Receive`. **Text stair-steps down the screen:** `\n` without `\r`. **Reception dies after a burst:** `ORE` is set and must be cleared.