KPS PUBLIC SCHOOLS • STUDENT TECH BENCH PROGRAM

Evaluator Key — managers only

Tier 3 — Advanced Repair

T3

System boards, daughterboards, heat sinks, liquid damage and full transplants.

In this guide

1 Answer key

2 Scoring the knowledge check

3 Running the practical exam

4 Awarding the certification

Rev 1.0 • October 2026

Keep this away from candidates. This key is for lead techs and managers. Don't leave it on the bench or share the file.

1 Answer key

#	Answer	Why
1	**C** — Daughterboard	Tier 3: motherboard, daughterboard, other major parts.
2	**A** — S1, S2, S3, known-good charger/battery, connectors reseated	Most dead boards turn out to be something cheaper.
3	**D** — System board or warranty	USB-C ports are soldered to the board on these models; no soldering at the bench.
4	**B** — The order printed on the heat sink	Even pressure protects the processor.
5	**B** — A pea-size dot, or the supplied pad	Too much is as bad as too little.
6	**D** — Power it on to test	Power through liquid causes the corrosion that kills boards.
7	**A** — On the system board	That's why board swaps need the lead tech.
8	**C** — Recovery if needed, re-enroll, full diagnostics	The device must be managed and fully working.
9	**D** — By its edges, ESD strap on	Static and pressure on chips damage boards.
10	**B** — Stop and escalate	Burn marks are a fire hazard and board-level work.
11	**C** — No, never	The processor can overheat in seconds.
12	**A** — The lead tech, using the fee schedule	Combinations can move a claim up a tier.
13	**A** — Shallow, under about 3 mm, away from the display cable	A deep pick cuts the cable or punctures the battery.
14	**C** — Corrosion: clean lightly or escalate	Corrosion keeps spreading if left.
15	**D** — Run the guide's verify checks and look inside before closing	Your check-off is the quality gate.

2 Scoring the knowledge check

- One point per question. Score 90% or better (14 of 15).
- Go over every missed question with the candidate, using the "Why" column, before they leave.
- A candidate who misses the pass mark can retake a different-order version after a week. Shuffle the answer letters when you reprint.

3 Running the practical exam

- Allow about 90 minutes. Set up the devices and any planted faults before the candidate arrives.
- Watch, don't coach. Step in only for safety.
- Mark each task Pass or Fail against the "To pass" column. All tasks must pass.
- Any automatic-fail item ends the exam immediately.

Task	Set up beforehand	Watch for
Board diagnosis	Given a "dead" device, decide whether the board is at fault.	Works through S1/S2/S3, charger, battery and connectors in order; correct conclusion; notes written.
Board or daughterboard swap	Swap a board (or daughterboard) on a practice unit.	Photos, ESD-safe handling, every connector reseated, device boots.
Heat sink	Remove and refit a heat sink with new paste.	Correct order, clean surfaces, correct amount, no power without the heat sink.
Liquid response	Talk through and demonstrate the first 10 minutes of a spill.	Force off, unplug, tent, battery out, no power-on, correct dry time.
Mentor check	Check off a planted student repair that has one hidden fault.	Finds the fault, explains it clearly, records the check-off correctly.

Automatic fail items. Powering on a board without a heat sink; Powering on a wet device; Handling a board without ESD protection; Ordering a board without the documented checks; Prying near a battery or display cable on a glued device.

4 Awarding the certification

- Check every requirement on the sign-off page is signed, including the prerequisite.
- Sign and date the candidate's sign-off page.
- In the portal, open Certifications, find the candidate, and click the box for this certification. It's recorded with your name and the date, and logged.
- If a certified student has a safety violation or repeated comebacks, remove the certification in the portal (click the check again) and note why in the audit log reason or the student's file.