

	1	2	3	4	5	6	7	8
A	Sparkfun.com			ST-Link V2 Programmer (typical <\$10 on Amazon)				
	PRT-10361 Connector			Signal Name				
	BLACK - PIN 6			Not Used				
	WHITE	PIN 5	RESET					
	WHITE	PIN 4	SWDIO					
B	WHITE	PIN 3	GND					
	WHITE	PIN 2	SWCLK					
	WHITE	PIN 1	Not Used					
C	Starting OpenOCD							
	sudo src/openocd -s tcl -f tcl/board/bluetailtech.cfg							
	Connect to openocd							
	telnet localhost 4444							
D	Halt Target							
	reset halt							
	Flash device with the firmware image							
	flash write_image erase p25rx_display.bin 0x8000000							
	Run The Firmware							
E	reset							
	Use up/down cursor keys to cycle through command history							
	1	2	3	4	5	6	7	8