

Lab 3 – I/O Programming

IS1200/IS1500 staff

2026

Contents

1	Introduction	2
1.1	Preparations	2
1.2	Resources and Reading Guidelines	2
2	Examination	3
3	Assignments	3
3.1	Assignment 1: Polling switches	3
3.2	Assignment 2: Timer	6
3.3	Assignment 3: Interrupts	7
3.4	Assignment 4: Surprise assignment	9
4	Version History	9

1 Introduction

Welcome to our third lab! In this laboratory exercise you will learn the fundamentals of input/output, timers, and interrupt programming. After finishing this lab, you should be able to

1. Write code to use simple input/output devices, such as switches and LEDs.
2. Write code to initialize and use devices with handshaking, such as a programmable timer.
3. Write code to initialize and handle interrupts.
4. Have a general understanding of how to read non-trivial technical manuals, data sheets, and C code.

1.1 Preparations

You must do the lab work in advance, except for the Surprise Assignment. The teachers will examine your skills and knowledge at the lab session.

Before your booked lab session, upload your solution files to the Canvas assignment **Lab 3 Files + Upload code** – the assignment page lists exactly which files. When you log in on the KTH lab computers at the session, your submitted code is downloaded automatically, and you explain it to the teachers there. If you modify your code during the session, you may re-upload it to Canvas; re-uploads end up in the “Files” section of your group page.

Booking opens one week before each lab session. We recommend that you book as soon as booking opens, and start preparing at least a week before the session.

You can ask for help any time before the lab session. There are several ways to get help; see the course website for details and alternatives.

During the lab session, the teachers work with examination as well as offering help. Make sure to state clearly that you want to *ask questions*, rather than being examined.

Sometimes, our teachers may have to refer help-seekers to other sources of information, so that other students can be examined.

1.2 Resources and Reading Guidelines

- Lectures 5 and 6.
- Exercise 2 (including the suggested solutions).
- Harris & Harris (2021) course book, chapters 9.2–9.4 (available online).
- **Note:** unlike the H&H board, which contains a built-in timer inside the processor, our DTEK-V board has this feature deliberately disabled. Hence, you must read the documentation on the timer (on the Canvas page) to understand how to program it and how to acknowledge interrupts from that source.
- See the course web page *Literature and Resources* for links and details. In particular, the documentation about the timer and the general-purpose I/O (which is what the buttons and switches are).

The file *lab3-files.zip* (containing the *labmain.c* template) is attached to the Canvas assignment **Lab 3 Files + Upload code**. You will also need your own code from Lab 1 and the board-support archive *time4riscv.zip*, attached to the Canvas assignment **Lab 1 Files + Upload code** (see Assignment 1 below).

2 Examination

Examination is for each assignment. Examining one assignment takes 5–15 minutes. Make sure to call the teacher immediately when you are done with an assignment.

Please state clearly that you want to be examined, rather than getting help.

The teacher checks that your program behaves correctly, and that your code follows all coding requirements and is easily readable. In particular, all assembly-language code must conform to the calling conventions for RISC-V (RV32IM) systems. Compile-time warnings are not acceptable.

The teacher will also ask questions, to check that your knowledge of the design and implementation of your program is deep, detailed and complete. Questions are answered *individually*: each of you must be able to answer on your own. When you write code, make detailed notes on your choices of algorithms, data structures, and implementation details. With these notes, you can quickly refresh your memory during examination, if some particular detail has slipped your mind.

You must be able to answer all questions. In the unlikely case that some of your answers are incorrect or incomplete, we follow a specific procedure for re-examination. This procedure is posted on the course website.

This lab is examined in three parts. You can only be examined on one part at a time.

- Part 1 – Assignment 1.
- Part 2 – Assignment 2.
- Part 3 – Assignment 3 and the Surprise Assignment.

When you pass a part, the teacher enters your grade in Canvas at the session. **Before you leave, immediately double-check under *Grades* that the teacher has registered your result** – if it is missing, tell the teacher right away.

Remember: upload your solution files to the Canvas assignment **Lab 3 Files + Upload code** *before* your booked session (the assignment page lists exactly which files). When you log in on the KTH lab computers, your submitted code is downloaded automatically – that is the code you present. If you modify it during the session, you may re-upload it to Canvas.

3 Assignments

Throughout all assignments, test your code continually by running it on the DTEK-V board.

3.1 Assignment 1: Polling switches

In this assignment, you will write code that (repeatedly) examines the values of one or more input bits. This is called *polling*, and is the simplest way to check input from a switch or push-button. You will also write code to send output-data to LEDs.

Parts (a) and (b) of this assignment are preliminaries, laying the foundation for your work.

a) Copy all your files from the first laboratory exercise (Lab 1) to a new directory and delete the *labmain.S* file. Next, copy and unzip the content of *lab3-files.zip* (attached to the Canvas assignment **Lab 3 Files + Upload code**) into the same directory. The *labmain.c* file from the third lab essentially does the same as the *timetemplate* function (from Lab 1) did, but in C code.

Note: you need to make the functions *time2string*, *tick*, *delay*, and *display_string* globally visible in the *timetemplate.S* file (with the *.globl* directive) – otherwise they cannot be called from C.

Note: in the *labmain.c* file, in the *main* function, you need to update the *delay* parameter to reflect what was set in your *timetemplate* function.

b) Open a Terminal window (or a WSL window on Windows). Change to the new directory and type the command

```
make
```

Then connect the DTEK-V board and type:

```
dtekv-run main.bin
```

Check that the code runs correctly on the DTEK-V board (that is, identical to your Lab 1 output). After these steps, you'll know that the board is working.

Parts (c) and (d) deal with output-data.

c) In the *labmain.c* file, add a function to turn the LEDs on or off. The LEDs' address is 0x04000000. Use a volatile pointer to write to this address. The DTEK-V board has 10 LEDs, which can be toggled on and off by setting the 10 least significant bits (LSBs) to either 1 or 0, respectively. For example, writing 0x7 (which is 0111 in binary) will toggle on the 1st, 2nd, and 3rd LEDs, and turn off the remaining ones.

- *Function prototype:* `void set_leds(int led_mask);`
- *Parameter:* `led_mask`, an integer where the 10 least significant bits correspond to the state of the corresponding LED.
- *Return value:* nothing.

d) In the *labmain.c* file, add code that runs at the start of your program. This code should increment the binary value displayed on the first 4 LEDs once each “second” has passed. Initialize the LEDs' value to 0, so that the LEDs show how many “seconds” have elapsed since the program started. The program should stop when all the first 4 LEDs are turned on simultaneously. You can use the function you created in part (c) to toggle the LEDs. Note that, at this stage, each “second” is an approximation and not an exact one.




Figure 1: Left: example of how the LEDs should be blinking at the beginning of your application. Right: a 7-segment display showing which bits control which LEDs (DP is controlled by bit 7).

e) Create a C function that sets the value to be shown on the 7-segment displays. There are six of these displays. The address of the first display is `0x04000050`, and each subsequent display has an offset of `0x10`. Therefore, the address of the last display is `0x040000a0`. *Hint:* writing '0' to a bit position lights up the LED.

- *Function prototype:* `void set_displays(int display_number, int value);`
- *Parameters:* `display_number` corresponds to the display the user wants to set; `value` corresponds to the value to display.
- *Return value:* nothing.

The remaining parts of Assignment 1 deal with input.

f) Create a C function that returns the status of the toggle-switches on the board. The toggles (or switches) are mapped to memory address `0x04000010`.

- *Function prototype:* `int get_sw(void);`
- *Parameter:* none.
- *Return value:* the ten least significant bits of the return value should contain data from the switches. SW1 corresponds to the least significant bit. All other bits of the return value must be zero.

g) Create a C function that returns the current status of the second push-button. The button is mapped to memory address `0x040000d0`. Note: the first push-button on the board is used to reset the board.

- *Function prototype:* `int get_btn(void);`
- *Parameter:* none.
- *Return value:* the least significant bit of the return value must correspond to the status of the second button.

h) After the start sequence (developed in part [d]), enter an infinite loop. In this infinite loop, you should count the seconds, minutes, and hours passed and display them on the 7-segment displays (use the previously developed *set_displays*). The two rightmost displays show the seconds, the middle two displays show the minutes passed, and the two leftmost displays show the hours passed.

Within the infinite loop, call *get_btn* to check if a button is pressed. If a button press is detected, read the switch values with *get_sw* and update the display as follows:

- The state of the two left-most (most significant) switches determines which pair of displays to update:
 - if the state is 01 (left switch down, right switch up), modify the second counter;
 - if the state is 10 (left switch up, right switch down), modify the minute counter;
 - if the state is 11 (both switches up), modify the hour counter.
- The value to be set is defined in binary by the state of the six right-most switches (the 6 least significant switches).

Example: if the two most significant switches are set to 10 (binary for 2), selecting the middle pair of displays (for minutes), and the least significant switches are set to 001111 (binary for 15), then the minutes should be updated to 15. Refer to the figure below for a visual explanation.

To show that you understand, use one of the remaining switches to exit the infinite loop and end the program.

Note: when running your code on the DTEK-V board, verify that you can set the seconds, minutes, and hours correctly.




Figure 2: Using the switches to select and set the seconds, minutes, and hours counters.

Questions for Assignment 1 The following questions aim to help you check that you understand the code well. At the examination, the teacher may choose to ask questions which are not on this list.

- How many “seconds” in theory have passed after the start sequence developed in part (d)?
- In the generated assembly code, in which RISC-V register will the return values from functions `get_btn` and `get_sw` be placed? You should be able to answer this question without debugging the generated assembly code.

3.2 Assignment 2: Timer

In this assignment, you will use a timer device. Timers are controlled directly by a very accurate pulse-generator (called a crystal oscillator). Because of this, timers can be used for very precise measurements of time. The resolution of these measurements depends on the pulse-frequency and is usually well into the sub-microsecond range. Some examples are:

- Measuring the interval between input-pulses from a sensor on a wheel, to calculate the speed of a vehicle.
- Examining the execution time of some part of a program, to determine if additional optimization could be useful.
- Repeating some action at precise intervals, such as updating the display of a clock every second. This is what you will do in the current assignment.

- a) Create a new directory *time4timer*. Copy all files from Assignment 1 into the new directory.
- b) In file *labmain.c*, in the *labinit* function, add code to initialize the timer for time-outs every 100 ms (that is, 10 time-outs per second). Remember that the DTEK-V board frequency is 30 MHz.

In file *labmain.c*, change the *main* function so that it never calls *delay*. Instead, insert code in the *main* function to test for the time-out event flag. If the flag indicates a time-out event, your code must reset the flag. Make the calls to *time2string*, *display_string*, *tick*, and the code for displaying the time on the 7-segment display conditional, so that they are only called in case of a time-out event. Run your code on the board and verify that the time-display is updated 10 times per second.

Note: the timer is memory-mapped to addresses 0x04000020–0x0400003F. Look up the timer documentation (on the Canvas homepage) to find out how to program the timer.

Note: don't let the call to *get_sw* depend on a time-out. The function *get_btn* can be called in every loop iteration. On the other hand, calling the display functions in every iteration would lead to unpleasant flickering.

- c) In file *labmain.c*, add a global counter *timeoutcount*. In function *main*, use the counter to count up to 10 time-out events. Change your code so that *time2string*, *display_string*, *tick*, and your code to display the time on the 7-segment display are only called once in 10 time-out events. Run your code on the board and verify that the time-display is updated once per second.

Questions for Assignment 2 The following questions aim to help you check that you understand the code well. At the examination, the teacher may choose to ask questions which are not on this list.

- When the time-out event-flag is a “1”, how does your code reset it to “0”?
- What would happen if the time-out event-flag was not reset to “0” by your code? Why?
- Which device-register (or registers) must be written to define the time between time-out events? Describe the function of that register (or of those registers).
- If you press BTN1 quickly, does the time update reliably? Why, or why not? If not, would that be easy to change? If so, how?

3.3 Assignment 3: Interrupts

In the previous assignments, you have used polling of input-data and polling of a timer event-flag. The downside of polling is that it keeps the processor busy, checking input and/or event flags.

With interrupts, the processor can perform any kind of useful computation instead. When input data changes, or when the timer event-flag goes on, ordinary computation is temporarily suspended; the processor starts executing an interrupt-service routine (ISR) instead.

However, the fact that ordinary program execution can be interrupted at any time makes it hard to debug problems related to interrupt programming. We will therefore limit this assignment to one source of interrupts: the timer event-flag.

Parts (a), (b), (c), and (d) of this assignment are preliminaries, laying the foundation for your work.

- a) Create a new directory *time4int*. Copy all files from Assignment 2 into the new directory.

b) In file *labmain.c*, add the following line near the beginning of the file:

```
int prime = 1234567;
```

c) In file *labmain.c*, change the *main* function to look like this:

```
int main ( void ) {
    labinit();
    while (1) {
        print("Prime: ");
        prime = nextprime( prime );
        print_dec( prime );
        print("\n");
    }
}
```

d) In file *labmain.c*, change the function *handle_interrupt* to include the code to display the time on the 7-segment hex display (1:h) as well as the *tick* function. Do not include your code to print the time to the terminal (*display_string*):

```
void handle_interrupt ( unsigned cause ) {
    /* Your code to display time on the 7-segment display */
    tick( &mytime );
}
```

In parts (e) and (f), you write code that will execute on an interrupt.

e) In file *labmain.c*, add code into the function *handle_interrupt* to acknowledge interrupts from the timer. Note that the function *handle_interrupt* should include the code that is called every time an interrupt occurs. It should not include the code that initializes the interrupt routine.

f) In file *labmain.c*, change function *handle_interrupt* to update and check the global counter *timeoutcount*, so that your code to display the time on the 7-segment display and the function *tick* are only called once in 10 invocations of *handle_interrupt*. This is similar to what you did in Assignment 2.

In parts (g) and (h), you write code to enable interrupts. All the other parts must be in place before interrupts are enabled.

g) In file *boot.S*, add a function *enable_interrupt* (at the end of the file) that enables interrupts and allows interrupts from the timer (remember to make the function globally visible).

h) In file *labmain.c*, add code to the function *labinit* that enables interrupts (see [g]), allows interrupts from the timer, and enables the timer to generate interrupts. **Note:** before enabling interrupts globally, all other initialization must be complete.

Questions for Assignment 3 The following questions aim to help you check that you understand the code well. At the examination, the teacher may choose to ask questions which are not on this list.

- When the time-out event-flag is a “1”, how does your code reset it to “0”?
- What would happen if the time-out event-flag was not reset to “0” by your code? Why?

- From which part of the code is the function *handle_interrupt* called? Why is it called from there?
- Why are registers saved before the call to *handle_interrupt*?
- Which device-register (or registers), and which processor-register (or registers) must be written to enable interrupts from the timer? Describe the functions of the relevant registers.

3.4 Assignment 4: Surprise assignment

During the lab session, each pair receives a surprise assignment on the parts of Lab 3 you have prepared. You solve the assignment *together as a pair* during the session and demonstrate the working result to the teacher; questions about it are answered *individually*. You must finish the surprise assignment during the session. The surprise assignment is demonstrated together with Assignment 3.

4 Version History

1.0 – First released version. 2015-09-28.

1.1 – Updated assignment 1d, specifying that `pic32mx.h` should not be used. 2015-09-29.

1.2 – Updated assignment 3e. Clarified the meaning of function `user_isr`. 2015-10-06.

1.3 – Clarified and condensed questions, and specified the parts explicitly. 2016-01-13.

1.4 – Ported to new DTEK-V board. 2024-06-30.

1.5 – Converted to $\text{\LaTeX}$; Canvas zip-submission procedure; surprise solved in pairs, questions individual. 2026.