

Campervan Electrical Wiring Cheat Sheet

Generated: 2025-06-13

This cheat sheet provides recommended wire sizes, fuses, and cable types for common campervan 12V and 24V electrical applications. Always verify exact current ratings and voltage drop using a calculator for long runs.

Application	Amp Range	Wire Size	Recommended Fuse
LED Lights	<1A	1.0 mm ² (17 AWG)	3A blade fuse
Water Pump	5-8A	2.0 mm ² (14 AWG)	7.5-10A blade
Fridge / Fan	5-10A	2.0-2.5 mm ²	10-15A blade
DC-DC Charger (30A)	30-40A	10-16 mm ²	40A MIDI
Solar Panel (400W)	~15A	4-6 mm ² PV Cable	15A inline
Inverter (3000W, 24V)	125A+	50-70 mm ²	300A ANL/MEGA
DC Fuse Box Feed	30-40A	6 mm ²	40A blade/MIDI
USB Outlets	3-5A	1.5 mm ²	5A fuse
Lighting Circuits	1-3A	1.0-1.5 mm ²	3A fuse

Notes:

- Wire size depends on run length. Increase size for longer runs (>5m).
- Use tinned copper marine cable for durability.
- Always fuse as close to the battery as possible.
- Use cable rated for at least 1.25x the expected current.