CODE N' CREATE / ELECTRICAL ENGINEERING

Tuesday Bell Ringer | Grades 9-10

Name: _____ Date: _____

4 questions • Show calculations when asked • Use your resistor color chart if needed

1. DECODE + VERIFY

RED – RED – BROWN – GOLD. A multimeter reads 232 Ω. Calculate the tolerance interval and determine whether the resistor passes.

2. DECODE + VERIFY

YELLOW – VIOLET – BROWN – GOLD. A meter reads 490 Ω. Calculate the interval and determine whether it passes.

3. ENCODE + VERIFY

Give four bands for 330 Ω ±5%. A meter reads 312 Ω. Is it within tolerance? Show the limits.

4. ENCODE + VERIFY

Give four bands for 1,000 Ω ±5%. A meter reads 1,040 Ω. Is it within tolerance? Show the limits.