Decode a resistor in three rows

NEW EXAMPLE • Green - Blue - Red - Gold • 4-band resistor

Required for every problem, in every grade: show all three rows below. Use your assignment’s own colors and values.

Read left to right; gold is last.

1 Set up the three rows

Green	Blue	Red	Gold
1st digit	2nd digit	Multiplier	Tolerance
5	**6**	**×100**	**±5%**

ROW 1: COLORS

Write the band colors in their order.

ROW 2: JOBS

Identify what each band represents.

ROW 3: VALUES

Match each color and job to the chart.

2 Combine, multiply, bring down

Combine the digits: 5 and 6 → 56

Multiply: 56 × 100 = 5,600 Ω

Bring down tolerance: 5,600 Ω ±5%

JOIN THE DIGITS

Join the digits.

USE THE MULTIPLIER

Multiply 56 by 100.

KEEP THE TOLERANCE

Keep ±5% with the final value.

3 Answer in full sentences

The resistor’s resistance is 5,600 ohms. The gold band indicates a tolerance of ±5%.

Every problem needs all three rows. Number each answer, show your calculations, and answer every part in full sentences with units. Do not rewrite the question.

For this example, identifying the tolerance percentage is enough.

Keep this format in your notebook.