220W – 250W SOLAR PANELS ARRANGEMENT FOR MPPT

No. OF PANELS	MODEL #: EXO-M-70	
	12V MAX. 1500W	24V MAX. 3000W
1	1 DIRECT	-
2	2-IN SERIES 1 GROUP	2-IN SERIES 1 GROUP
3	3-IN SERIES 1 GROUP	3-IN SERIES 1 GROUP
4	2-IN SERIES 2 GROUP	2-IN SERIES 2 GROUP
6	3-IN SERIES 2 GROUP	3-IN SERIES 2 GROUP
8	-	2-IN SERIES 4 GROUP
9	-	3-IN SERIES 3 GROUP
12	-	3-IN SERIES 4 GROUP
15	-	-

No. OF PANELS	MODEL #: EXO-M-100	
	12V MAX. 1500W	24V MAX. 3000W
1	1 DIRECT	-
2	2-IN SERIES 1 GROUP	2-IN SERIES 1 GROUP
3	3-IN SERIES 1 GROUP	3-IN SERIES 1 GROUP
4	2-IN SERIES 2 GROUP	2-IN SERIES 2 GROUP
6	3-IN SERIES 2 GROUP	3-IN SERIES 2 GROUP
8	-	2-IN SERIES 4 GROUP
9	-	3-IN SERIES 3 GROUP
12	-	3-IN SERIES 4 GROUP
15	-	-

310W – 380W SOLAR PANELS ARRANGEMENT FOR MPPT

No. OF PANELS	MODEL #: EXO-M-70	
	12V MAX. 1500W	24V MAX. 3000W
1	1 DIRECT	-
2	2-IN SERIES 1 GROUP	2-IN SERIES 1 GROUP
3	3-IN SERIES 1 GROUP	3-IN SERIES 1 GROUP
4	2-IN SERIES 2 GROUP	2-IN SERIES 2 GROUP
6	-	3-IN SERIES 2 GROUP
8	-	2-IN SERIES 4 GROUP
9	-	3-IN SERIES 3 GROUP
12	-	-

No. OF PANELS	MODEL #: EXO-M-100	
	12V MAX. 1500W	24V MAX. 3000W
1	1 DIRECT	-
2	2-IN SERIES 1 GROUP	2-IN SERIES 1 GROUP
3	3-IN SERIES 1 GROUP	3-IN SERIES 1 GROUP
4	2-IN SERIES 2 GROUP	2-IN SERIES 2 GROUP
6	-	3-IN SERIES 2 GROUP
8	-	2-IN SERIES 4 GROUP
9	-	3-IN SERIES 3 GROUP
12	-	-

سولر کنکشن:

سولر پینل اور MPPT کنٹرولر کے درمیان DC Circuit Braker لازمی لگائیں۔

سولر پینل سے کنکشن کے لئے صحیح تار کا انتخاب کرنے کیلئے مندرجہ ذیل چارٹ کا استعمال کریں۔ خیال رہے کہ صحیح تار کا استعمال نہ صرف MPPT کنٹرولر کی اچھی کارکردگی کیلئے ضروری ہے بلکہ حفاظتی لحاظ سے بھی انتہائی ضروری ہے۔

5 AMP - 7 AMP	4 MM
8 AMP - 15 AMP	6 MM
16 AMP - 30 AMP	10 MM

MPPT کنٹرولز کی بہتر کارکردگی کیلئے اس کے ساتھ کم از کم 4 اور زیادہ سے زیادہ 6 پینلز (550 Watt) کا استعمال کیجئے۔

