EXIT TICKET / REFLECTION

Check your understanding

Complete the actual lesson Exit Ticket before checking the answer.

Pipelining always reduces the number of stages required for an individual instruction.

How confident are you? Circle one: Confident / Getting there / Need help

Explain your choice, identifying one concept you can now use independently.

GREEN PEN — Correct and explain

Choose one mistake from your independent work. Write the correct method and explain precisely why your original answer was wrong.

Next step: revisit the model or a relevant revision-guide section if needed.

DO NOW — RECALL

Clock speed, cache and pipelining

Name: _____ Class: _____ Date: _____

1. What does the data bus transport during an instruction fetch?

2. Which register holds the address of the next instruction?

3. What is a dependency between tasks?

4. A rising-edge D flip-flop initially has Q=0. D changes 0→1 between edges, then 1→0 just before the next rising edge. What is Q immediately after that edge? Justify.

DO NOW — CHECK / OBJECTIVES

Correct and improve

Check page 1 in GREEN PEN. Write corrections in full.

1. Model answer

The instruction's contents from memory towards the CPU.

2. Model answer

PC.

3. Model answer

One operation cannot proceed until another result is ready.

4. Model answer

Q=0. The flip-flop samples D at the rising edge (D=0 at that instant); an earlier pulse between clock edges is not stored.

Vocabulary — know these terms

clock speed — Number of processor clock cycles each second.

cache — Small, fast memory that reduces some main-memory accesses.

pipeline — Overlap stages of several instructions.

hazard — Dependency or uncertainty disrupting smooth pipelining.

throughput — Amount of work completed in a given time.

YOU DO — INDEPENDENT PRACTICE

Questions · Part 2

Answer independently. Show code, calculations, a trace or justified reasoning as appropriate.

Question 3

Explain why doubling clock speed does not necessarily double an application's performance. Include one pipeline hazard.

YOU DO — INDEPENDENT PRACTICE

Questions · Part 1

Answer independently. Show code, calculations, a trace or justified reasoning as appropriate.

Question 1

State two processor performance factors and explain one way each might improve throughput.

Question 2

For a three-stage F–D–E pipeline with three independent instructions, write the stages occupied in cycles 1–5 and the completion cycle for I3.

NEW LEARNING

Read, annotate and explain

Different performance factors

Clock speed indicates cycles per second; multiple cores can execute independent work; cache reduces some slower-memory access.

Overlap pipeline stages

Without overlap, three three-stage instructions need nine stage slots; an ideal pipeline finishes them by the fifth cycle.

Account for hazards

Branches, data dependencies and waiting for memory may cause stalls or pipeline flushing; pipelining does not make every instruction individually three times faster.

Explain one step in your own words, using the correct technical terms.

I DO — WORKED EXAMPLE

Follow the worked method

Trace two independent instructions through a 3-stage F–D–E pipeline.

Predict first

Cycle 1 fetch I1. In cycle 2 decode I1 while fetching I2.

Explain and check

Cycle 3 executes I1 and decodes I2; I2 executes in cycle 4.

WE DO — GUIDED PRACTICE

Try → Discuss → Improve