EXIT TICKET / REFLECTION

Check your understanding

Complete the actual lesson Exit Ticket before checking the answer.

Copying only the correct result proves a misconception has been resolved.

How confident are you? Circle one: Confident / Getting there / Need help

Explain your choice, identifying one concept you can now use independently.

GREEN PEN — Correct and explain

Choose one mistake from your independent work. Write the correct method and explain precisely why your original answer was wrong.

Next step: revisit the model or a relevant revision-guide section if needed.

DO NOW — RECALL

Paper 1 targeted reteaching

Name: _____ Class: _____ Date: _____

1. What does CIR hold?

2. What is a foreign key?

3. What is DNS used for?

4. Simplify A∨(¬A∧B), showing working.

DO NOW — CHECK / OBJECTIVES

Correct and improve

Check page 1 in GREEN PEN. Write corrections in full.

1. Model answer

Current instruction.

2. Model answer

Reference to a key in another table.

3. Model answer

Resolving a domain name to an IP address.

4. Model answer

(A∨¬A)∧(A∨B)=A∨B.

By the end, you can…

- Diagnose specific Paper 1 misconceptions
- Correct numerical and technical explanations
- Transfer improved method to new questions

Vocabulary — know these terms

reteach — Address an identified knowledge gap.

transfer — Apply a method to changed values.

method mark — Credit for correct intermediate reasoning.

YOU DO — INDEPENDENT PRACTICE

Questions · Part 2

Answer independently. Show code, calculations, a trace or justified reasoning as appropriate.

Question 3

Student(ID,Name) contains (1,Ada),(2,Ben). Mark(ID,Score) contains (2,80). Write an INNER JOIN using Student.ID=Mark.ID to select Name and Score, and state the output row. [6]

YOU DO — INDEPENDENT PRACTICE

Questions · Part 1

Answer independently. Show code, calculations, a trace or justified reasoning as appropriate.

Question 1

In a simple sequential fetch-decode-execute cycle, PC initially holds 70 and memory location 70 contains the instruction LOAD 25. State MAR, MDR, CIR and the next PC value, and explain one action of the control unit. Assume no branch or interrupt. [6]

Question 2

Convert −18 to eight-bit two's complement and explain sign. [6]

NEW LEARNING

Read, annotate and explain

Identify

Identify exact lost mark or incorrect idea

Model

Study fresh model with different values

Apply

Try an independent unseen example

Evaluate

Record the correction for exam revision

Explain one step in your own words, using the correct technical terms.

I DO — WORKED EXAMPLE

Follow the worked method

A sequential fetch starts PC=120. Explain what MAR, MDR and CIR do.

Explain the method

MAR holds address, MDR transfers contents, and CIR holds instruction for decoding.

WE DO — GUIDED PRACTICE

Try → Discuss → Improve