Microcontrollers, flowcharts & programming

ENGINEERING WITH MR KELLY

Higher · Electronics & control · Worksheet

Name _____ Class _____ Date _____

By the end of this worksheet I can…

- ☐ draw flowcharts with start/stop, input, output, decision and loop symbols
- ☐ use fixed loops, continuous loops and conditional loops
- ☐ write programs using high, low, pause, if…then, for…next
- ☐ use subroutines, variables and analogue inputs in a program
- ☐ find faults in a program and correct them

I DO — Worked example

Read how a full-mark answer is built

A program is meant to loop continuously but stops after one cycle.

1 Identify the fault and write the correction. (2 marks)

Full-mark answer each ✓ is one mark

The program never returns to the start, so it stops after one cycle ✓. Add the line "goto main" at the end ✓.

Why marks are not awarded

"The loop is missing."

0 marks: no corrected line written.

WE DO — Guided practice

Use the starters and word bank to help you

A traffic light sequence must repeat 20 times then stop.

2 Describe how a fixed loop is used in the program. (2 marks)

Sentence starters

First, …

Next, … using a …

Word bank

program · surrounds · sequence · repeats

Tip: 2 marks = 2 separate, developed points.

YOU DO **On your own** No notes. Check your answers afterwards.

3 Quick check: tick one box for each.

a) Which symbol tests whether a switch is pressed?
☐ Parallelogram ☐ Rectangle ☐ Diamond ☐ Oval

b) Increasing the mark (on time) in a PWM signal makes a motor...
☐ Slower ☐ Faster ☐ Reverse ☐ Stop

c) "for b0 = 1 to 15 ... next b0" is a...
☐ Continuous loop ☐ Fixed loop ☐ Decision ☐ Delay

d) Which is an advantage of a microcontroller over a hard-wired circuit?
☐ Needs no software ☐ Fewer components, so more reliable ☐ Always cheaper than any IC ☐ Never needs a driver

4 Key terms: write the letter of the matching description next to each term.

1. **Sub-procedure**	____	**A** Parallelogram, e.g. "pin 7 on".
2. **ADC reading**	____	**B** Diamond with Y/N exits, used to test an input or a count.
3. **Decision symbol**	____	**C** Rectangle with a time and unit, e.g. "wait 2 s".
4. **Output symbol**	____	**D** Code called with gosub and ended with return.
5. **Delay symbol**	____	**E** Repeats a set number of times.
6. **Fixed loop**	____	**F** Vin ÷ Vref × 255

A flowchart uses different symbols.

5 Draw the flowchart symbol for a decision and for an output. (2 marks)

A program reads an LDR on an analogue input into a variable.

6 Describe how the program could switch on a lamp when the reading is below 80. (2 marks)

A flowchart switches on an LED on output 2 when a switch on input 0 is pressed, waits 3 seconds, then switches it off, and repeats.

7 Write a program for the flowchart. (4 marks)

Check and reflect

Mark your answers with the answer sheet. Go back to the checklist on the site and re-rate each “I can” statement above. Which one still needs work?