Pneumatics

National 5 · Mechanisms & structures · Worksheet

ENGINEERING WITH MR KELLY

Name _____ Class _____ Date _____

By the end of this worksheet I can…

- ☐ name pneumatic components and draw their symbols
- ☐ describe circuits with the correct terms: actuate, change state, outstroke, instroke
- ☐ identify AND and OR control in pneumatic circuits
- ☐ calculate force, pressure and area in N/mm²
- ☐ describe speed control and time delays with restrictors and reservoirs

I DO — Worked example

Read how a full-mark answer is built

A single-acting cylinder is controlled by a push-button 3/2 valve.

1 Describe the operation of the circuit. (3 marks)

Full-mark answer each ✓ is one mark

When the push button actuates the 3/2 valve, main air flows from port 1 to port 2 and the piston outstrokes ✓. When the button is released, the spring returns the valve ✓. Air in the cylinder exhausts through port 3 and the spring instrokes the piston ✓.

Why marks are not awarded

"Press the button, the valve opens, air goes in and pushes the piston out. Let go and it goes back."

1 mark at most: "opens", "pushes out" and "goes back" aren't the accepted terms.

WE DO — Guided practice

Use the starters and word bank to help you

Two 3/2 valves are piped in series to control a cylinder.

2 State the type of control and describe why it is used. (2 marks)

Sentence starters

1. …
2. …

Word bank

operator's · actuated · valves · safety · AND control · two-handed

Tip: 2 marks = 2 separate, developed points.

YOU DO **On your own** No notes. Check your answers afterwards.

3 Quick check: tick one box for each.

a) Two valves piped in series give...
☐ OR control ☐ AND control ☐ NOT control ☐ A time delay

b) A 12 mm diameter piston: area is about...
☐ 113 mm² ☐ 452 mm² ☐ 37.7 mm² ☐ 144 mm²

c) Which is an advantage of pneumatics?
☐ Very precise positioning ☐ No sparks, so safe near flammable materials ☐ Silent ☐ Larger forces than hydraulics

d) How many ports and states does a 5/2 valve have?
☐ 5 states, 2 ports ☐ 5 ports, 2 states ☐ 2 ports, 5 states ☐ 3 ports, 2 states

4 Key terms: write the letter of the matching description next to each term.

1. **Semi-automatic circuit**	____	**A** One cycle per press: a roller trip returns the piston.
2. **Fully automatic circuit**	____	**B** Air outstrokes; a spring instrokes.
3. **Single-acting cylinder**	____	**C** Air drives the piston both ways.
4. **Double-acting cylinder**	____	**D** 5 ports, 2 states; "changes state"; controls a double-acting cylinder.
5. **3/2 valve**	____	**E** 3 ports, 2 states; "actuated".
6. **5/2 valve**	____	**F** Roller trips at both ends keep it cycling.

A cylinder operating at 0.5 N/mm² has a piston area of 800 mm².

5 Calculate the outstroke force. (2 marks)

A press cylinder must outstroke slowly and smoothly.

6 Describe how the circuit can be modified. (2 marks)

A double-acting cylinder is controlled by a 5/2 pilot-operated valve and two 3/2 valves.

7 Describe what happens when valve A is actuated. (2 marks)

Check and reflect

Mark your answers with the answer sheet. Go back to the checklist on the site and re-rate each “I can” statement above. Which one still needs work?