

LBS 2190 DAYS/TA PM FORM

EQ#: _____ Unit: _____ SN# _____ WO# _____ Date: _____ PM Cycle: 2190 Days or each T/A

EQ	PM Item	Standard	Result	Comment
Cabinet & Aux Compartment	1 Appearance	Check for abnormal noise, dust, water, smoke, corrosion, cracks or inflammable vapors	PASS ☐ Abnormal ☐	
		Check for any abnormal signs of arcing, burning, melting, or discoloration on the busbar and insulator	PASS ☐ Abnormal ☐	
		Check gauges/meter	PASS ☐ Abnormal ☐	
		Check switches	PASS ☐ Abnormal ☐	
		Check indication lights	PASS ☐ Abnormal ☐	
		Check all label (Relay, Name tag, Arc flash, Testing/Calibration date and warning sign label)	PASS ☐ Abnormal ☐	
	2 wiring and Conduit	Check the wire and conduit entry seals	PASS ☐ Abnormal ☐	
	3 Grounding	Check that grounding conductors and terminals are securely connected	PASS ☐ Abnormal ☐	
	4 Ground Test	Ground resistance < 5 Ω	PASS ☐ Abnormal ☐ G: _____ Ω	
	5 Door lock and interlock	Ensure door locks, interlocks, and safety warning labels are intact and functional	PASS ☐ Abnormal ☐	
	6 Cleaning	Clean the stationary portion by wiping with a clean cloth. Clean insulation with a dry cloth, dry vacuum, or OSHA approved solvent	PASS ☐ Abnormal ☐	

LBS 2190 DAYS/TA PM FORM

EQ	PM Item	Standard	Result	Comment				
LBS	1	Mechanical Structure and Operating Mechanism	Lubricate mechanisms, contacts, and other moving components	PASS ☐ Abnormal ☐				
			Manually operate the switch (CLOSE/OPEN) three times; motion should be smooth without jamming	PASS ☐ Abnormal ☐				
			Check linkages, springs, and moving parts for adequate lubrication and signs of wear or fatigue	PASS ☐ Abnormal ☐				
			Test interlock functions between the main switch and the grounding switch (if equipped)	PASS ☐ Abnormal ☐				
	2	Internal Conductors and Contacts	Inspect main contacts for pitting, burning, or oxidation	PASS ☐ Abnormal ☐				
			Measure contact resistance of each phase 1. Each phase < 200 $\mu\Omega$ 2. Phase difference < 50 $\mu\Omega$	PASS ☐ Abnormal ☐ <table border="1" style="width: 100%; border-collapse: collapse;"> <tr> <td style="width: 33%;">A Phase</td> <td style="width: 33%;">B Phase</td> <td style="width: 33%;">C Phase</td> </tr> <tr> <td style="height: 20px;"></td> <td></td> <td></td> </tr> </table>	A Phase	B Phase	C Phase	
A Phase	B Phase	C Phase						
Examine insulators for cracks, tracking marks, or contamination.	PASS ☐ Abnormal ☐							
Insulation resistance test Megger 800M Ω (5KV test 60s)	PASS ☐ Abnormal ☐ Phase-Ground (M Ω): <table border="1" style="width: 100%; border-collapse: collapse;"> <tr> <td style="width: 33%;">A-G</td> <td style="width: 33%;">B-G</td> <td style="width: 33%;">C-G</td> </tr> <tr> <td style="height: 20px;"></td> <td></td> <td></td> </tr> </table>	A-G	B-G	C-G				
A-G	B-G	C-G						

Manager: _____ Engineer: _____ Review By: _____ Inspect By: _____