
POS RAIL LRS-150-24 #1 (21.6 V) -> LC -> LM1084-ADJ 17.0 V, soft start; OUT = +V, RTN = 0V





POS rail green

POS CROWBAR TL431 at 66K5 / 10K = 19.1 V -> PNP -> SCR gate; SCR 2N6505G across the rail




NEG RAIL LRS-150-24 #2 (21.6 V) -> LC -> LM1084-ADJ 17.0 V, soft start; OUT = 0V, RTN = -V





NEG rail green

NEG CROWBAR TL431 at 66K5 / 10K = 19.1 V -> PNP -> SCR gate; SCR 2N6505G across the rail



OUTPUT 7-way terminal to the NC7FD-LX on the PSU panel: 1 earth, 2-3 +V, 4-5 0 V, 6-7 -V (0 V not earthed here)



Two floating rails: LRS-150-24 -> LC -> LM1084-ADJ -> TL431/SCR crowbar
Generated by tools/gen_psu.py from psu_spec.md v0.2 (option B)

Sheet: /
File: psu.kicad_sch

Title: External PSU regulator board — goa console (+-17 V, 4 A per rail)

Size: User	Date: 2026-10-19	**Rev: 0.2**
KiCad E.D.A. 10.0.7		Id: 1/1