Build a Live Chicago CTA Wall Map

A Step-by-Step Guide for a Cheap ESP32 + WS2812B DIY Project

DIY Transit Electronics

August 14, 2026

Contents

1 Introduction **3**

2 Bill of Materials **3**

3 Step 1: Get the Data Feeds **4**
3.1 1.1 CTA Train Tracker API Key 4
3.2 1.2 CTA GTFS Static Data 5

4 Step 2: Generate the Station List **5**

5 Step 3: Design the Physical Map and Assign LED Indices **7**
5.1 3.1 Create or Obtain a Map 7
5.2 3.2 Mount the Map and Mark Holes 7
5.3 3.3 Number Every Station 7
5.4 3.4 Fill in the CSV 8

6 Step 4: Generate the Arduino Mapping Header **8**

7 Step 5: Prototype with a Few LEDs **9**

8 Step 6: Wire and Mount the Full LED Array **10**
8.1 6.1 Cut the LED Strip 10
8.2 6.2 Solder Extension Wires Between LEDs 10
8.3 6.3 Mount LEDs Behind the Map 10
8.4 6.4 Add Power Injection 10

9 Step 7: Connect the ESP32 and Power Supply **11**
9.1 Power Supply Notes 11

10 Step 8: Install and Configure the Firmware **11**
10.1 8.1 Install Arduino IDE and Libraries 11
10.2 8.2 Create the Sketch 12
10.3 8.3 Configure the Sketch 14
10.4 8.4 Upload and Test 14

11 Step 9: Finish the Frame **15**

12 Step 10: Calibration and Troubleshooting **15**
12.1 Common Issues 15
12.2 Improving Shared Station Behavior 15

13 Safety and Legal Notes **16**

14 Possible Cost-Saving Substitutions **16**

15 Conclusion **16**

A File Checklist **17**

B Complete Python Scripts **17**

C Complete Arduino Sketch **17**

1 Introduction

This guide describes how to build a framed wall map of the Chicago Transit Authority (CTA) "L" rail system where a small RGB LED at each station lights up when a train is approaching or has just departed that station. The data comes live from the official CTA Train Tracker API.

The build is intended to be as cheap as possible while still producing a reliable, attractive object. It uses:

- An ESP32 development board as the WiFi microcontroller.
- WS2812B addressable RGB LEDs, one per station.
- A printed or laser-cut schematic map mounted in a shadow box.
- A 5V power supply.
- Free software: Arduino IDE, Python, Inkscape or similar.

You should have basic soldering skills and be comfortable uploading code to an ESP32. This project is for **personal use**. The CTA map, logo, and data have copyright/trademark restrictions; do not sell the finished item without addressing licensing and API terms.

2 Bill of Materials

The total can be around $70–$140 depending on what you already own. The table below gives the recommended cheap parts.

Item	**Specification**	**Qty**	**Approx. Cost**	**Source**
ESP32 Dev Board	WROOM-32, USB-C or micro-USB, 30-pin or 38-pin	1	$4–$8	AliExpress, Amazon, eBay
WS2812B LED strip	30 LED/m, 5V, IP30 non-waterproof, 5m roll (150 LEDs)	1	$12–$20	AliExpress, Amazon
Power supply	5V DC, 10A, barrel jack or screw terminals	1	$10–$15	Amazon, AliExpress
Level shifter	74AHCT125 or 74HCT245 DIP	1	$0.50–$2	eBay, local electronics
330 Ω resistor	1/4 W, metal film or carbon	1	pennies	local or online
1000 μF capacitor	10V or higher electrolytic	1	$0.50	local or online
Hook-up wire	22 AWG solid core, multiple colors	5–10 m	$5	local or online
Heat shrink tubing	Assorted small diameters	1 pack	$3	local or online
Foam board or plywood	24×36 inch or larger	1	$3–$10	dollar store, art store, hardware store
Printed map	24×36 inch color print of a simplified CTA L map	1	$10–$25	local print shop, FedEx Office

Diffuser material	tracing paper, vellum, or thin white acrylic	1 sheet	$2–$8	art store or online
Frame/shadow box	24×36 inch or custom	1	$15–$40	IKEA, thrift store, craft store
Solder, flux, glue, tape	Misc consumables	—	$10–$15	local or online

Table 1: Cheap BOM for the CTA wall map. Prices are approximate and vary by region.

Tools You Will Need

- Soldering iron with fine tip
- Solder wire and flux
- Wire strippers
- Multimeter
- Hot glue gun or double-sided tape
- Computer with Arduino IDE
- USB cable for ESP32
- Hobby knife or scissors
- Ruler or straightedge

3 Step 1: Get the Data Feeds

3.1 1.1 CTA Train Tracker API Key

The live train positions come from CTA's official API. You need a free developer key.

1. Go to https://www.transitchicago.com/developers/traintracker/.
2. Register for a developer account if you do not have one.
3. Request access to the **Train Tracker API**.
4. You will receive an API key, usually a string of letters and numbers.

The key is free for non-commercial use. Read the terms of service. Do not share your key publicly.

3.2 1.2 CTA GTFS Static Data

You also need the static schedule and station data, provided in GTFS format.

- Download from: https://www.transitchicago.com/downloads/sch_data/google_transit.zip
- Extract the ZIP file somewhere on your computer.

The GTFS file contains `stops.txt`, `routes.txt`, `trips.txt`, and `stop_times.txt`, which we will use to build a station list.

4 Step 2: Generate the Station List

We need a list of every rail station with its CTA `stop_id`. The script below downloads the GTFS feed, filters for rail routes, and writes a CSV template.

Create a file named `prepare_gtfs.py`:

```
import urllib.request
import zipfile
import csv
import io
import os
from collections import defaultdict

GTFS_URL = "https://www.transitchicago.com/downloads/sch_data/
    google_transit.zip"
OUT_DIR = "cta_gtfs"
OUT_CSV = "stations_template.csv"

def download_gtfs():
    print("Downloading GTFS feed...")
    data = urllib.request.urlopen(GTFS_URL).read()
    with zipfile.ZipFile(io.BytesIO(data)) as z:
        z.extractall(OUT_DIR)
    print(f"Extracted GTFS to {OUT_DIR}")

def read_csv(filename):
    with open(filename, newline='', encoding='utf-8-sig') as f:
        return list(csv.DictReader(f))

def main():
    if not os.path.exists(os.path.join(OUT_DIR, "stops.txt")):
        download_gtfs()

    routes = read_csv(os.path.join(OUT_DIR, "routes.txt"))
    trips = read_csv(os.path.join(OUT_DIR, "trips.txt"))
    stop_times = read_csv(os.path.join(OUT_DIR, "stop_times.txt"))
    stops = read_csv(os.path.join(OUT_DIR, "stops.txt"))

    # Filter for rail routes. In CTA GTFS, route_type == 1 means subway/
        metro.
    rail_routes = [r for r in routes if r.get("route_type") == "1"]
```

```
    if not rail_routes:
        # Fallback: use known route short names.
        known = {"Red", "Blue", "Brn", "G", "Org", "Pink", "P", "Y"}
        rail_routes = [r for r in routes if r.get("route_short_name") in
            known]

    route_ids = {r["route_id"] for r in rail_routes}
    route_short_names = {r["route_id"]: r["route_short_name"] for r in
        rail_routes}

    # Map trip_id to route_id for rail trips only.
    trip_to_route = {}
    for t in trips:
        if t["route_id"] in route_ids:
            trip_to_route[t["trip_id"]] = t["route_id"]

    stop_to_routes = defaultdict(set)
    stop_id_to_name = {s["stop_id"]: s["stop_name"] for s in stops}

    # Iterate through stop_times. This may take a minute because the file
        is large.
    print("Scanning stop_times.txt...")
    for st in stop_times:
        route_id = trip_to_route.get(st["trip_id"])
        if route_id is not None:
            stop_id = st["stop_id"]
            stop_to_routes[stop_id].add(route_id)

    print(f"Found {len(stop_to_routes)} unique rail station IDs.")

    # Write CSV template. You will fill in led_index manually later.
    with open(OUT_CSV, "w", newline='', encoding="utf-8") as f:
        writer = csv.writer(f)
        writer.writerow(["line", "stop_id", "stop_name", "led_index"])
        for stop_id, routes_for_stop in sorted(stop_to_routes.items()):
            lines = [route_short_names[rid] for rid in routes_for_stop]
            writer.writerow([",".join(lines), stop_id, stop_id_to_name.get
                (stop_id, ""), ""])

    print(f"Wrote {OUT_CSV}")
    print("Open the CSV and fill in the led_index column.")

if __name__ == "__main__":
    main()
```

Listing 1: Python script to extract CTA rail stations from GTFS.

Run the script:

```
python prepare_gtfs.py
```

This creates `stations_template.csv` with columns:

```
line,stop_id,stop_name,led_index
```

```
Red,41090,Jarvis,
Red,41100,Morse,
...
```

5 Step 3: Design the Physical Map and Assign LED Indices

You need a physical map with one LED per station. A geographically accurate map will be too crowded downtown, so a schematic transit map is better.

5.1 3.1 Create or Obtain a Map

For a personal project you can trace a simplified CTA map, draw one in Inkscape, or use a map image for personal reference. Keep these points in mind:

- Leave enough space between Loop stations.
- Use a dark background; black or dark charcoal makes LED light pop.
- Mark each station with a small circle or dot.
- Do not use the official CTA logo if you might later sell the item.

A good size is 24×36 inches. You can print the map at a local print shop.

5.2 3.2 Mount the Map and Mark Holes

Attach the printed map to a rigid board such as foam board or thin plywood. Poke or drill a small hole at each station location. The holes should be slightly smaller than the LED package diameter, typically 8–10 mm for WS2812B 5050 LEDs.

5.3 3.3 Number Every Station

Starting at one end of the map, assign each station a unique integer LED index beginning at 0. Write the number next to each hole on the back of the board. This number is the `led_index` in the CSV.

Be systematic. A suggested order:

1. Red Line from Howard to 95th/Dan Ryan
2. Blue Line from O'Hare to Forest Park
3. Brown Line
4. Green Line
5. Orange Line
6. Pink Line
7. Purple Line
8. Yellow Line

9. Shared Loop stations only once, with one LED per physical station.

Make sure no two stations share the same index. The total should be around 145–146 unique stations.

5.4 3.4 Fill in the CSV

Open `stations_template.csv` in a spreadsheet program. For each row, enter the `led_index` that you assigned to that station. Save the file.

6 Step 4: Generate the Arduino Mapping Header

The ESP32 firmware needs a mapping from CTA `stop_id` to LED index. The script below reads your filled CSV and emits a C++ header file.

Create `make_mapping.py`:

```
import csv
import sys

def main(csv_file, output_header):
    rows = []
    max_led = -1

    with open(csv_file, newline='', encoding='utf-8') as f:
        reader = csv.DictReader(f)
        for row in reader:
            led_str = row.get("led_index", "").strip()
            stop_id = row.get("stop_id", "").strip()
            if led_str == "" or stop_id == "":
                continue
            led_index = int(led_str)
            rows.append((led_index, stop_id))
            max_led = max(max_led, led_index)

    if not rows:
        print("Error: no rows with led_index filled in.")
        sys.exit(1)

    rows.sort()

    with open(output_header, "w", encoding="utf-8") as f:
        f.write("#ifndef MAPPING_H\n")
        f.write("#define MAPPING_H\n\n")
        f.write(f"#define NUM_LEDS {max_led + 1}\n")
        f.write(f"const int stationCount = {len(rows)};\n\n")
        f.write("struct StationMap {\n")
        f.write("  const char* stopId;\n")
        f.write("  int ledIndex;\n")
        f.write("};\n\n")
        f.write("const StationMap stationMap[] = {\n")
        for led_index, stop_id in rows:
            f.write(f'  {{"{stop_id}", {led_index}}},\n')
        f.write("};\n\n")
```

```
        f.write("#endif\n")

    print(f"Wrote {output_header} with {len(rows)} stations, NUM_LEDS={max_led + 1}")

if __name__ == "__main__":
    if len(sys.argv) != 3:
        print("Usage: python make_mapping.py stations_template.csv mapping.h")
        sys.exit(1)
    main(sys.argv[1], sys.argv[2])
```

Listing 2: Python script to generate mapping.h from the filled CSV.

Run it:

```
python make_mapping.py stations_template.csv mapping.h
```

This creates `mapping.h`. An example of the first few lines:

```
#ifndef MAPPING_H
#define MAPPING_H

#define NUM_LEDS 145
const int stationCount = 145;

struct StationMap {
  const char* stopId;
  int ledIndex;
};

const StationMap stationMap[] = {
  {"41090", 0},
  {"41100", 1},
  // ... many more ...
};

#endif
```

Listing 3: Example generated mapping.h (fragment).

7 Step 5: Prototype with a Few LEDs

Before building the full map, test the electronics and firmware with a small strip of 5–10 LEDs.

1. Cut a short segment of WS2812B strip containing 5–10 LEDs.
2. Solder wires to the 5V, GND, and DIN pads on the input end of the strip.
3. Connect the ESP32 to the strip according to the wiring diagram in Section 9.
4. Install the required Arduino libraries.
5. Use the firmware in Section 10, but temporarily set `NUM_LEDS` to a small number for the test.

6. Upload the code and verify that the LEDs light up when you call `FastLED.show()`.
7. Do not proceed until the prototype works reliably.

8 Step 6: Wire and Mount the Full LED Array

8.1 6.1 Cut the LED Strip

You need one WS2812B LED per station. Cut the 5m strip into individual LED segments at the copper pads. The data direction is marked by arrows or `DIN` and `DOUT` labels.

- The input side has `DIN`, 5V, GND.
- The output side has `DOUT`, 5V, GND.
- You only use the `DIN` of the first LED and `DOUT` of each LED to the next `DIN`.

8.2 6.2 Solder Extension Wires Between LEDs

Because the LEDs must be placed at irregular station positions, you cannot use the strip as a continuous line. For each LED:

- Solder three wires to the LED's 5V, GND, and `DOUT` pads.
- Route those wires to the next LED's 5V, GND, and `DIN` pads.
- Use 22 AWG wire. Data wire can be thinner; power wires should be at least 22 AWG.
- Keep data wires reasonably short, ideally under 30 cm between LEDs. Use a 330 Ω resistor in series with the first data input to reduce ringing.
- Use heat shrink tubing to cover solder joints.

This is tedious but cheap.

8.3 6.3 Mount LEDs Behind the Map

Position each LED directly behind its station hole. Hot glue works well. Leave a gap of about 1–2 cm between the LED and the map surface so the light diffuses. You can use a spacer layer such as foam board strips or 3D-printed standoffs.

8.4 6.4 Add Power Injection

With 145 WS2812B LEDs, voltage drop along the power wires will cause color and brightness problems. Add power injection every 30–40 LEDs.

- Connect the 5V and GND from the power supply to the beginning of the LED chain.
- Run additional 5V and GND wires to points after LEDs 30, 60, 90, and 120.
- Do not connect data at these injection points; only power and ground.

9 Step 7: Connect the ESP32 and Power Supply

The ESP32 GPIO output is 3.3 V, but WS2812B data inputs officially expect 5 V logic. A 74AHCT125 level shifter converts 3.3 V to 5 V and prevents many flickering problems.

```
5V Power Supply (+) ----[1000uF cap]----> LED strip 5V bus
5V Power Supply GND (-) ------------------> LED strip GND bus

ESP32 3.3V -------------------------> 74AHCT125 VCC (pin 14)
ESP32 GND --------------------------> 74AHCT125 GND (pin 7)
ESP32 GPIO12 --> 330 ohm --> 74AHCT125 1A (pin 2)

74AHCT125 1Y (pin 3) ---------------> First LED DIN
74AHCT125 1OE (pin 1) --------------> GND

ESP32 GND --------------------------> LED strip GND bus
```

Listing 4: Wiring diagram with 74AHCT125 level shifter.

If you skip the level shifter, connect the ESP32 GPIO through a 330 Ω resistor directly to the first LED DIN. This often works for short chains, but if the first LED flickers or shows random colors, use the level shifter.

9.1 Power Supply Notes

- Use a 5V DC supply rated at least 4A for low brightness operation.
- A 10A supply is safer for full brightness and future expansion.
- Connect the 1000 μF capacitor across the 5V and GND terminals close to the LED strip. The capacitor side marked with a stripe or minus sign goes to GND.
- Do not power the LED strip from the ESP32's 5V pin.

10 Step 8: Install and Configure the Firmware

10.1 8.1 Install Arduino IDE and Libraries

1. Download and install the Arduino IDE from https://www.arduino.cc/en/software.
2. Add ESP32 board support. In Preferences, add the boards manager URL:

   https://raw.githubusercontent.com/espressif/arduino-esp32/gh-pages/package_esp32_index.json

   Then install `esp32` by Espressif Systems.
3. Install the following libraries from the Library Manager:
   - `FastLED`
   - `ArduinoJson`

10.2 8.2 Create the Sketch

Create a new Arduino sketch named `cta_wall_map`. Copy the code below into the sketch. Place the generated `mapping.h` file in the same sketch folder.

```
/*
  CTA Wall Map - ESP32 + WS2812B
  Fetches CTA Train Tracker positions and lights station LEDs.
  Requires mapping.h generated by make_mapping.py
*/

#include <WiFi.h>
#include <WiFiClientSecure.h>
#include <HTTPClient.h>
#include <FastLED.h>
#include <ArduinoJson.h>
#include "mapping.h"

// ---------- User configuration ----------
const char* ssid = "YOUR_WIFI_SSID";
const char* password = "YOUR_WIFI_PASSWORD";
const char* ctaApiKey = "YOUR_CTA_API_KEY";

#define LED_PIN 12
#define BRIGHTNESS 64        // 0-255, lower is safer/cheaper
const char* routeCodes = "red,blue,brn,g,org,pink,p,y";
// ----------------------------------------

CRGB leds[NUM_LEDS];
String apiUrl = "https://lapi.transitchicago.com/api/1.0/ttpositions.aspx?
    key="
                + String(ctaApiKey) + "&rt=" + String(routeCodes) + "&
                    outputType=json";

WiFiClientSecure client;
HTTPClient http;

int stationToLed(const char* stopId) {
  for (int i = 0; i < stationCount; i++) {
    if (strcmp(stationMap[i].stopId, stopId) == 0) {
      return stationMap[i].ledIndex;
    }
  }
  return -1;
}

CRGB lineColor(const char* line) {
  if (strcmp(line, "red") == 0) return CRGB(198, 12, 48);
  if (strcmp(line, "blue") == 0) return CRGB(0, 161, 222);
  if (strcmp(line, "brn") == 0) return CRGB(98, 54, 27);
  if (strcmp(line, "g") == 0) return CRGB(0, 155, 58);
  if (strcmp(line, "org") == 0) return CRGB(249, 70, 28);
  if (strcmp(line, "pink") == 0) return CRGB(226, 126, 166);
  if (strcmp(line, "p") == 0) return CRGB(82, 35, 152);
  if (strcmp(line, "y") == 0) return CRGB(249, 227, 0);
```

```
  return CRGB(255, 255, 255);
}

void connectWiFi() {
  Serial.print("Connecting to WiFi");
  WiFi.mode(WIFI_STA);
  WiFi.setAutoReconnect(true);
  WiFi.begin(ssid, password);
  unsigned long start = millis();
  while (WiFi.status() != WL_CONNECTED && millis() - start < 20000) {
    delay(500);
    Serial.print(".");
  }
  if (WiFi.status() == WL_CONNECTED) {
    Serial.println("\nWiFi connected. IP: " + WiFi.localIP().toString());
  } else {
    Serial.println("\nWiFi connection failed. Will retry in loop.");
  }
}

void fetchAndUpdate() {
  if (WiFi.status() != WL_CONNECTED) {
    connectWiFi();
    if (WiFi.status() != WL_CONNECTED) return;
  }

  client.setInsecure();  // Skip certificate validation; personal
     prototype only.
  http.begin(client, apiUrl);
  int httpCode = http.GET();

  if (httpCode == HTTP_CODE_OK) {
    // CTA response can be ~50-100KB. 128KB JSON buffer is safe on ESP32.
    DynamicJsonDocument doc(128 * 1024);
    DeserializationError err = deserializeJson(doc, http.getStream());

    if (!err) {
      FastLED.clear();
      JsonArray routeArray = doc["ctatt"]["route"].as<JsonArray>();

      for (JsonObject route : routeArray) {
        const char* line = route["@name"];
        JsonArray trains = route["train"].as<JsonArray>();

        for (JsonObject train : trains) {
          const char* nextStaId = train["nextStaId"];
          int ledIndex = stationToLed(nextStaId);
          if (ledIndex >= 0 && ledIndex < NUM_LEDS) {
            // Overwrites if multiple trains at same station.
            // Optional: add occupancy blending or cycling for shared
               stations.
            leds[ledIndex] = lineColor(line);
          }
        }
```

```
      }

      FastLED.show();
      Serial.println("Updated LEDs.");
    } else {
      Serial.print("JSON parse error: ");
      Serial.println(err.c_str());
    }
  } else {
    Serial.printf("HTTP error: %d\n", httpCode);
  }

  http.end();
}

void setup() {
  Serial.begin(115200);
  delay(100);

  FastLED.addLeds<WS2812B, LED_PIN, GRB>(leds, NUM_LEDS);
  FastLED.setBrightness(BRIGHTNESS);
  FastLED.clear();
  FastLED.show();

  connectWiFi();
}

void loop() {
  fetchAndUpdate();
  delay(15000); // CTA data updates roughly every 15-20 seconds
}
```

Listing 5: Complete ESP32 Arduino sketch for the CTA wall map.

10.3 8.3 Configure the Sketch

Edit the following lines in the sketch:

- `ssid` and `password` to match your WiFi network.
- `ctaApiKey` to your CTA Train Tracker API key.
- `LED_PIN` if you are using a different ESP32 GPIO pin. GPIO12 is a common choice, but avoid pins that conflict with boot modes.
- `BRIGHTNESS` to a value between 20 and 80 for low heat and low power.

10.4 8.4 Upload and Test

Select the correct ESP32 board and port in the Arduino IDE. Click Upload. Open the Serial Monitor at 115200 baud to see debug messages.

If everything works, the LEDs at the next stations of active trains should light in the appropriate line colors.

11 Step 9: Finish the Frame

1. Add a diffuser layer between the LEDs and the printed map. Tracing paper or thin white acrylic works well.
2. Mount the LED board inside a shadow box or deep frame.
3. Use foam board spacers to create a gap between the map and the LEDs so the light spreads evenly.
4. Bundle and secure excess wires on the back.
5. Drill a hole for the power cable and route the 5V supply outside the frame.
6. If the power supply is internal, ensure adequate ventilation and strain relief.

12 Step 10: Calibration and Troubleshooting

12.1 Common Issues

Symptom	**Likely Cause / Fix**
No LEDs light	Check power supply, common ground between ESP32 and LED strip, data direction.
First LED flickers or random colors	Use 74AHCT125 level shifter; shorten data wire; add 330 Ω resistor.
LEDs are dim or white-looking	Low power or voltage drop; add power injection; lower brightness.
API returns HTTP 403	Invalid or inactive API key; check key and API access.
JSON parse error	Increase `DynamicJsonDocument` size; check URL string.
WiFi disconnects	Move ESP32 closer to router; use `WiFi.setAutoReconnect(true)`.
Some stations never light	Check that `stop_id` in CSV matches CTA API `nextStaId`; check `led_index`.

Table 2: Basic troubleshooting table.

12.2 Improving Shared Station Behavior

Many Loop stations serve multiple lines. With one LED per station, only the last train written to the LED will be shown. Possible improvements:

- Cycle colors for shared stations every 800 ms.
- Add a second LED at major shared stations.
- Blend colors using an occupancy array.

For a first build, the simple override behavior is acceptable.

13 Safety and Legal Notes

- This project uses low voltage, but a 5V 10A supply can still melt wires if shorted. Use insulated connectors, avoid loose wires, and add a fuse if desired.
- Do not leave the device powered unattended until it has been tested for several hours.
- The CTA Train Tracker API is free for non-commercial use. Do not redistribute the data or use it for a commercial product without permission.
- CTA logos and official maps are protected. This guide is for personal/educational use.

14 Possible Cost-Saving Substitutions

- Use a 5V 2A phone charger and set `BRIGHTNESS` to 40 or below. This will likely work if you never display full white.
- Use cardboard and black spray paint instead of foam board and a printed map.
- Skip the frame initially; hang the map with command strips.
- Use individual WS2812B LEDs purchased in bulk if you can find them cheaper than a full strip.
- Use a NodeMCU or Wemos D1 Mini if you already have one, but the ESP32 is recommended for HTTPS and RAM.

15 Conclusion

You should now have a functional, live-updating CTA wall map. The build is inexpensive, educational, and visually striking. Once the basic version works, you can add features such as:

- A web portal for WiFi configuration.
- OTA firmware updates.
- A small OLED display showing train ETAs.
- Sound or vibration alerts.
- A custom PCB to replace point-to-point wiring.

Enjoy your build!

A File Checklist

Filename	Purpose
`prepare_gtfs.py`	Extract CTA rail stations from GTFS.
`stations_template.csv`	Station list with empty LED index column.
`make_mapping.py`	Generate `mapping.h` from filled CSV.
`mapping.h`	CTA `stop_id` to LED index mapping.
`cta_wall_map.ino`	ESP32 Arduino firmware.

Table 3: Files used in this project.

B Complete Python Scripts

The scripts are included in Listings 1 and 2. Save them with the exact filenames and run them as described.

C Complete Arduino Sketch

The Arduino sketch is included in Listing 5. Place it in a sketch folder with the generated `mapping.h`.