

**MCA01 – Due: Fri., Sept. 11, 2026, before 11:50 PM**

**Electrical and Computer Engineering Department  
University of Puerto Rico at Mayagüez**



**COMMUNICATIONS THEORY I  
MATLAB CLASS ASSIGNMENT 01 (MCA01)  
Modeling a Double Sideband Suppressed Carrier  
Communications System for Underwater Analog  
and Digital Acoustic Communications**

**By**

**<SXXXGPYY>**

**For**

**Prof. Domingo Antonio Rodríguez  
Electrical and Computer Engineering Department  
University of Puerto Rico at Mayagüez  
[domingo.rodriguez1@upr.edu](mailto:domingo.rodriguez1@upr.edu)**

**<260825>**

## **INTRODUCTION**

The main objective of this **MCA01** is to model a double sideband suppressed carrier communications system (**DSB-SC**) for the communication of **speech** and **DTMF** signals in an **underwater medium**. The **maximum frequency content** of all these signals is assumed to be  $F_V = 4000\text{Hz}$  and the “one-sided” **channel bandwidth** is said to be  $B = 14000\text{Hz}$ . A receiver **low-pass filter** must be designed to recover the signal  $x_r(t) \approx s(t)$  (see **Fig. 3**).

The channel itself is modeled as a composition of two basic systems, an **ideal, linear phase, low-pass filter**  $T_C$ , with **cut-off frequency**,  $f = F_L$ , and a noise signal **summing system**,  $T_N$ , where the channel underwater acoustics **noise signal**,  $n(t)$ , is added to the output of the linear phase filter  $T_C$ . This DSB-SC communications channel is given the name  $T_{CN} = T_{AM}$ . Thus, it is given by cascading the sub-systems,  $T_C$  and  $T_N$  (see **Fig. 2**).

The overall sampling frequency of the DSB-SC communications system must be set to a value greater than **twice the maximum frequency** (**Nyquist-Shannon sampling theorem**) content of the output of the demodulator. That is,  $F_S > 2(2f_c + F_V)$ , where  $f_c$  is the **carrier frequency** of the modulator (demodulator) and must be  $f_c = 8640$ . The input signal  $x_m(t)$  to the modulator is the sum of a “**wanted**” speech signal  $s(t)$  and an “**unwanted**” **interference signal**  $g(t)$ . After the demodulator, an ideal, linear phase, low-pass filter,  $T_L$  is used, with cut-off frequency  $F_M = 4000\text{Hz}$ , to recover the **speech or voice signal** or **DTMF** signal  $s(t)$  (see **Fig. 1**).

## **DESIGN PROJECT:**

Each group must work together modifying and running the **DSB-SC simulation** to complete and submit the MCA01.

- 01.-** Access and review **all** hyperlinks provided.  
**02.-** **Run** the given program, study **all** the graphs, and **observe** that the ideal, linear phase, **band-pass filter** **does eliminate** given interference signal  $g(t)$ .

$$g(t) = \cos(2\pi 4400t) + \cos(2\pi 4900t) + \cos(2\pi 5400t)$$

- 03.-** **Verify** that **channel filter** is an “all pass” :  $h_c(t) = \delta(t)$ .  
**04.-** **Verify** that **receiver’s band-pass filter** is:  $h_R(t) = \delta(t)$ .  
**05.-** **Change** the carrier frequency to  $f_c = 8640$ .  
**06.-** **Increase** value of **noise parameter factor**  $n_{ATT}$  by 40 dB, from  $\frac{1}{\sqrt[2]{24000}}$  to  $\frac{1}{\sqrt[2]{2.4}}$  to obtain about –4 dB **SNR** decrease in the channel output  $y_{co}(t)$ .  
**07.-** A linear phase, **low-pass filter**,  $T_L$ , with cut-off frequency  $F_V = 4000\text{Hz}$ , for the receiver was designed. A **figure of merit** for this assignment, is the **time-delay**,  $T_d = \left(\frac{M_L - 1}{2}\right) T_s$ , where  $M_L$  is the order of the filter and  $T_s = \frac{1}{F_s}$  is the overall **sampling time** or **sampling period** of the system. For this work, in order to enhance **impulse response function**, set the order to  $M_L = N_{low} = 1323$ .  
**08.-** **Generate:** 1) magnitude of the spectrum of the output signal  $y_{co}(t)$  of the channel, 2) the magnitude of the spectrum of the output signal  $y_d(t)$  of the demodulator, 3) the impulse response function  $h_L(t)$  of the receiver’s low pass filter, 4) the magnitude of its spectrum,  $H_L(f)$ , 5) the receiver’s output signal  $x_r(t)$ , and 6) the magnitude of its spectrum,  $X_r(f)$ .  
**09.-** **Select** a word or message, composed of a **symbol sequence**, and determine at the receiver the two **decimal digits** (**dits**) transmitted in this **digital communication**.  
**10.-** **Proceed** to calculate the information **baud rate** ( $D_r$  in symbols/second), **symbol-bit rate** ( $S_b$  in bits/symbol), the “info” **gross bit rate** ( $R_b$  in bits/second), and the **code rate** ( $C_r$  dimensionless), for **DTMF** digital communication operation.

**MCA01 – Due: Fri., Sept. 11, 2026, before 11:50 PM**

## **TAKE-HOME ASSIGNMENT GUIDELINES:**

**A.-** This take-home work does not require a written result. It requires for each student group to send a **.zip** folder with the following items provided in the list below. There should be **NOTHING else** inside the requested **.zip** folder:

- i.- Original, INEL4301\_SYYY\_GPZZ\_MCA01\_250825.docx
- ii.- Original, INEL4301\_SYYY\_GPZZ\_MCA01\_250825pdf
- iii.- Original, unaltered, **dtmfad.wav** and **star\_story.wav**
- iv.- Original, unaltered, **inel4301s000gp00mca01.m**
- v.- One modified **inel4301s000gp00sn00mca01.m** per student.

Refers to the class section number: **sxxx**

Refers to the student's group number: **gpyy**

**B.-** Name of **.zip** folder and the name of the **e-mail subject**:

**INEL4301\_SXXX\_GPYY\_MCA01**

**C.-** Send e-mail, with the correct **e-mail subject**, and **.zip** file, with appropriate name, to the following e-mail address:

[domingo.rodriquez1@upr.edu](mailto:domingo.rodriquez1@upr.edu)

## **STANDARD DEMERIT TABLE**

|                                                          |                 |
|----------------------------------------------------------|-----------------|
| <b>01.- MATLAB m-script file does NOT execute</b>        | <b>-05 pts.</b> |
| <b>02.- Correct script file NOT included</b>             | <b>-05 pts.</b> |
| <b>03.- Missing INEL4301_SYYY_GPZZ_MCA01_260825.docx</b> | <b>-03 pts.</b> |
| <b>04.- Missing INEL4301_SYYY_GPZZ_MCA01_260825.pdf</b>  | <b>-03 pts.</b> |
| <b>05.- Missing class section number sxxx</b>            | <b>-02 pts.</b> |
| <b>06.- Unzipped folder does NOT have same name</b>      | <b>-02 pts.</b> |
| <b>07.- Missing student's group number gpyy</b>          | <b>-05 pts.</b> |
| <b>08.- Missing or incorrect e-mail subject</b>          | <b>-05 pts.</b> |

**Late works will not be accepted!!!**

**MCA01 – Due: Fri., Sept. 11, 2026, before 11:50 PM**

```
%inel14301s000qp00sn00mca01
%Prof. Domingo Antonio Rodriguez
%Name of Student, sn01, DTMF_WORD, DITS, %XX of Contribution
%Name of Student, sn02, DTMF_WORD, DITS, %XX of Contribution
%Name of Student, sn03, DTMF_WORD, DITS, %XX of Contribution
%Name of Student, sn04, DTMF_WORD, DITS, %XX of Contribution
%Name of Student, sn05, DTMF_WORD, DITS, %XX of Contribution
%*****Prof. D. Rodriguez*****
%*****DSB-SC COMMUNICATIONS SYSTEMS AND GAUSSIAN NOISE*****
%*****ANALOG AND DIGITAL COMMUNICATIONS SIMULATIONS*****
%*****
clear all %Clear working space
close all
%*****
disp('*****')
disp('Begin Simulation for Underwater Communications.')
disp('*****')
%*****
%*****Wanted Signal Input/Output*****
%*****
[sig,Fs]=audioread('star_story.wav'); %Get overall sampling frequency
save dsig.txt sig -ascii %Save signal as dsig.txt file
load -ascii dsig.txt; %Load ascii file dsig.txt
wsiz=length(dsig); %Get the length of the "dsig" signal
%*****
%*****Parameter Setting*****
%*****
Ts=1/Fs; %Sampling time or temporal resolution
Nq=wsiz; %Number of samples of wanted signal
Vq=Nq*Ts; %Observation window or signal duration
fincq=1/Vq; %Frequency resolution of wanted signal
fkq=-(Fs/2):fincq:(Fs/2)-fincq; %Frequency axis of wanted signal
tq=0:Ts:Vq-Ts; %Time axis of wanted signal
%
fV=4000; %Cut-off frequency of wanted signal
Wn=(2*fV/Fs); %Normalized cut-off frequency
Lp=(1/567); %Proportionality factor
Nh=2*floor(Lp*Nq)+1; %Low-pass filter length
hL=fir1(Nh,Wn); %Impulse response of low-pass filter
dsigL=conv(dsig,hL); %Filtered wanted signal up to fV=4000 Hz
%
f1=4400; %Input interference frequency
f2=4900; %Input interference frequency
f3=5400; %Input interference frequency
g1=cos(2*pi*f1*tq); %Unwanted input signal
g2=cos(2*pi*f2*tq); %Unwanted input signal
g3=cos(2*pi*f3*tq); %Unwanted input signal
g=(1/80)*g1+(1/160)*g2+(1/240)*g3; %Sum of unwanted signals
gmax=max(g); %Maximum value of sum
g=transpose((1/gmax)*g); %Normalized interference signal
%*****
%*****SIGNALS AND SYSTEMS MODELING*****
fc=9900; %Carrier frequency
c=transpose((cos(2*pi*fc*tq))); %Carrier signal
wsig=dsigL(1:Nq,1); %Wanted input signal
xm=wsig+g; %Sum of wanted and unwanted signals
xc=xm.*c; %Modulated wanted signal plus interference
%*****
%*****BAND-PASS FILTER*****
Nb=1001; %Order of band-pass filter
```

## MCA01 – Due: Fri., Sept. 11, 2026, before 11:50 PM

```
Wb=[(2*4640)/Fs (2*12640)/Fs]; %Vector of normilized cut-off freqs.
hB=firl(Nb-1,Wb,'bandpass'); %Impulse response of band-pass filter
%*****
%*****CHANNEL INPUT SIGNAL*****
yci=conv(xc,hB); %Removal of unwanted interferences
Nyci=length(yci); %Order of channel input signal
tyci=0:Ts:(Nyci-1)*Ts; %Time axis for yci(t)
fryci=1/(Nyci*Ts); %Frequency resolution for Yci(f)
fayci=-(Fs/2):fryci:(Fs/2)-fryci; %Frequency axis of wanted signal
%*****
%*****CHANNEL NOISE*****
nsig=randn(size(yci)); %Generation of AWGN signal: noise signal
nnsig=(1/max(abs(nsig)))*nsig; %Normalized noise signal
nATT=sqrt(1/24000); %Noise attenuation about -44 dB SNR
nsig=nATT*nnsig; %Attenuated noise present in the channel
%*****
%*****CHANNEL OUTPUT*****
yco=yci+nsig; %Channel output signal with Gaussian noise
tqn=0:Ts:(length(yco)-1)*Ts; %New time axis for output signal
cn=transpose((cos(2*pi*fc*tqn))); %New carrier signal
yd=yco.*(2*cn); %Demodulation stage
%*****
%*****LOW-PASS FILTER*****
Nlow=663; %Designed low-pass filter order
Wlow=(2*fV)/Fs; %Normalized cut-off frequency
hlow=firl(Nlow-1,Wlow); %FIR low-pass impulse response function
taxis_hlow=0:Ts:(length(hlow)-1)*Ts;
fres_hlow=1/((length(hlow))*Ts);
faxis_hlow=(-Fs/2):fres_hlow:(+Fs/2)-fres_hlow;
%*****
%*****RECEIVER OUTPUT*****
xr=conv(yd,hlow); %Low pass filtering at the receiver
taxis_xr=0:Ts:(length(xr)-1)*Ts;
fres_xr=1/((length(xr))*Ts);
faxis_xr=(-Fs/2):fres_xr:(+Fs/2)-fres_xr;
%*****
%*****SPECTRA*****
fwsig=fft(wsig); %Spectrum of wanted signal (Fund. Reg.)
sfwsig=fftshift(fwsig); %Spectrum of wanted signal (Princ. Reg.)
asfwsig=abs(sfwsig); %Magnitude of spectrum of wanted signal
%
fxc=fft(xc); %Spectrum of modd. signal (Fund. Reg.)
sfxc=fftshift(fxc); %Spectrum of modd. signal (Princ. Reg.)
asfxc=abs(sfxc); %Magnitude of spectrum of modd. signal
%
fyci=fft(yci); %Spectrum of input signal (Fund. Reg.)
sfyci=fftshift(fyci); %Spectrum of input signal (Princ. Reg.)
asfyci=abs(sfyci); %Magnitude of spectrum of input signal
%
fyco=fft(yco); %Spectrum of output signal (Fund. Reg.)
sfyco=fftshift(fyco); %Spectrum of output signal (Princ. Reg.)
asfyco=abs(sfyco); %Magnitude of spectrum of output signal
%
fyd=fft(yd); %Spectrum of output signal (Fund. Reg.)
sfyd=fftshift(fyd); %Spectrum of output signal (Princ. Reg.)
asfyd=abs(sfyd); %Magnitude of spectrum of output signal
%
fnsig=fft(nsig); %Spectrum of noise signal (Fund. Reg.)
sfnsig=fftshift(fnsig); %Spectrum of noise signal (Princ. Reg.)
asfnsig=abs(sfnsig); %Magnitude of spectrum of noise signal
```

## MCA01 – Due: Fri., Sept. 11, 2026, before 11:50 PM

```
%
fhlow=fft(hlow); %Spectrum of IRF (Fund. Region)
sfhlow=fftshift(fhlow); %Spectrum of IRF (Princ. Region)
asfhlow=abs(sfhlow); %Magnitude of spectrum IRF
%
fxr=fft(xr); %Spectrum of xr(t) (Fund. Region)
sfxr=fftshift(fxr); %Spectrum of xr(t) (Princ. Region)
asfxr=abs(sfxr); %Magnitude of spectrum IRF
%*****PLOTS*****
plot(tq,wsig);
axis([0 (length(wsig)*Ts) min(wsig) max(wsig)]);
xlabel('Time in Seconds')
ylabel('Amplitude')
title('Wanted signal s(t) in the Time Domain')
grid
%
figure
plot(tq,g);
axis([0 (length(g)*Ts) min(g) max(g)]);
xlabel('Time in Seconds')
ylabel('Amplitude')
title('Interference signal g(t) in the Time Domain')
grid
%
figure
plot(tq,xm);
axis([0 (length(xm)*Ts) min(xm) max(xm)]);
xlabel('Time in Seconds')
ylabel('Amplitude')
title('Modulating signal xm(t) in the Time Domain')
grid
%
figure
plot(tq,xc)
axis([0 (length(xc)*Ts) min(xc) max(xc)]);
xlabel('Time in Seconds')
ylabel('Amplitude')
title('Modulated Signal xc(t)')
grid
%
figure
plot(ty,nn,nnsig)
axis([0 (length(nnsig)*Ts) min(nnsig) max(nnsig)]);
xlabel('Time in Seconds')
ylabel('Amplitude')
title('Normalized Noise Signal nn(t)')
grid
%
figure
plot(ty,yci)
axis([0 (length(yci)*Ts) min(yci) max(yci)]);
xlabel('Time in Seconds')
ylabel('Amplitude')
title('Channel Input Signal yci(t)')
grid
%
figure
plot(ty,yco)
axis([0 (length(yco)*Ts) min(yco) max(yco)]);
xlabel('Time in Seconds')
```

## MCA01 – Due: Fri., Sept. 11, 2026, before 11:50 PM

```
ylabel('Amplitude')
title('Channel Output Signal yco(t)')
grid
%
figure
plot(fkq,asfwsig)
xlabel('Frequency in Hertz')
ylabel('Magnitude')
title('Magnitude of Spectrum S(f) of Wanted Signal s(t)')
grid
%
figure
plot(fkq,asfxc)
xlabel('Freq in Hertz')
ylabel('Magnitude')
title('Magnitude of Spectrum Xc(f) of Modulated Signal xc(t)')
grid
%
figure
plot(fayci,asfyci)
xlabel('Freq in Hertz')
ylabel('Magnitude')
title('Magnitude of Spectrum Yci(f) of Channel Input Signal yci(t)')
grid
%
figure
plot(fayci,asfyco)
xlabel('Frequency in Hertz')
ylabel('Magnitude')
title('Magnitude of Spectrum Yco(f) of Channel Output Signal yco(t)')
grid
%
figure
plot(fayci,asfyd)
xlabel('Frequency in Hertz')
ylabel('Magnitude')
title('Magnitude of Spectrum Yd(f) of Demodulator Output yd(t)')
grid
%
figure
plot(taxis_hlow,hlow);
axis([0 (length(hlow)*Ts) min(hlow) max(hlow)]);
xlabel('Time in Seconds')
ylabel('Amplitude')
title('Impulse Response Function of Receiver's Low-Pass Filter')
grid
%
figure
plot(faxis_hlow,asfhlow)
xlabel('Frequency in Hertz')
ylabel('Magnitude')
title('Magnitude of Spectrum of Impulse Response Function hlow(t)')
grid
%
figure
plot(taxis_xr,xr);
axis([0 (length(xr)*Ts) min(xr) max(xr)]);
xlabel('Time in Seconds')
ylabel('Amplitude')
title('Receiver's Low-Pass Filter Output Signal xr(t)')
```



## MCA01 – Due: Fri., Sept. 11, 2026, before 11:50 PM

```
grid
%
figure
plot(faxis_xr,asf_xr)
xlabel('Frequency in Hertz')
ylabel('Magnitude')
title('Magnitude of Spectrum of Receiver''s Output x_r(t)')
grid
%
%*****OUTPUTS*****
sound(wsig,Fs) %Sound of Wanted Signal
disp('Sound of Wanted Signal')
pause(20)
sound(g,Fs) %Sound of Interference Signal
disp('Sound of Interference Signal')
pause(20)
sound(xm,Fs) %Sound of Modulating Signal
disp('Sound of Modulating Signal')
pause(20)
sound(xc,Fs) %Sound of Modulated Signal
disp('Sound of Modulated Signal')
pause(20)
sound(yci,Fs) %Sound of Channel's Input Signal
disp('Sound of Channel''s Input Signal')
pause(20)
sound(yco,Fs) %Sound of Channel's Output Signal
disp('Sound of Channel''s Output Signal')
pause(20)
sound(xr,Fs) %Sound of Channel's Output Signal
disp('Sound of Receiver''s Output Signal')
%*****
disp('*****')
disp('Simulation ended succesfully.')
disp('*****')
```