

Adding and Subtracting in Scientific Notation

Teacher's Edition

The Period

MA.8.NSO.1.5 Add, subtract, multiply and divide numbers expressed in scientific notation with procedural fluency.

Must Add and subtract numbers written in scientific notation with procedural fluency, and write every answer with a coefficient at least 1 and less than 10.

Must not The two exponents stay within 2 of each other — that is this benchmark's own limit. Multiplication and division are 4.02-03; significant digits are 4.04.

Target I can add and subtract two numbers written in scientific notation, and write the answer in scientific notation.

MTR **MTR.5.1** — Notes I · **MTR.6.1** — Boards 3 and 4 · **MTR.4.1** — Board 6

Segment	Slides	Time
Settle in; post the learning target	1	1 min
Warm-Up	2-3	5 min
Notes	4-6	11 min
Example 1	7-8	3 min
Your Turn	9-10	3 min
Example 2	11-12	3 min
Your Turn	13-14	3 min
Whiteboards	15-32	13 min
Independent Set	33	6 min
IXL	34	5 min
Total		53 min

Say these three things out loud today

1. The powers of ten have to match before a single digit is added. That is the whole lesson.
2. The power of ten is a label, like the word thousands. You never add the label.
3. When you finish, look at the coefficient. If it is not between 1 and 10, you are not done.

Slide by Slide

1. **Adding and Subtracting in Scientific Notation.** Post the learning target.
2. **Warm-Up — On your own. Four minutes. No notes.** Q4 is today's lesson in miniature.
3. **Warm-Up — Answers.** Reveal. 1. 6.2×10^{-4} 2. 4,000 3. 12 4. 1.69
4. **Notes — Copy the table.** You can only add things that are the same size. Ten-thousands add to ten-thousands, and the label never changes.
5. **Notes.** The power of ten is a label. Six thousands plus two thousands is eight thousands — you never add the word thousands.
6. **Notes.** The exponents are never added. Adding 10 to the fifth and 10 to the third does not make 10 to the eighth — it does not make a power of ten at all.
7. **Example 1 — Same power, and the answer is not finished.** SPOKEN ONLY.
8. **Example 1 — Worked.** Add the coefficients, keep 10^7 , then repair.
9. **Your Turn — Same steps, your numbers. Boards up when done.** Same shape with negative exponents.
10. **Your Turn — Answer.** Reveal; name what a wrong board most likely did (see the note above).
11. **Example 2 — Different powers, and a subtraction.** SPOKEN ONLY.
12. **Example 2 — Worked.** Rewrite 4.5×10^5 over 10^6 — exponent up one, point one place left — and the subtraction becomes ordinary.
13. **Your Turn — Same steps, your numbers. Boards up when done.** The exponents are two apart — the widest gap this benchmark allows.
14. **Your Turn — Answer.** Reveal; name what a wrong board most likely did (see the note above).
- 15-16. **Board 1.** $(3.2 \times 10^5) + (4.1 \times 10^5) \rightarrow 7.3 \times 10^5$ 7.3×10^{10} — the exponents were added as well as the coefficients [B1G-M 8.NSO.1.5 misconception: exponents added]; 1.312×10^{11} — the numbers were multiplied [8.NSO.1.5: the operation is addition]
- 17-18. **Board 2.** A stadium sold 4.2×10^4 tickets on Friday and 3.5×10^4 on Saturday. Each ticket cost 38 dollars. How many tickets were sold on the two days? $\rightarrow 7.7 \times 10^4$ The ticket price of 38 dollars is not needed. anything built from 38 — the unneeded figure was used [the question asks for a count, not a cost]; 7.7×10^8 — the exponents were added [B1G-M 8.NSO.1.5 misconception]
- 19-20. **Board 3.** $(6 \times 10^{-5}) + (7 \times 10^{-5}) \rightarrow 1.3 \times 10^{-4}$ 13×10^{-5} — right value, but 13 is not less than 10 [B1G-M 8.NSO.1.5 named misconception: leaving 12×10^9 instead of 1.2×10^{10}]; 1.3×10^{-10} — the exponents were added
- 21-22. **Board 4.** $(5.6 \times 10^8) - (4.9 \times 10^8) \rightarrow 7 \times 10^7$ 0.7×10^8 — right value, but 0.7 is not at least 1 [8.NSO.1.5: the coefficient satisfies $1 \leq a < 10$]; 1.05×10^9 — added instead of subtracting
- 23-24. **Board 5.** $(1.3 \times 10^3) + (3.4 \times 10^5)$. Which is the sum? $\rightarrow C - 3.413 \times 10^5$ (A) the coefficients were added without matching the powers of ten first [8.NSO.1.5: the powers must match]; (B) the coefficients were added and the exponents were added [B1G-M 8.NSO.1.5 named misconception: $(1.3 \times 10^3) + (3.4 \times 10^5) = 4.7 \times 10^8$]; (D) 1.3×10^3 was rewritten as 0.13×10^5 — the decimal point moved one place too few [8.NSO.1.5: the point moves as many places as the exponent changes] Split (no option near two-thirds)? Sixty seconds, convince your neighbour, re-vote, then reveal.

- 25-26. Board 6.** $(2.5 \times 10^6) + (9.8 \times 10^6)$. Which is the sum, written in scientific notation? → **$D - 1.23 \times 10^7$** (A) equal in value, but 12.3 is not less than 10 [B1G-M 8.NSO.1.5 named misconception: leaving 12×10^9 instead of 1.2×10^{10}]; (B) the exponents were added as well as the coefficients [8.NSO.1.5: the power of ten does not change]; (C) the coefficient was repaired but the exponent was not raised [8.NSO.1.5: point one place left, exponent up one] Split (no option near two-thirds)? Sixty seconds, convince your neighbour, re-vote, then reveal.
- 27-28. Board 7.** $(7.8 \times 10^{-2}) - (6.4 \times 10^{-3})$ → **7.16×10^{-2}** 1.4×10^{-2} — the coefficients were subtracted without matching the powers [8.NSO.1.5]; 7.16×10^{-5} — the exponents were added, $-2 + (-3)$ [8.NSO.1.5: the power of ten is a label, not a term]
- 29-30. Board 8.** $(4.5 \times 10^6) + (n \times 10^6) = 1.02 \times 10^7$. What is the value of n? → **$n = 5.7$** -3.48 — the target was not rewritten over 10^6 before subtracting [8.NSO.1.5: match the powers first]; 5.7×10^6 — the blank holds a coefficient, not a whole term
- 31-32. Board 9.** Devon writes $(1.3 \times 10^3) + (3.4 \times 10^5) = 4.7 \times 10^8$. Name the two mistakes he made, and give the correct sum. → **3.413×10^5** 'he added wrong' — no mistake is actually named [the item asks which two]; 4.7×10^5 — the exponent mistake was caught and the matching mistake was not
- 33. Independent Set — Six questions. On your own, in writing.** Hand out the Independent Set; the same six questions are on the board.
- 34. IXL — Last five minutes.** IXL: every listed skill is required, SmartScore 67.

Misconceptions to Watch

- Board 1.** 7.3×10^{10} — the exponents were added as well as the coefficients [B1G-M 8.NSO.1.5 misconception: exponents added]
- Board 2.** anything built from 38 — the unneeded figure was used [the question asks for a count, not a cost]
- Board 3.** 13×10^{-5} — right value, but 13 is not less than 10 [B1G-M 8.NSO.1.5 named misconception: leaving 12×10^9 instead of 1.2×10^{10}]
- Board 4.** 0.7×10^8 — right value, but 0.7 is not at least 1 [8.NSO.1.5: the coefficient satisfies $1 \leq a < 10$]
- Board 5.** the coefficients were added without matching the powers of ten first [8.NSO.1.5: the powers must match]
- Board 6.** equal in value, but 12.3 is not less than 10 [B1G-M 8.NSO.1.5 named misconception: leaving 12×10^9 instead of 1.2×10^{10}]
- Board 7.** 1.4×10^{-2} — the coefficients were subtracted without matching the powers [8.NSO.1.5]
- Board 8.** -3.48 — the target was not rewritten over 10^6 before subtracting [8.NSO.1.5: match the powers first]
- Board 9.** 'he added wrong' — no mistake is actually named [the item asks which two]
- Materials** Whiteboards and markers. Calculators are allowed on everything; entering $6E-5 + 7E-5$ and reading $1.3E-4$ back off the display is worth thirty seconds at whiteboard 3.