
Adiabatic Gate Teleportation

Warning! **Warning!**

Dave Bacon
Department of Computer Science & Engineering
University of Washington, Seattle, WA USA

Warning! **Warning!**



[joint work with Steve Flammia (Perimeter),
Alice Neels (Washington), Andrew Landahl (Sandia Labs)]

8th Symposium on Topological Quantum Computing, Zurich 29th-31st August 2009

Zurich



Seattle



Newsweek


The Complete List: The Top 100 Global Universities

18. University of Toronto
19. Cornell University
20. University of Chicago
21. Swiss Federal Institute of Technology in Zurich
22. University of Washington at Seattle
23. University of California at San Diego
24. Johns Hopkins University
25. University College London

Huh?



ENIAC, 1946



- 17,468 vacuum tubes
- 7,200 crystal diodes
- 1,500 relays
- 70,000 resistors
- 10,000 capacitors
- ~5,000,000 hand-soldered joints

~ one vacuum tube failure / day
(equivalent to ~ one transistor failure /second today)

Alternative History

Imagine: no transistors, no integrated circuits...








Could we build a computer out of unreliable components?


J. von Neumann, "Probabilistic Logics and the Synthesis of Reliable Organism from Unreliable Components" 1956

Von Neumann's Model



NAND gate


x	y	f
0	0	1
0	1	1
1	0	1
1	1	0



majority gate

x	y	z	f
0	0	0	0
0	0	1	0
0	1	0	0
0	1	1	1
1	0	0	0
1	0	1	1
1	1	0	1
1	1	1	1


full adder




suppose each gate fails (outputs wrong answer) *independently* and with probability p

Von Neumann's Conundrum

Observation: If all gates fail with probability p, then an output bit of any circuit most fail with at least probability p



"Loophole": replace wire by "bundle" of N wires




$\leq \beta N$ 0s decode as "1"


$\geq (1-\beta)N$ 0s decode as "0"

$0<\beta<1/2$

Von Neumann's Solution 1

Simulate the majority gate redundantly:






2. incoming errors may add


1. M gates may fail

Von Neumann's Solution 2

"Restorative organ":




random permutation



αN "0s" $\Rightarrow$ $[3\alpha^2(1-\alpha)+\alpha^3]N$ "0s" = $\alpha^* N$ "0"s

Von Neumann's Solution 1&2



gate error correction

Theorem (von Neumann): A circuit of g gates can be made to fail with probability ε using $O(g \log(g/\varepsilon))$ gates which fail with probability p, assuming $p < p_{th}$ (vN estimated $p_{th} \sim 1\%$)


Controversy

Is topological quantum computing fault-tolerant?

If we use this definition of fault-tolerant, then I believe the answer is NO!

But I also think this is the wrong definition

Cartoon Guide to Classical Physical Fault-Tolerance



$+1$

-1

spin

$s_i \in \{+1, -1\}$

Energy

$$E = -J \sum_{\langle i,j \rangle} s_i s_j$$

neighbors


total magnetization

$$M = \sum_i s_i$$

"0" as $M > N_0$

"1" as $M < -N_0$

Cartoon Guide to Classical Physical Fault-Tolerance



"bare" noise time step

N_r runs of 1-3

Simple noise model

1. Pick spin at random

2. If flipping spin would decrease energy
   a. flip spin


3. If flipping spin would increase energy:
   a. flip spin with probability

$$\exp(-\beta \Delta E) \qquad \beta = T^{-1}$$


$\beta = T^{-1}$


Memory


1D 




rate ~ $\exp(-c\beta J)$




2D 



$T < T_C$





$T > T_C$




Fault-Tolerance

1D




2D 



Resilience to "gate" of flipping spins: self-correcting

Toy Model / Strawman





periodic boundary conditions (torus)

plaquette operator



$$S_p = \prod_{e \in \delta P} Z_e$$

vertex operator



$$S_v = \prod_{e | v \in e} X_e$$


$$[S_p, S_v] = 0 \qquad S_p^2 = S_v^2 = I$$

Kitaev Toric Code Hamiltonian:

$$H = -\frac{\Delta}{4}\left[\sum_p S_p + \sum_v S_v\right]$$

A Problem?

Toric code is like 1D Ising:



"On Thermalization in Kitaev's 2D model" R. Alicki, M. Fannes, and M. Horodecki, arXiv:0810.4584

Decay rate for information encoded into ground state is independent of system size, but proportional to

$$\exp(-c\beta J)$$

Contrast with 4D model

"On thermal stability of topological qubit in Kitaev's 4D model" R. Alicki, (M.+P. +R.) Horodecki, arXiv:0811.0033

$$\exp(-cN)$$

Not a Problem?

Factor a 1000 bit number:

1881988129206079638386972394616504398071635633794173827007633564229888597152346654853190606065047430453173880113033967161996923212057340318795506569962213051687593076502570 59


Naive algorithm: ~10^9 gates

Gap to temp ratio: ~20

Seems likely that exponential suppression as function of temp well worth working for

A Problem?

What about during computing?



Creation and manipulation of excited states require operators like:


$$X^{\otimes 5}$$

How to do this?

$\$^{\otimes 5}$ not $X^{\otimes 5}$

How do you "create" and "move" anyons without creating errors = creating extra anyons

The Quantum Threshold Theorem



Theorem: If decoherence and lack of control are below a threshold p* (relative to coherent control), then a quantum computation of size g can be carried out with error probability ε using $O(g \log^c(g/\varepsilon))$ extra qubits

Aharonov, Ben-Or, Knill, LaFlamme, Zurek, Shor, Kitaev, Gottesman, Preskill (~1996)

Challenge


TQC should provide it's own "threshold theorem" if it is truly fault-tolerant.

Why is this important?

A path toward proving fault-tolerance of universal adiabatic quantum computation?

Ideas from TQC important to more traditional approaches to quantum computing.

Adiabatic Dragging



Require: degenerate through entire evolution

"Open loop" holonomic evolution

Adiabatic Teleportation



Initial Code

$$|\Phi_+\rangle = \frac{1}{\sqrt{2}}(|00\rangle + |11\rangle)$$

Final Code



$|\psi\rangle \otimes |\Phi_+\rangle$



$|\Phi_+\rangle \otimes |\psi'\rangle$

Initial Stabilizer

$$\begin{aligned} S_1 &= Z_2 Z_3 \\ S_2 &= X_2 X_3 \end{aligned}$$

$$S_i|\psi\rangle \otimes |\Phi_+\rangle = |\psi\rangle \otimes |\Phi_+\rangle$$

Final Stabilizer

$$\begin{aligned} S'_1 &= Z_1 Z_2 \\ S'_2 &= X_1 X_2 \end{aligned}$$

$$S'_i|\Phi_+\rangle \otimes |\psi\rangle = |\Phi_+\rangle \otimes |\psi\rangle$$

Adiabatic Teleportation

Initial Code



$|\psi\rangle \otimes |\Phi_+\rangle$

Final Code



$|\Phi_+\rangle \otimes |\psi'\rangle$

Initial Hamiltonian $\Delta > 0$ Final Hamiltonian

$$H_i = -\Delta(X_2X_3 + Z_2Z_3) \qquad H_f = -\Delta(X_1X_2 + Z_1Z_2)$$

$$H_i = -\Delta(S_1 + S_2) \qquad H_i = -\Delta(S_1' + S_2')$$

Evolution: $H(t) = \left(1 - \frac{t}{T}\right) H_i + \frac{t}{T} H_f$

Adiabatic Teleportation

$$\begin{aligned} \bar{X}_1 &= X_1 X_2 & \bar{Z}_1 &= Z_2 Z_3 \\ \bar{X}_2 &= X_2 X_3 & \bar{Z}_2 &= Z_1 Z_2 \\ \bar{X}_3 &= X_1 X_2 X_3 & \bar{Z}_3 &= Z_1 Z_2 Z_3 \end{aligned}$$


Initial Hamiltonian

$$H_i = -\Delta(\bar{Z}_1 + \bar{X}_2)$$

Final Hamiltonian

$$H_f = -\Delta(\bar{X}_1 + \bar{Z}_2)$$

$$H(s) = (1-s)H_i + sH_f$$



Adiabatic Teleportation

$$\begin{aligned} \bar{X}_1 &= X_1 X_2 & \bar{Z}_1 &= Z_2 Z_3 \\ \bar{X}_2 &= X_2 X_3 & \bar{Z}_2 &= Z_1 Z_2 \\ \bar{X}_3 &= X_1 X_2 X_3 & \bar{Z}_3 &= Z_1 Z_2 Z_3 \end{aligned}$$

Initial Hamiltonian

$$H_i = -\Delta(\bar{Z}_1 + \bar{X}_2)$$

$$X_1 = \bar{X}_2 \bar{X}_3$$

$$Z_1 = \bar{Z}_1 \bar{Z}_3$$

Final Hamiltonian

$$H_f = -\Delta(\bar{X}_1 + \bar{Z}_2)$$

$$X_3 = \bar{X}_1 \bar{X}_3$$

$$Z_3 = \bar{Z}_2 \bar{Z}_3$$

$$|\psi\rangle \otimes |\Phi_+\rangle \quad \rightarrow \quad |\Phi_+\rangle \otimes |\psi\rangle$$

Adiabatic Gate Teleportation

$$H_i = -U_3 \Delta (X_2 X_3 + Z_2 Z_3) U_3^\dagger \qquad H_f = -\Delta (X_1 X_2 + Z_1 Z_2)$$

Note: spectrum unchanged by unitary

$$|\psi\rangle \otimes |\Phi_+\rangle \longrightarrow |\Phi_+\rangle \otimes U_3 |\psi\rangle$$

Example (Hadamard gate):

$$H_i = -\Delta (X_2 Z_3 + Z_2 X_3) \qquad H_f = -\Delta (X_1 X_2 + Z_1 Z_2)$$

$$|\psi\rangle \otimes |\Phi_+\rangle \longrightarrow |\Phi_+\rangle \otimes H |\psi\rangle$$


$$H = \frac{1}{\sqrt{2}} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix}$$

Let's Build a Computer

One qubit gates



Two qubit gates



Problem: initial Hamiltonian requires 3 qubit interactions

Example



$$H_i = -\Delta(X_2X_3Z_6 + Z_2Z_3 + Z_5Z_6 + Z_3X_5X_6)$$

To get 2 qubit interactions: perturbation theory gadgets

Gadgets



Replace 3,6 by encoded qubits: $|0_L\rangle = |00\rangle, |1_L\rangle = |11\rangle$

$$
\begin{aligned}
H_i &= -\lambda(X_2X_{3a} + Z_2Z_{3a}) - \lambda(X_5X_{6a} + Z_5Z_{6a}) \\
&\quad -\omega Z_{3a}Z_{3b} - \lambda(X_{3b}Z_{6b} + Z_{3b}X_{6b}) \qquad \lambda \ll \omega \\
H_f &= -\lambda(X_1X_2 + Z_1Z_2) - \lambda(X_4X_5 + Z_4Z_5) \\
&\quad -\omega Z_{3a}Z_{3b}
\end{aligned}
$$

[S. D. Bartlett and T. Rudolph, Phys. Rev. A 74, 040302 (2006)]

Gadgets



$$
\begin{aligned}
H_i &= -\lambda(X_2X_{3a} + Z_2Z_{3a}) - \lambda(X_5X_{6a} + Z_5Z_{6a}) \\
&\quad -\omega Z_{3a}Z_{3b} - \lambda(X_{3b}Z_{6b} + Z_{3b}X_{6b}) \\
H_f &= -\lambda(X_1X_2 + Z_1Z_2) - \lambda(X_4X_5 + Z_4Z_5) \\
&\quad -\omega Z_{3a}Z_{3b}
\end{aligned}
$$

Minimum gap: $O\left(\frac{\lambda^2}{\omega}\right)$

Initial ground state fidelity: $1 - O\left(\frac{\lambda^2}{\omega^2}\right)$

Variations on a Theme

Exchange interactions:

$$H = -\Delta(X_1X_2 + Y_1Y_2 + Z_1Z_2)$$

Adiabatically preparing rotated Hamiltonians:

$$H_i = -\Delta(X_1X_2 + Z_1Z_2) \qquad H_f = -\Delta U_2(X_1X_2 + Z_1Z_2)U_2^\dagger$$

Not all U's allow a gap

$$A = \frac{1}{2}\begin{bmatrix} 1+i\sqrt{2} & 1 \\ 1 & -1+1\sqrt{2} \end{bmatrix} \qquad B = \begin{bmatrix} 1 & 0 \\ 0 & e^{i\pi} \end{bmatrix}$$

gap: $\sqrt{2}\Delta$ gap: $\sqrt{2-\sqrt{2}}\Delta$

"Impossibility" Theorem

Is it possible to adiabatically SWAP with only one adiabatic interpolation?

$$H_i = \delta_1(|01\rangle\langle 01| + |11\rangle\langle 11|) + \delta_2|00\rangle\langle 00| + \delta_3|10\rangle\langle 10|$$


$$H_f = \gamma_1(|10\rangle\langle 10| + |11\rangle\langle 11|) + \gamma_2|00\rangle\langle 00| + \gamma_3|01\rangle\langle 01|$$

$$H(t) = \left(1 - \frac{t}{T}\right) H_i + \frac{t}{T} H_f$$

Diagonal in same basis so cannot transfer amplitude to perform SWAP

Architectures





Sequence of Hamiltonians: $H_1, H_2, H_3, H_1, H_2, H_3, \ldots$


Sequence of single qubit gates applied: $U_1, U_2, U_3, U_4, U_5, \ldots$


Generalizing to more than 1 qubit:

Universal QC by cycling between only 3 Hamiltonians

Architectures







n qubit circuit

4n or 5n qubits

Comparison

Holonomic quantum computing, but open loop

open loop holomic QC:
[D. Kult, J. Aberg, E. Sjoqvist, Phys. Rev. A 74, 022106 (2006)]

Adiabatic universal quantum computing, but with piecewise evolution

D. Aharonov et al., in 45th Annual IEEE FOCS (2004)]

Path robustness in holonomy is subsystem dependent


compare:
[O. Oreshkov, T. A. Brun, D. A. Lidar, Phys. Rev. Lett. 102, 070502 (2009)]

Piecewise keeps gap constant:


compare spin-1 chain transmission of:
[K. Eckert, O. Romero-Isart, and A. Sanpera, New J. Phys. 9, 155 (2007)]

Details: arXiv:0905.0901


Back to TQC!



Encoded Qubits





Smooth qubit



Rough qubit

Back to TQC!






$\bar{X} = X^{\otimes c_1}$

$\bar{Z} = Z^{\otimes c_2}$

Smooth qubit

Prepare Smooth Puncture




$$H_0$$


$$H_0 + \frac{\Delta}{4}(S_{p_1} + S_{p_2}) - \frac{\Delta}{2}X$$

Turn off 2 plaquette operators
adjacent to a qubit where X is turned on.


Prepare Smooth Puncture




$S_{p_1} = \bar{Z}_1$



$S_{p_2} = \bar{Z}_2$




$\bar{X}_1$



$\bar{X}_2$

$$-\frac{\Delta}{4}(\bar{Z}_1 + \bar{Z}_2) \longrightarrow -\frac{\Delta}{2}\bar{X}_1\bar{X}_2$$

Prepare Smooth Puncture



$$H_0$$

$$\downarrow$$

$$H_0 + \frac{\Delta}{4}(S_{p_1} + S_{p_2}) + \frac{\Delta}{2}X_a$$

$$-\frac{\Delta}{4}(\bar{Z}_1 + \bar{Z}_2)$$

$$\downarrow$$

$$-\frac{\Delta}{2}\bar{X}_1\bar{X}_2$$


$\bar{Z}_1\bar{Z}_2$ commutes with H(t)

$+1$ eigenspace of $\bar{Z}_1\bar{Z}_2$

$$-\frac{\Delta}{2}X \longrightarrow -\frac{\Delta}{2}Z$$

end up in +1 e.v. of smooth qubit encoded Z

Prepare Smooth Puncture



$$H_0$$

$$\downarrow$$


$$H_0 + \frac{\Delta}{4}(S_{p_1} + S_{p_2}) + \frac{\Delta}{2}X_a$$

$$\downarrow$$

$$H_0 + \frac{\Delta}{4}(S_{p_1} + S_{p_2}) - \frac{\Delta}{2}X_a + \frac{\Delta}{4}(S_{v_1} + S_{v_2}) - \frac{\Delta}{4}(S'_{v_1} + S'_{v_2}))$$

Smooth qubit in +1 eigenvalue of encoded Z

Deform Smooth Puncture



Turn on

$$-\frac{\Delta}{2}X_b$$

While turning off

$$-\frac{\Delta}{4}S_{p_3}$$

+ relevant vertex operators

Rough qubits: Ditto

Rough qubit prepare +1 e.v. of encoded X

Toolkit

1. Create small smooth qubit in +1 e.v. of Z
2. Create small rough qubit in +1 e.v. of X
3. Enlarge, move both punctures
4. Braid puncture: this give a C_X target = rough

These things all commute with each other, as of course these are Abelian anyons.

Universal Toolkit

1. Create small smooth qubit in +1 e.v. of Z
2. Create small rough qubit in +1 e.v. of X
3. Enlarge, move both punctures
4. Braid puncture: this give a C_X target = rough

5. Measure encoded X,Z of qubits
6. Create magic states

Requires distillation.


Morals

Adiabatically deforming between different Hamiltonians which have stabilizer codewords as energy eigenstates yields interesting protocols like AGT

Using AGT as a motivator you can understand how topological quantum computing can compute (and thus can provide rigorous error bounds.)

Adiabatic Gate Teleportation

Dave Bacon
University of Washington, Seattle, WA USA



[joint work with Steve Flammia (Perimeter), Alice Neels (Washington), Andrew Landahl (Sandia Labs)]

8th Symposium on Topological Quantum Computing, Zurich 29th-31st August 2009