A9.1 About the low-power interface

The low-power interface is an optional extension to the AXI protocol that targets two different classes of peripherals:

- Any peripheral that has no power-down sequence, and that can indicate when its clocks can be turned off.
- Any peripheral that requires a power-down sequence, and that can have its clocks turned off only after it enters a low-power state. The peripheral requires an indication from a system clock controller to indicate when to initiate the power-down sequence, and must then signal when it has entered its low-power state.

Copyright © 2003, 2004, 2010, 2011 ARM. All rights reserved.
Non-Confidential