8W - 01 WIRING DIAGRAM INFORMATION

TABLE OF CONTENTS

page

WIRING DIAGRAM INFORMATION
DESCRIPTION
DESCRIPTION - HOW TO USE WIRING DIAGRAMS 1
DESCRIPTION - CIRCUIT INFORMATION 5
DESCRIPTION - CIRCUIT FUNCTIONS 5
DESCRIPTION - SECTION IDENTIFICATION AND INFORMATION 5
DESCRIPTION - CONNECTOR, GROUND AND SPLICE INFORMATION 6
WARNINGS - GENERAL 6
DIAGNOSIS AND TESTING - WIRING HARNESS 6
STANDARD PROCEDURE
STANDARD PROCEDURE - ELECTROSTATIC DISCHARGE (ESD) SENSITIVE DEVICES 7
STANDARD PROCEDURE - TESTING OF VOLTAGE POTENTIAL. 8
STANDARD PROCEDURE - TESTING FOR CONTINUITY 8

page

STANDARD PROCEDURE - TESTING FOR A SHORT TO GROUND 8
STANDARD PROCEDURE - TESTING FOR A SHORT TO GROUND ON FUSES POWERING SEVERAL LOADS 8
STANDARD PROCEDURE - TESTING FOR A VOLTAGE DROP 9
SPECIAL TOOLS
WIRING/TERMINAL 9
CONNECTOR
REMOVAL 10
INSTALLATION 12
DIODE
REMOVAL 13
INSTALLATION 13
TERMINAL
REMOVAL 13
INSTALLATION 13
WIRE
STANDARD PROCEDURE - WIRE SPLICING . . 14

WIRING DIAGRAM INFORMATION

DESCRIPTION

DESCRIPTION - HOW TO USE WIRING DIAGRAMS

DaimlerChrysler Corporation wiring diagrams are designed to provide information regarding the vehicles wiring content. In order to effectively use the wiring diagrams to diagnose and repair DaimlerChrysler Corporation vehicles, it is important to understand all of their features and characteristics.

Diagrams are arranged such that the power (B+) side of the circuit is placed near the top of the page, and the ground (B-) side of the circuit is placed near the bottom of the page.

All switches, components, and modules are shown in the at rest position with the doors closed and the key removed from the ignition.

Components are shown two ways. A solid line around a component indicates that the component is complete. A dashed line around the component indicates that the component is being shown is not complete. Incomplete components have a reference number to indicate the page where the component is shown complete.

It is important to realize that no attempt is made on the diagrams to represent components and wiring as they appear on the vehicle. For example, a short piece of wire is treated the same as a long one. In addition, switches and other components are shown as simply as possible, with regard to function only.

SYMBOLS

International symbols are used throughout the wiring diagrams. These symbols are consistent with those being used around the world.

TERMINOLOGY

This is a list of terms and definitions used in the wiring diagrams.