P0072-AMBIENT TEMP SENSOR CIRCUIT LOW — Continued

TEST	ACTION	APPLICABILITY
4	Measure the resistance between the (G31) AAT Signal circuit and the (K900) Sensor ground circuit at the AAT Sensor harness connector. Is the resistance below 100 ohms? Yes → Repair the short between the (K900) Sensor ground circuit and the (G31) AAT Signal circuit. Perform POWERTRAIN VERIFICATION TEST VER - 5. No → Go To 5	All
5	**NOTE: Before continuing, check the PCM harness connector terminals for corrosion, damage, or terminal push out. Repair as necessary.** Using the schematics as a guide, inspect the wire harness and connectors. Pay particular attention to all Power and Ground circuits. If there are no possible causes remaining, view repair. Repair Replace and program the Powertrain Control Module per Service Information. Perform POWERTRAIN VERIFICATION TEST VER - 5.	All