Symptom:

P0480-COOLING FAN NO.1 CONTROL CIRCUIT

When Monitored and Set Condition:

P0480-COOLING FAN NO.1 CONTROL CIRCUIT

When Monitored: With the ignition on. Battery voltage greater than 10 volts.

Set Condition: An open or shorted circuit is detected in the radiator fan relay control circuit.

POSSIBLE CAUSES
LOW SPEED RADIATOR FAN RELAY OPERATION
LOW SPEED RADIATOR FAN RELAY
(F20) FUSED IGNITION SWITCH OUTPUT CIRCUIT
(A16) FUSED B+ CIRCUIT
(N201) LOW SPEED RAD FAN RELAY CONTROL CIRCUIT OPEN
(N201) LOW SPEED RAD FAN RELAY CONTROL CIRCUIT SHORTED TO GROUND
PCM

TEST	ACTION	APPLICABILITY
1	Ignition on, engine not running. With the DRBIII®, actuate the Low Speed Radiator Fan Relay. Is the Radiator Fan Relay cycling on and off? Yes → Refer to the INTERMITTENT CONDITION Symptom (Diagnostic Procedure). Perform POWERTRAIN VERIFICATION TEST VER - 5. No → Go To 2	All
2	Turn the ignition off. Remove the Low Speed Radiator Fan Relay from the PDC. Measure the resistance of the Low Speed Radiator Fan Relay Coil by measuring between the (F20) Fused Ignition Switch terminal and the (N201) Control circuit terminal at the Relay . Is the resistance between 60 and 80 ohms? Yes → Go To 3 No → Replace the Low Speed Radiator Fan Relay. Perform POWERTRAIN VERIFICATION TEST VER - 5.	All