P1593-SPEED CONTROL SWITCH NO.1 STUCK — Continued

TEST	ACTION	APPLICABILITY
6	Disconnect the C2 and C3 PCM harness connectors. Measure the resistance between the (V37) S/C Signal circuit and the (K900) Sensor ground circuit in the Speed Control harness connector. Is the resistance below 5.0 ohms? Yes → Repair the short between the (V37) S/C Signal circuit and the (K900) Sensor ground circuit. Perform POWERTRAIN VERIFICATION TEST VER - 4. No → Go To 7	All
7	**NOTE: The measurement must be taken from both Speed Control Switch harness connectors.** **CAUTION: DO NOT PROBE THE PCM HARNESS CONNECTORS. PROBING THE PCM HARNESS CONNECTORS WILL DAMAGE THE PCM TERMINALS RESULTING IN POOR TERMINAL TO PIN CONNECTION. INSTALL MILLER SPECIAL TOOL #8815 TO PERFORM DIAGNOSIS.** Measure the resistance of the (K900) Sensor ground circuit from the Speed Control harness connector to the appropriate terminal of special tool #8815. Is the resistance below 5.0 ohms for both measurements? Yes → Go To 8 No → Repair the open in the (K900) Sensor ground circuit. Perform POWERTRAIN VERIFICATION TEST VER - 4.	All
8	**NOTE: Before continuing, check the PCM harness connector terminals for corrosion, damage or terminal push out. Repair as necessary.** Using the schematics as a guide, inspect the wire harness and connectors. Pay particular attention to all Power and Ground circuits. If there are no possible causes remaining, view repair. Repair Replace and program the Powertrain Control Module per Service Information. Perform POWERTRAIN VERIFICATION TEST VER - 4.	All