P0562-BATTERY VOLTAGE LOW — Continued

TEST	ACTION	APPLICABILITY
6	Measure the resistance between ground and the (K125) Gen Field Control circuit in the Generator Field harness connector. Is the resistance below 100 ohms? Yes → Repair the short to ground in the (K125) Gen Field Control circuit. Perform POWERTRAIN VERIFICATION TEST VER - 3. No → Go To 7	All
7	Using a 12-volt test connected to 12-volts, probe the (Z20) Ground circuit in the Generator Field harness connector. Does the test light illuminate brightly? Yes → Go To 8 No → Repair the open in the (Z20) Ground circuit. Perform POWERTRAIN VERIFICATION TEST VER - 3.	All
8	**NOTE: Before continuing, check the PCM harness connector terminals for corrosion, damage or terminal push out. Repair as necessary.** Using the schematics as a guide, inspect the wire harness and connectors. Pay particular attention to all Power and Ground circuits. If there are no possible causes remaining, view repair. Repair Replace and program the Powertrain Control Module per Service Information. Perform POWERTRAIN VERIFICATION TEST VER - 3.	All