*CHECKING A/C SYSTEM OPERATION WITH NO DTCS — Continued

TEST	ACTION	APPLICABILITY
15	Turn the ignition off. Disconnect the BCM C1 harness connector. Disconnect the A/C - Heater Control C1 harness connector. Measure the resistance of the A/C On/Off Control circuit between the BCM C1 harness connector and the A/C - Heater Control C1 harness connector. Is the resistance below 5.0 ohms? Yes → Replace and program the Body Control Module per Service Information. Perform BODY VERIFICATION TEST - VER 1. No → Repair the A/C On/Off Control Circuit for an open. Perform BODY VERIFICATION TEST - VER 1.	All