

Law	Prime (') notation	Overbar notation
Identity	$A + 0 = A$ $A \cdot 1 = A$	$A + 0 = A$ $A \cdot 1 = A$
Null / Domination	$A + 1 = 1$ $A \cdot 0 = 0$	$A + 1 = 1$ $A \cdot 0 = 0$
Idempotent	$A + A = A$ $A \cdot A = A$	$A + A = A$ $A \cdot A = A$
Complement	$A + A' = 1$ $A \cdot A' = 0$	$A + \overline{A} = 1$ $A \cdot \overline{A} = 0$
Double Negation	$(A')' = A$	$\overline{\overline{A}} = A$
Commutative	$A + B = B + A$ $A \cdot B = B \cdot A$	$A + B = B + A$ $A \cdot B = B \cdot A$
Associative	$(A + B) + C = A + (B + C)$ $(A \cdot B) \cdot C = A \cdot (B \cdot C)$	$(A + B) + C = A + (B + C)$ $(A \cdot B) \cdot C = A \cdot (B \cdot C)$
Distributive	$A \cdot (B + C) = AB + AC$ $A + (BC) = (A + B)(A + C)$	$A \cdot (B + C) = AB + AC$ $A + (BC) = (A + B)(A + C)$
Absorption	$A + AB = A$ $A \cdot (A + B) = A$	$A + AB = A$ $A \cdot (A + B) = A$
De Morgan's	$(A \cdot B)' = A' + B'$ $(A + B)' = A' \cdot B'$	$\overline{A \cdot B} = \overline{A} + \overline{B}$ $\overline{A + B} = \overline{A} \cdot \overline{B}$
XOR Identity	$A'B + AB' = A \oplus B$	$\overline{A}B + A\overline{B} = A \oplus B$