

Newton on KKT $\min f(x) = x_1^2 + 5x_2^2$, **s.t.** $g(x) = 4 - x_1 - x_2 \leq 0$
 Form KKT residual system $r(x, \lambda) = 0$:

$$r = \begin{bmatrix} \nabla_x l \\ g(x) \end{bmatrix} = \begin{bmatrix} 2x_1 - \lambda \\ 10x_2 - \lambda \\ x_1 + x_2 - 4 \end{bmatrix} \qquad J = \frac{\partial r}{\partial (x_1, x_2, \lambda)} = \begin{bmatrix} 2 & 0 & -1 \\ 0 & 10 & -1 \\ 1 & 1 & 0 \end{bmatrix}$$

Init: $z_0 = (0, 0, 0)^\top$; $r(z_0) = (0, 0, -4)^\top$
Newton step: solve $J \Delta z = -r(z_0)$

$$\begin{bmatrix} 2 & 0 & -1 \\ 0 & 10 & -1 \\ 1 & 1 & 0 \end{bmatrix} \begin{bmatrix} \Delta x_1 \\ \Delta x_2 \\ \Delta \lambda \end{bmatrix} = \begin{bmatrix} 0 \\ 0 \\ 4 \end{bmatrix}$$

Row 1: $\Delta x_1 = \frac{\Delta \lambda}{2}$ Row 2: $\Delta x_2 = \frac{\Delta \lambda}{10}$
 Row 3: $\frac{\Delta \lambda}{2} + \frac{\Delta \lambda}{10} = 4 \Rightarrow 6\Delta \lambda = 40 \Rightarrow \Delta \lambda = \frac{20}{3}$

$$\Delta x_1 = \frac{10}{3} \qquad \Delta x_2 = \frac{2}{3}$$

Update ($\alpha = 1$, linear system $\Rightarrow$ exact in one step):

$$z_1 = z_0 + \Delta z = \left(\frac{10}{3}, \frac{2}{3}, \frac{20}{3} \right) \qquad f(x^*) = \frac{100}{9} + \frac{20}{9} = \frac{40}{3}$$

SQP connection

KKT — necessary conditions for a constrained optimum; gives the system $r(x, \lambda) = 0$

Lagrangian — function whose stationarity encodes the KKT conditions; introduces λ

Slack variables — convert inequalities to equalities; lead to complementary slackness $\lambda s = 0$

SQP — solves $r = 0$ using Newton's method; each step inverts the Jacobian of r :

$$r(x, \lambda) = \begin{bmatrix} \nabla_x \mathcal{L} \\ g(x) \end{bmatrix} = \begin{bmatrix} 2x_1 - \lambda \\ 10x_2 - \lambda \\ x_1 + x_2 - 4 \end{bmatrix} = 0 \qquad J = \frac{\partial r}{\partial (x_1, x_2, \lambda)} = \begin{bmatrix} 2 & 0 & -1 \\ 0 & 10 & -1 \\ 1 & 1 & 0 \end{bmatrix}$$

BFGS — quasi-Newton approximation of the Hessian of $\mathcal{L}$ when exact computation is too costly

KKT $\min f(x) = x_1^2 + 5x_2^2, \quad x \in \mathbb{R}^2, \quad \text{s.t. } g(x) = x_1 + x_2 - 4$
Slack: $g(x) - s^2 = 0$, **so** $l(x, \lambda, s) = f(x) - \lambda(g(x) - s^2)$

$$\frac{\partial l}{\partial s} = 2\lambda s = 0 \Rightarrow \lambda = 0 \text{ (inactive) or } s = 0 \text{ (active)}$$

Test: $X_{\text{unc}} = (0, 0)$; $g(X_{\text{unc}}) = -4 < 0 \quad \therefore \text{infeasible} \Rightarrow \lambda \neq 0$
 $\xrightarrow{2\lambda s=0} \quad s = 0$, **constraint active**

$$l(x, \lambda) = x_1^2 + 5x_2^2 - \lambda(x_1 + x_2 - 4) \qquad \text{KKT: set } s = 0$$

Restating $g(x) = x_1 + x_2 - 4$; form residual and Jacobian:

$$r(x, \lambda) = \begin{bmatrix} \nabla_x l \\ g(x) \end{bmatrix} = \begin{bmatrix} 2x_1 - \lambda \\ 10x_2 - \lambda \\ x_1 + x_2 - 4 \end{bmatrix} \qquad J = \begin{bmatrix} 2 & 0 & -1 \\ 0 & 10 & -1 \\ 1 & 1 & 0 \end{bmatrix}$$

$$\nabla_x l = \begin{bmatrix} 2x_1 - \lambda \\ 10x_2 - \lambda \end{bmatrix} \rightarrow x^*(\lambda) = \begin{bmatrix} \lambda/2 \\ \lambda/10 \end{bmatrix}$$

$$g(x^*(\lambda)) = \frac{\lambda}{2} + \frac{\lambda}{10} - 4 \qquad \Rightarrow \qquad \frac{\lambda}{2} + \frac{\lambda}{10} = 4$$

$$10\lambda + 2\lambda = 80 \qquad \lambda = \frac{80}{12} = \frac{20}{3}$$

$$x^* = \begin{bmatrix} \frac{20/3}{2} \\ \frac{20/3}{10} \end{bmatrix} = \begin{bmatrix} \frac{10}{3} \\ \frac{2}{3} \end{bmatrix} \qquad f(x^*) = \left(\frac{10}{3} \right)^2 + 5 \left(\frac{2}{3} \right)^2 = \frac{100}{9} + \frac{20}{9} = \frac{120}{9} = \frac{40}{3}$$

Newton's method applied to KKT (same example: $\min x_1^2 + 5x_2^2$ s.t. $x_1 + x_2 = 4$, starting at $z_0 = (0, 0, 0)$)

Step 1 — residual at z_0 :

$$r(z_0) = \begin{bmatrix} 2(0) - 0 \\ 10(0) - 0 \\ 0 + 0 - 4 \end{bmatrix} = \begin{bmatrix} 0 \\ 0 \\ -4 \end{bmatrix}$$

Step 3 — solve $J \Delta z = -r(z_0)$:

$$\begin{bmatrix} 2 & 0 & -1 \\ 0 & 10 & -1 \\ 1 & 1 & 0 \end{bmatrix} \begin{bmatrix} \Delta x_1 \\ \Delta x_2 \\ \Delta \lambda \end{bmatrix} = \begin{bmatrix} 0 \\ 0 \\ 4 \end{bmatrix}$$

Step 2 — Jacobian (constant here since r is linear):

$$J = \begin{bmatrix} 2 & 0 & -1 \\ 0 & 10 & -1 \\ 1 & 1 & 0 \end{bmatrix}$$

Row 1: $2\Delta x_1 - \Delta \lambda = 0 \Rightarrow \Delta x_1 = \frac{\Delta \lambda}{2}$
 Row 2: $10\Delta x_2 - \Delta \lambda = 0 \Rightarrow \Delta x_2 = \frac{\Delta \lambda}{10}$
 Row 3: $\Delta x_1 + \Delta x_2 = 4 \Rightarrow \frac{\Delta \lambda}{2} + \frac{\Delta \lambda}{10} = 4 \Rightarrow 6\Delta \lambda = 40 \Rightarrow \Delta \lambda = \frac{20}{3}$

$$\Delta x_1 = \frac{10}{3} \qquad \Delta x_2 = \frac{2}{3}$$

Step 4 — update: $z_1 = z_0 + \Delta z$

$$z_1 = \left(\frac{10}{3}, \frac{2}{3}, \frac{20}{3} \right) = x^* \quad \checkmark \quad (\text{one step: KKT system is linear})$$