

Function a: $C + A + \bar{B}\bar{D} + BD$
 CD

		00	01	11	10
00		1	0	1	1
01		0	1	1	1
11		-	-	-	-
10		1	1	-	-

Function e: $\bar{B}\bar{D} + C\bar{D}$
 CD

		00	01	11	10
00		1	0	0	1
01		0	0	0	1
11		-	-	-	-
10		1	0	-	-

Function b: $A + B + \bar{C}\bar{D}$
 CD

		00	01	11	10
00		1	0	0	0
01		1	1	1	1
11		-	-	-	-
10		1	1	-	-

Function f: $\bar{C} + B + D$
 CD

		00	01	11	10
00		1	1	1	0
01		1	1	1	1
11		-	-	-	-
10		1	1	-	-

Function c: $\bar{B} + CD + \bar{C}\bar{D}$
 CD

		00	01	11	10
00		1	1	1	1
01		1	0	1	0
11		-	-	-	-
10		1	1	-	-

Function g: $A + \bar{B}\bar{D} + \bar{B}C + C\bar{D} + B\bar{C}D$
 CD

		00	01	11	10
00		1	0	1	1
01		0	1	0	1
11		-	-	-	-
10		1	1	-	-

Function d: $A + \bar{B}C + B\bar{D} + B\bar{C}$
 CD

		00	01	11	10
00		0	0	1	1
01		1	1	0	1
11		-	-	-	-
10		1	1	-	-