

$$\begin{array}{c|c|c} a & b & c \\ \hline d & e & f \\ \hline g \end{array}$$

0

a	b	c	d	e	f	g
1	1	1	0	1	1	1
0	0	1	0	0	1	0
1	0	1	1	1	0	1
1	0	1	1	0	1	1
0	1	1	1	0	1	0
1	1	0	1	0	1	1
1	1	0	1	1	1	1
1	1	1	0	0	1	0
1	1	1	1	1	1	1
1	1	1	1	0	1	1

1

2

3

4

5

6

7

8

9

→ in quello da 8bit
Non c'è

$$\begin{array}{c|c|c} a & & \\ b & d & c \\ e & g & f \end{array}$$

- 0 •
- 1 •
- 2 •
- 3 •
- 4 •
- 5 •
- 6 •
- 7 •

	x	y	z	w	a	b	c	d	e	f	g
0	0	0	0	0							
1	0	0	0	1							
2	0	0	1	0							
3	0	0	1	1							
4	0	1	0	0							
5	0	1	0	1							
6	0	1	1	0							
7	0	1	1	1							
8	1	0	0	0							
9	1	0	0	1							
10	1	0	1	0							
11	1	0	1	1							
12	1	1	0	0							
13	1	1	0	1							
14	1	1	1	0							
15	1	1	1	1							

$$\begin{aligned} a &= \bar{y}\bar{z}\bar{w} + y\bar{y}w + \bar{x}z \\ b &= \bar{y}\bar{z}w + \bar{x}y \\ c &= \bar{x}\bar{y} + \bar{y}\bar{z}\bar{w} + \bar{x}\bar{z}\bar{w} + \bar{x}\bar{z}w \\ d &= \bar{x}y\bar{z} + \bar{x}\bar{y}\bar{z}\bar{w} + \bar{x}\bar{y}z + \bar{x}\bar{z}\bar{w} \\ e &= \bar{y}\bar{z}\bar{w} + \bar{x}\bar{z}\bar{w} \\ f &= \bar{y}\bar{z}\bar{w} + \bar{x}\bar{y} + \bar{x}\bar{y}w \\ g &= \bar{y}\bar{z}\bar{w} + \bar{y}\bar{z}w + \bar{x}\bar{z}\bar{w} \end{aligned}$$

$\backslash xy$	00	01	11	10
zw				
00	1		x	1
01		1	x	1
11	1	1	x	x
10	1	1	x	x

a

$$a = \bar{y}\bar{z}\bar{w} + z + yw + x$$

$$b = \bar{z}\bar{w} + y + x$$

$\backslash xy$	00	01	11	10
zw				
00	1	1	x	1
01		1	x	1
11		1	x	x
10		1	x	x

b

$\backslash xy$	00	01	11	10
zw				
00	1	1	x	1
01	1		x	1
11	1	1	x	x
10	1		x	x

c

$$c = \bar{y} + \bar{z}\bar{w} + zw$$

$$d = y\bar{z} + x + \bar{y}z + \bar{z}\bar{w}$$

$\backslash xy$	00	01	11	10
zw				
00		1	x	1
01		1	x	1
11	1		x	x
10	1	1	x	x

d

$\backslash xy$	00	01	11	10
zw				
00	1		x	1
01			x	0
11			x	x
10	1	1	x	x

e

$$e = \bar{y}\bar{z}\bar{w} + z\bar{w}$$

$$f = \bar{z} + w + y$$

$\backslash xy$	00	01	11	10
zw				
00	1	1	x	1
01	1	1	x	1
11	1	1	x	x
10		1	x	x

f

$\backslash xy$	00	01	11	10
zw				
00	1		x	1
01		1	x	1
11	1		x	x
10	1	1	x	x

g

$$g = \bar{y}\bar{z}\bar{w} + y\bar{z}w + \bar{x}\bar{y}z + zw + x$$