

Function a: $\bar{B}\bar{D} + BD + \bar{A}\bar{D} + \bar{A}C + \bar{A}\bar{B}\bar{C} + \bar{A}BD$
 CD

	00	01	11	10
00	1	0	1	1
01	0	1	1	1
11	1	0	1	1
10	1	1	0	1

Function e: $\bar{A}\bar{B} + \bar{C}\bar{D} + \bar{A}B + \bar{A}D + \bar{B}\bar{C}$
 CD

	00	01	11	10
00	1	1	1	0
01	1	1	1	1
11	0	1	0	0
10	1	1	1	1

Function b: $\bar{A}\bar{B} + \bar{A}B + \bar{C}\bar{D} + AC$
 CD

	00	01	11	10
00	1	0	0	0
01	1	1	1	1
11	1	0	1	1
10	1	1	1	1

Function f: $\bar{B}\bar{D} + \bar{B}\bar{C} + \bar{A}CD + \bar{A}\bar{C}D + \bar{A}\bar{C}\bar{D}$
 CD

	00	01	11	10
00	1	1	1	1
01	1	0	1	0
11	0	1	0	0
10	1	1	0	1

Function c: $\bar{B}\bar{D} + \bar{C}\bar{D} + AB + AC$
 CD

	00	01	11	10
00	1	0	0	1
01	0	0	0	1
11	1	1	1	1
10	1	0	1	1

Function g: $C\bar{D} + \bar{A}\bar{B} + \bar{B}C + AD + \bar{A}\bar{B}\bar{C}$
 CD

	00	01	11	10
00	0	0	1	1
01	1	1	0	1
11	0	1	1	1
10	1	1	1	1

Function d: $AB\bar{D} + \bar{B}\bar{C}\bar{D} + \bar{B}\bar{C}D + \bar{A}\bar{C}\bar{D} + \bar{A}BD + \bar{A}\bar{B}C$
 CD

	00	01	11	10
00	1	0	1	1
01	0	1	0	1
11	1	1	0	1
10	1	1	1	0