WIRE LIST	FILE	PRINTED
PanelViz Wiring Sc?	mycnc.yml	2026-08-02 **PAGE 1 OF 6**

Wire count: 262 **Component count: 64**

Wire	From	Pin	To	Pin	Net	AWG	Tags	From Ref	To Ref
110L/4	wall_plug	1	wall_power_t	1A	110L	12	vfd	Y12	Y13
110L/8	wall_power_t	1B	power_switch	L_IN	110L	12	vfd	X13	X12
110L/6	power_switch	L_OUT	breaker	L_IN	110L	12	vfd	W12	V11
110L/7	breaker	L_OUT	live_power_t	1A	110L	12	vfd	V11	O10
110L/5	live_power_t	1B	transformer	110L	110L	20	vfd	N10	V7
110L/2	live_power_t	3A	contactor_110	T2	110L	20	vfd	O11	L8
110L/1	24v	110L	live_power_t	3B	110L	20	dc_power, vfd	L10	N11
110L/3	5v	110L	live_power_t	5A	110L	20	dc_power, vfd	L12	O11
110L_SWITCHED/1	contactor_110	L2	switched_110L	1A	110L_SWITCHED	20	vfd	J8	N9
110L_SWITCHED/2	48v	110L	switched_110L	1B	110L_SWITCHED	20	vfd	Q13	O9
110L_SWITCHED/3	36V_X1	110L	switched_110L	2A	110L_SWITCHED	20	vfd	Q5	N9
110L_SWITCHED/4	36V_X2	110L	switched_110L	2B	110L_SWITCHED	20	vfd	Q9	O9
110N/4	wall_plug	2	live_power_t	2A	110N	12	vfd	Y12	O10
110N/5	live_power_t	2B	transformer	110N	110N	20	vfd	N10	V7
110N/2	live_power_t	4A	contactor_110	T3	110N	20	vfd	O11	L9
110N/1	24v	110N	live_power_t	4B	110N	20	dc_power, vfd	L10	N11
110N/3	5v	110N	live_power_t	6A	110N	20	dc_power, vfd	L12	O11
110N_SWITCHED/1	contactor_110	L3	switched_110N	1A	110N_SWITCHED	20	vfd	J9	N10
110N_SWITCHED/2	36V_X1	110N	switched_110N	1B	110N_SWITCHED	20	vfd	Q4	O10
110N_SWITCHED/3	36V_X2	110N	switched_110N	2A	110N_SWITCHED	20	vfd	Q8	N10
110N_SWITCHED/4	48v	110N	switched_110N	2B	110N_SWITCHED	20	vfd	Q12	O10
24V/15	z_limits	24v	cnc_terminals	11A	24V	20	terminals	A11	B11
24V/16	cnc_terminals	11B	terminals_24v	1A	24V	20	terminals	C11	B15
24V/17	y_limits	24v	cnc_terminals	25A	24V	20	terminals	B10	B10
24V/18	cnc_terminals	25B	terminals_24v	1B	24V	20	terminals	C10	C15
24V/19	x1_limits	24v	cnc_terminals	37A	24V	20	terminals	A8	B9
24V/20	cnc_terminals	37B	terminals_24v	2A	24V	20	terminals	C9	B15
24V/21	x2_limits	24v	cnc_terminals	49A	24V	20	terminals	A7	B8
24V/22	cnc_terminals	49B	terminals_24v	2B	24V	20	terminals	C8	C15
24V/1	estop_panel	estop+	cnc_terminals	57A	24V	20	terminals	B5	B7
24V/2	cnc_terminals	57B	terminals_24v	3A	24V	20	terminals	C7	B14
24V/3	estop_panel	light+	cnc_terminals	59A	24V	20	terminals	B5	B7
24V/4	cnc_terminals	59B	terminals_24v	3B	24V	20	terminals	C7	C14
24V/14	24v	24V	dc_power_24v	1A	24V	20	dc_power	L11	L14
24V/13	dc_power_24v	1B	safety_24v	1A	24V	20	dc_power, safe?	K14	I15
24V/12	safety_24v	1B	control_24v	1A	24V	20	safety, control	H15	D15
24V/5	control_24v	1B	terminals_24v	4A	24V	20	control, termi?	E15	B14
24V/6	control_24v	2A	axbb-e	I1+	24V	20	control	D15	D11
24V/7	control_24v	2B	axbb-e	I2+	24V	20	control	E15	D11
24V/8	control_24v	3A	axbb-e	I3+	24V	20	control	D15	D11
24V/9	control_24v	3B	axbb-e	I4+	24V	20	control	E15	D11
24V/10	control_24v	4A	axbb-e	I5+	24V	20	control	D15	D11

Wire	From	Pin	To	Pin	Net	AWG	Tags	From Ref	To Ref
24V/11	axbb-e	IN-24V+	control_24v	4B	24V	20	control	F12	E15
24V/27	opto_board	1+	safety_24v	4A	24V	20	safety	G10	I15
24V/28	opto_board	2+	safety_24v	4B	24V	20	safety	G10	H15
24V/29	opto_board	3+	safety_24v	5A	24V	20	safety	G10	I15
24V/30	opto_board	4+	safety_24v	5B	24V	20	safety	G10	H15
24V/23	opto_board	5+	safety_24v	2A	24V	20	safety	G10	I15
24V/24	opto_board	6+	safety_24v	2B	24V	20	safety	G10	H15
24V/25	opto_board	7+	safety_24v	3A	24V	20	safety	G9	I15
24V/26	opto_board	8+	safety_24v	3B	24V	20	safety	G9	H15
24V0/8	z_limits	24v0	cnc_terminals	14A	24V0	20	terminals	A11	B11
24V0/9	cnc_terminals	14B	terminals_24v0	1A	24V0	20	terminals	C11	B15
24V0/10	y_limits	24v0	cnc_terminals	28A	24V0	20	terminals	B10	B9
24V0/11	cnc_terminals	28B	terminals_24v0	1B	24V0	20	terminals	C9	C15
24V0/21	x1_control	alrm-	cnc_terminals	32A	24V0	20	terminals	A8	B9
24V0/22	cnc_terminals	32B	terminals_24v0	4A	24V0	20	terminals	C9	B15
24V0/12	x1_limits	24v0	cnc_terminals	40A	24V0	20	terminals	A8	B8
24V0/13	cnc_terminals	40B	terminals_24v0	2A	24V0	20	terminals	C8	B15
24V0/23	x2_control	alrm-	cnc_terminals	44A	24V0	20	terminals	A7	B8
24V0/24	cnc_terminals	44B	terminals_24v0	4B	24V0	20	terminals	C8	C15
24V0/14	x2_limits	24v0	cnc_terminals	52A	24V0	20	terminals	A7	B7
24V0/15	cnc_terminals	52B	terminals_24v0	2B	24V0	20	terminals	C7	C15
24V0/7	24v	24V0	dc_power_24v0	1A	24V0	20	dc_power	L11	L15
24V0/6	dc_power_24v0	1B	safety_24v0	1A	24V0	20	dc_power, safe?	K15	H15
24V0/3	safety_24v0	1B	control_24v0	1A	24V0	20	safety, control	I15	D15
24V0/25	y_cl57s	COM-	control_24v0	2B	24V0	20	control	D3	E15
24V0/26	Z_cl57s	COM-	control_24v0	3A	24V0	20	control	D7	D15
24V0/2	axbb-e	IN-24V0	control_24v0	1B	24V0	20	control	F12	E15
24V0/4	run_relay	COM	safety_24v0	2A	24V0	20	safety	I8	H15
24V0/5	upper_limits_ok_relay	COM	safety_24v0	2B	24V0	20	safety	I7	I15
24V0/20	control_24v0	2A	terminals_24v0	3A	24V0	20	control, termi?	D15	B15
36V0_X1/3	36V_X1	36V0_X1	driver_power	2A	36V0_X1	20	vfd	Q4	O12
36V0_X1/1	x1_motor	M-	cnc_terminals	30A	36V0_X1	16	terminals	B8	B9
36V0_X1/2	cnc_terminals	30B	driver_power	2B	36V0_X1	16	terminals, vfd	C9	N12
36V0_X2/3	36V_X2	36V0_X2	driver_power	4A	36V0_X2	20	vfd	Q8	O13
36V0_X2/1	x2_motor	M-	cnc_terminals	42A	36V0_X2	16	terminals	B7	B8
36V0_X2/2	cnc_terminals	42B	driver_power	4B	36V0_X2	16	terminals, vfd	C8	N13
36V_X1/3	36V_X1	36V_X1	driver_power	1A	36V_X1	20	vfd	Q4	O12
36V_X1/1	x1_motor	M+	cnc_terminals	29A	36V_X1	16	terminals	B8	B9
36V_X1/2	cnc_terminals	29B	driver_power	1B	36V_X1	16	terminals, vfd	C9	N12
36V_X2/3	36V_X2	36V_X2	driver_power	3A	36V_X2	20	vfd	Q8	O12
36V_X2/1	x2_motor	M+	cnc_terminals	41A	36V_X2	16	terminals	B7	B8
36V_X2/2	cnc_terminals	41B	driver_power	3B	36V_X2	16	terminals, vfd	C8	N12
5V/17	run_relay	DC+	safety_5v	1A	5V	20	safety	H8	H14
5V/18	upper_limits_ok_relay	DC+	safety_5v	1B	5V	20	safety	H7	I14
5V/20	5v	5V	dc_power_5v	1A	5V	20	dc_power	L12	L14

WIRE LIST
PanelViz Wiring Sc?

FILE
mycnc.yml

PRINTED
2026-08-02

Wire	From	Pin	To	Pin	Net	AWG	Tags	From Ref	To Ref
5V/19	dc_power_5v	1B	safety_5v	2A	5V	20	dc_power, safe?	K14	H14
5V/11	safety_5v	2B	control_5v	1A	5V	20	safety, control	I14	D13
5V/9	control_5v	1B	terminals_5v	1A	5V	20	control, termi?	E13	B13
5V/10	axbb-e	IN-5V+	control_5v	2A	5V	20	control	F12	D13
5V/16	alarm_limit_board	5V	safety_5v	3A	5V	20	safety	H13	H14
5V/21	opto_board	VCC	safety_5v	5B	5V	20	safety	I10	I13
5V0/7	x1_control	dir-	cnc_terminals	34A	5V0	20	terminals	A8	B9
5V0/8	cnc_terminals	34B	terminals_5v0	1A	5V0	20	terminals	C9	C14
5V0/9	x1_control	pul-	cnc_terminals	36A	5V0	20	terminals	A8	B9
5V0/10	cnc_terminals	36B	terminals_5v0	1B	5V0	20	terminals	C9	B14
5V0/15	x2_control	dir-	cnc_terminals	46A	5V0	20	terminals	A7	B8
5V0/16	cnc_terminals	46B	terminals_5v0	2A	5V0	20	terminals	C8	C14
5V0/17	x2_control	pul-	cnc_terminals	48A	5V0	20	terminals	A7	B8
5V0/18	cnc_terminals	48B	terminals_5v0	2B	5V0	20	terminals	C8	B14
5V0/21	estop_panel	reset_sw+	cnc_terminals	55A	5V0	20	terminals	B5	B7
5V0/22	cnc_terminals	55B	terminals_5v0	3A	5V0	20	terminals	C7	C14
5V0/37	run_relay	DC-	safety_5v0	1A	5V0	20	safety	H8	H15
5V0/38	upper_limits_ok_relay	DC-	safety_5v0	1B	5V0	20	safety	H7	I15
5V0/40	5v	5V0	dc_power_5v0	1A	5V0	20	dc_power	L12	L14
5V0/39	dc_power_5v0	1B	safety_5v0	2A	5V0	20	dc_power, safe?	K14	H14
5V0/31	safety_5v0	2B	control_5v0	1A	5V0	20	safety, control	I14	D14
5V0/23	control_5v0	1B	terminals_5v0	3B	5V0	20	control, termi?	E14	B14
5V0/28	y_cl57s	PUL-	control_5v0	2A	5V0	20	control	D2	D14
5V0/29	y_cl57s	DIR-	control_5v0	2B	5V0	20	control	D2	E14
5V0/24	Z_cl57s	PUL-	control_5v0	3A	5V0	20	control	D6	D14
5V0/25	Z_cl57s	DIR-	control_5v0	3B	5V0	20	control	D7	E14
5V0/27	axbb-e	IN-5V0	control_5v0	4A	5V0	20	control	F12	D14
5V0/36	alarm_limit_board	5V0	safety_5v0	3A	5V0	20	safety	H12	H14
5V0/41	opto_board	GND	safety_5v0	5B	5V0	20	safety	I10	I14
COIL-/4	contactor_110	A2	coil_t	3A	COIL-	20	vfd	L9	L6
COIL-/3	contactor_220	A2	coil_t	3B	COIL-	20	vfd	L7	K6
COIL-/1	axbb-e	I6-	coil_t	4A	COIL-	20	control, vfd	D11	L6
COIL-/2	run_relay	NO	coil_t	4B	COIL-	20	safety, vfd	I8	K6
DRIVER_48V/3	48v	48V	driver_power	5A	DRIVER_48V	20	vfd	Q12	O13
DRIVER_48V/2	y_cl57s	+VDC	driver_power	5B	DRIVER_48V	20	control, vfd	D4	N13
DRIVER_48V/1	Z_cl57s	+VDC	driver_power	6A	DRIVER_48V	20	control, vfd	D8	O13
DRIVER_GND/7	48v	48V0	driver_power	7A	DRIVER_GND	20	vfd	Q12	O13
DRIVER_GND/6	y_cl57s	GND	driver_power	7B	DRIVER_GND	20	control, vfd	D4	N13
DRIVER_GND/5	Z_cl57s	GND	driver_power	8A	DRIVER_GND	20	control, vfd	D8	O13
RESET_SW/1	estop_panel	reset_sw-	cnc_terminals	56A	RESET_SW	20	terminals	B5	B7
RESET_SW/2	cnc_terminals	56B	alarm_limit_board	D12	RESET_SW	20	terminals, saf?	C7	H12
RUN_RELAY_CTL/1	alarm_limit_board	D10	run_relay	IN	RUN_RELAY_CTL	20	safety	H12	H8
UL1/1	upper_limits_ok_relay	NC	axbb-e	I1-	UL1	20	safety, control	I7	D11
UPPER_LIMITS_OK_RE/1	alarm_limit_board	D11	upper_limits_ok_relay	IN	UPPER_LIMITS_OK_RE	20	safety	H12	H7
VFD_FWD/1	axbb-e	O3	vfd	FOR	VFD_FWD	20	control, vfd	D12	O16

Wire	From	Pin	To	Pin	Net	AWG	Tags	From Ref	To Ref
VFD_REV/1	axbb-e	O2	vfd	REV	VFD_REV	20	control, vfd	D12	O16
VFD_V1/1	axbb-e	A01	vfd	VI	VFD_V1	20	control, vfd	F12	P19
X1DIR/1	x1_control	dir+	cnc_terminals	33A	X1DIR	20	terminals	A8	B9
X1DIR/2	cnc_terminals	33B	axbb-e	O12	X1DIR	20	terminals, con?	C9	F11
X1LL/1	x1_limits	ll	cnc_terminals	39A	X1LL	20	terminals	A8	B8
X1LL/2	cnc_terminals	39B	axbb-e	I3-	X1LL	20	terminals, con?	C8	D11
X1STEP/1	x1_control	pul+	cnc_terminals	35A	X1STEP	20	terminals	A8	B9
X1STEP/2	cnc_terminals	35B	axbb-e	O11	X1STEP	20	terminals, con?	C9	F11
X1UL_OK/1	alarm_limit_board	D2	opto_board	O1	X1UL_OK	20	safety	H12	I10
X1_ALM_OK/1	alarm_limit_board	D6	opto_board	O5	X1_ALM_OK	20	safety	H12	I10
X2DIR/1	x2_control	dir+	cnc_terminals	45A	X2DIR	20	terminals	A7	B8
X2DIR/2	cnc_terminals	45B	axbb-e	O14	X2DIR	20	terminals, con?	C8	F11
X2LL/1	x2_limits	ll	cnc_terminals	51A	X2LL	20	terminals	A7	B7
X2LL/2	cnc_terminals	51B	axbb-e	I4-	X2LL	20	terminals, con?	C7	D11
X2STEP/1	x2_control	pul+	cnc_terminals	47A	X2STEP	20	terminals	A7	B8
X2STEP/2	cnc_terminals	47B	axbb-e	O13	X2STEP	20	terminals, con?	C8	F11
X2UL_OK/1	alarm_limit_board	D3	opto_board	O2	X2UL_OK	20	safety	H12	I10
X2_ALM_OK/1	alarm_limit_board	D7	opto_board	O6	X2_ALM_OK	20	safety	H12	I10
YDIR/1	y_cl57s	DIR+	axbb-e	O10	YDIR	20	control	D2	F11
YLL/1	y_limits	ll	cnc_terminals	27A	YLL	20	terminals	B10	B9
YLL/2	cnc_terminals	27B	axbb-e	I2-	YLL	20	terminals, con?	C9	D11
YSTEP/1	y_cl57s	PUL+	axbb-e	O9	YSTEP	20	control	D2	F11
YUL_OK/1	alarm_limit_board	D4	opto_board	O3	YUL_OK	20	safety	H12	I10
Y_ALM_OK/1	alarm_limit_board	D8	opto_board	O7	Y_ALM_OK	20	safety	H12	I9
ZDIR/1	Z_cl57s	DIR+	axbb-e	O16	ZDIR	20	control	D7	F11
ZLL/1	z_limits	ll	cnc_terminals	13A	ZLL	20	terminals	A11	B11
ZLL/2	cnc_terminals	13B	axbb-e	I5-	ZLL	20	terminals, con?	C11	D11
ZSTEP/1	Z_cl57s	PUL+	axbb-e	O15	ZSTEP	20	control	D6	F11
ZUL_OK/1	alarm_limit_board	D5	opto_board	O4	ZUL_OK	20	safety	H12	I10
Z_ALM_OK/1	alarm_limit_board	D9	opto_board	O8	Z_ALM_OK	20	safety	H12	I9
Z_cl57s.ALM/1	Z_cl57s	ALM	opto_board	8-	Z_cl57s.ALM	20	control, safety	D7	G9
earth/8	wall_plug	GND	vfd_earth	1A	earth	12	vfd	Y12	N13
earth/9	transformer	GND	vfd_earth	1B	earth	20	vfd	V8	O13
earth/10	48v	GND	vfd_earth	2A	earth	20	vfd	Q13	N13
earth/4	24v	GND	dc_power_earth	1A	earth	20	dc_power	L10	K15
earth/5	5v	GND	dc_power_earth	1B	earth	20	dc_power	L11	L15
earth/11	36V_X1	GND	vfd_earth	2B	earth	20	vfd	Q5	O13
earth/12	36V_X2	GND	vfd_earth	3A	earth	20	vfd	Q9	N13
earth/7	vfd	GND	vfd_earth	3B	earth	20	vfd	O22	O13
earth/6	vfd_earth	4A	dc_power_earth	2A	earth	20	vfd, dc_power	N13	K15
earth/3	dc_power_earth	2B	safety_earth	1A	earth	20	dc_power, safe?	L15	H16
earth/2	safety_earth	1B	control_earth	1A	earth	20	safety, control	I16	D16
earth/1	control_earth	1B	terminals_earth	1A	earth	20	control, termi?	E16	B13
estop_panel.estop?	estop_panel	estop-	cnc_terminals	58A	estop_panel.estop-	20	terminals	B5	B7
estop_panel.estop?	cnc_terminals	58B	cnc_terminals	61B	estop_panel.estop-	20	terminals	C7	C7

Wire	From	Pin	To	Pin	Net	AWG	Tags	From Ref	To Ref
secondary_estop.e?	secondary_estop	estop+	cnc_terminals	61A	estop_panel.estop-	20	terminals	A6	B7
estop_panel.light?	estop_panel	light-	cnc_terminals	60A	estop_panel.light-	20	terminals	B5	B7
estop_panel.light?	cnc_terminals	60B	run_relay	NC	estop_panel.light-	20	terminals, saf?	C7	I8
probe.probe+/1	probe	probe+	cnc_terminals	53A	probe.probe+	20	terminals	B6	B7
probe.probe-/1	probe	probe-	cnc_terminals	54A	probe.probe-	20	terminals	B6	B7
COIL+/5	contactor_110	A1	coil_t	1A	secondary_estop.est?	20	vfd	J9	L6
COIL+/4	contactor_220	A1	coil_t	1B	secondary_estop.est?	20	vfd	J7	K6
secondary_estop.e?	secondary_estop	estop-	cnc_terminals	62A	secondary_estop.est?	20	terminals	A6	B7
COIL+/1	cnc_terminals	62B	coil_t	2A	secondary_estop.est?	20	terminals, vfd	C7	L6
COIL+/3	axbb-e	I6+	coil_t	2B	secondary_estop.est?	20	control, vfd	D11	K6
shield/2	z_motor	shield	connector_earth	1A	shield	20	terminals	B11	B17
shield/8	z_control	shield	connector_earth	1B	shield	20	terminals	A11	C17
shield/12	z_limits	shield	connector_earth	2A	shield	20	terminals	A11	B17
shield/1	y_motor	shield	connector_earth	2B	shield	20	terminals	A10	C17
shield/6	y_control	shield	connector_earth	3A	shield	20	terminals	A10	B17
shield/11	y_limits	shield	connector_earth	3B	shield	20	terminals	B10	C17
shield/3	x1_motor	shield	connector_earth	4A	shield	20	terminals	B8	B17
shield/10	x1_limits	shield	connector_earth	4B	shield	20	terminals	A8	C17
shield/5	x2_motor	shield	connector_earth	5A	shield	20	terminals	B7	B16
shield/9	x2_limits	shield	connector_earth	5B	shield	20	terminals	A7	C16
shield/7	probe	shield	connector_earth	6A	shield	20	terminals	B6	B16
shield/4	spindle	shield	connector_earth	6B	shield	20	terminals	A6	C16
spindle.u/1	spindle	u	cnc_terminals	63A	spindle.u	16	terminals	A6	B6
spindle.u/2	cnc_terminals	63B	vfd	U	spindle.u	16	terminals, vfd	C6	O22
spindle.v/1	spindle	v	cnc_terminals	64A	spindle.v	16	terminals	A6	B6
spindle.v/2	cnc_terminals	64B	vfd	V	spindle.v	16	terminals, vfd	C6	O22
spindle.w/1	spindle	w	cnc_terminals	65A	spindle.w	16	terminals	A6	B6
spindle.w/2	cnc_terminals	65B	vfd	W	spindle.w	16	terminals, vfd	C6	O22
transformer.220L/1	transformer	220L	contactor_220	T1	transformer.220L	20	vfd	V7	L7
transformer.220N/1	transformer	220N	contactor_220	T2	transformer.220N	20	vfd	V7	L7
vfd.R/1	vfd	R	contactor_220	L1	vfd.R	20	vfd	O22	J7
vfd.T/1	vfd	T	contactor_220	L2	vfd.T	20	vfd	O22	J7
x1_control.alrm+/1	x1_control	alrm+	cnc_terminals	31A	x1_control.alrm+	20	terminals	A8	B9
x1_control.alrm+/2	cnc_terminals	31B	opto_board	5-	x1_control.alrm+	20	terminals, saf?	C9	G10
x1_limits.ul/1	x1_limits	ul	cnc_terminals	38A	x1_limits.ul	20	terminals	A8	B9
x1_limits.ul/2	cnc_terminals	38B	opto_board	1-	x1_limits.ul	20	terminals, saf?	C9	G10
x2_control.alrm+/1	x2_control	alrm+	cnc_terminals	43A	x2_control.alrm+	20	terminals	A7	B8
x2_control.alrm+/2	cnc_terminals	43B	opto_board	6-	x2_control.alrm+	20	terminals, saf?	C8	G9
x2_limits.ul/1	x2_limits	ul	cnc_terminals	50A	x2_limits.ul	20	terminals	A7	B8
x2_limits.ul/2	cnc_terminals	50B	opto_board	2-	x2_limits.ul	20	terminals, saf?	C8	G10
y_cl57s.ALM/1	y_cl57s	ALM	opto_board	7-	y_cl57s.ALM	20	control, safety	D3	G9
y_control.ea+/1	y_control	ea+	cnc_terminals	21A	y_control.ea+	20	terminals	A10	B10
y_control.ea+/2	cnc_terminals	21B	y_cl57s	EA+	y_control.ea+	20	terminals, con?	C10	D3
y_control.ea-/1	y_control	ea-	cnc_terminals	22A	y_control.ea-	20	terminals	A10	B10
y_control.ea-/2	cnc_terminals	22B	y_cl57s	EA-	y_control.ea-	20	terminals, con?	C10	D3

WIRE LIST

PanelViz Wiring Sc?

FILE

mycnc.yml

PRINTED

2026-08-02

Wire	From	Pin	To	Pin	Net	AWG	Tags	From Ref	To Ref
y_control.eb+/1	y_control	eb+	cnc_terminals	19A	y_control.eb+	20	terminals	A10	B10
y_control.eb+/2	cnc_terminals	19B	y_cl57s	EB+	y_control.eb+	20	terminals, con?	C10	D3
y_control.eb-/1	y_control	eb-	cnc_terminals	20A	y_control.eb-	20	terminals	A10	B10
y_control.eb-/2	cnc_terminals	20B	y_cl57s	EB-	y_control.eb-	20	terminals, con?	C10	D3
y_control.gnd/1	y_control	gnd	cnc_terminals	24A	y_control.gnd	20	terminals	A10	B10
y_control.gnd/2	cnc_terminals	24B	y_cl57s	EGND	y_control.gnd	20	terminals, con?	C10	D3
y_control.vcc/1	y_control	vcc	cnc_terminals	23A	y_control.vcc	20	terminals	A10	B10
y_control.vcc/2	cnc_terminals	23B	y_cl57s	VCC	y_control.vcc	20	terminals, con?	C10	D3
y_limits.ul/1	y_limits	ul	cnc_terminals	26A	y_limits.ul	20	terminals	B10	B10
y_limits.ul/2	cnc_terminals	26B	opto_board	3-	y_limits.ul	20	terminals, saf?	C10	G10
y_motor.ma+/1	y_motor	ma+	cnc_terminals	15A	y_motor.ma+	16	terminals	A10	B10
y_motor.ma+/2	cnc_terminals	15B	y_cl57s	A+	y_motor.ma+	16	terminals, con?	C10	D3
y_motor.ma-/1	y_motor	ma-	cnc_terminals	16A	y_motor.ma-	16	terminals	A10	B10
y_motor.ma-/2	cnc_terminals	16B	y_cl57s	A-	y_motor.ma-	16	terminals, con?	C10	D3
y_motor.mb+/1	y_motor	mb+	cnc_terminals	17A	y_motor.mb+	16	terminals	A10	B10
y_motor.mb+/2	cnc_terminals	17B	y_cl57s	B+	y_motor.mb+	16	terminals, con?	C10	D4
y_motor.mb-/1	y_motor	mb-	cnc_terminals	18A	y_motor.mb-	16	terminals	A10	B10
y_motor.mb-/2	cnc_terminals	18B	y_cl57s	B-	y_motor.mb-	16	terminals, con?	C10	D4
z_control.ea+/1	z_control	ea+	cnc_terminals	7A	z_control.ea+	20	terminals	A11	B11
z_control.ea+/2	cnc_terminals	7B	Z_cl57s	EA+	z_control.ea+	20	terminals, con?	C11	D7
z_control.ea-/1	z_control	ea-	cnc_terminals	8A	z_control.ea-	20	terminals	A11	B11
z_control.ea-/2	cnc_terminals	8B	Z_cl57s	EA-	z_control.ea-	20	terminals, con?	C11	D7
z_control.eb+/1	z_control	eb+	cnc_terminals	5A	z_control.eb+	20	terminals	A11	B11
z_control.eb+/2	cnc_terminals	5B	Z_cl57s	EB+	z_control.eb+	20	terminals, con?	C11	D7
z_control.eb-/1	z_control	eb-	cnc_terminals	6A	z_control.eb-	20	terminals	A11	B11
z_control.eb-/2	cnc_terminals	6B	Z_cl57s	EB-	z_control.eb-	20	terminals, con?	C11	D7
z_control.gnd/1	z_control	gnd	cnc_terminals	10A	z_control.gnd	20	terminals	A11	B11
z_control.gnd/2	cnc_terminals	10B	Z_cl57s	EGND	z_control.gnd	20	terminals, con?	C11	D8
z_control.vcc/1	z_control	vcc	cnc_terminals	9A	z_control.vcc	20	terminals	A11	B11
z_control.vcc/2	cnc_terminals	9B	Z_cl57s	VCC	z_control.vcc	20	terminals, con?	C11	D7
z_limits.ul/1	z_limits	ul	cnc_terminals	12A	z_limits.ul	20	terminals	A11	B11
z_limits.ul/2	cnc_terminals	12B	opto_board	4-	z_limits.ul	20	terminals, saf?	C11	G10
z_motor.ma+/1	z_motor	ma+	cnc_terminals	1A	z_motor.ma+	16	terminals	B11	B12
z_motor.ma+/2	cnc_terminals	1B	Z_cl57s	A+	z_motor.ma+	16	terminals, con?	C12	D8
z_motor.ma-/1	z_motor	ma-	cnc_terminals	2A	z_motor.ma-	16	terminals	B11	B11
z_motor.ma-/2	cnc_terminals	2B	Z_cl57s	A-	z_motor.ma-	16	terminals, con?	C11	D8
z_motor.mb+/1	z_motor	mb+	cnc_terminals	3A	z_motor.mb+	16	terminals	B11	B11
z_motor.mb+/2	cnc_terminals	3B	Z_cl57s	B+	z_motor.mb+	16	terminals, con?	C11	D8
z_motor.mb-/1	z_motor	mb-	cnc_terminals	4A	z_motor.mb-	16	terminals	B11	B11
z_motor.mb-/2	cnc_terminals	4B	Z_cl57s	B-	z_motor.mb-	16	terminals, con?	C11	D8