WIRE LIST	FILE	PRINTED
PanelViz Wiring Sc?	mycnc.yml	2026-06-13 **PAGE 1 OF 6**

Wire count: 259 **Component count: 64**

Wire	From	Pin	To	Pin	Net	AWG	Tags	From Ref	To Ref
110L/4	wall_plug	1	wall_power_t	1A	110L	12	vfd	Y11	Y11
110L/8	wall_power_t	1B	power_switch	L_IN	110L	12	vfd	X11	X11
110L/6	power_switch	L_OUT	breaker	L_IN	110L	12	vfd	W11	V10
110L/7	breaker	L_OUT	live_power_t	1A	110L	12	vfd	V10	O9
110L/5	live_power_t	1B	transformer	110L	110L	20	vfd	O9	V6
110L/2	live_power_t	3A	contactor_110	T2	110L	20	vfd	O9	M6
110L/1	24v	110L	live_power_t	3B	110L	20	dc_power, vfd	M8	O9
110L/3	5v	110L	live_power_t	5A	110L	20	dc_power, vfd	M10	O9
110L_SWITCHED/1	contactor_110	L2	switched_110L	1A	110L_SWITCHED	20	vfd	K6	N8
110L_SWITCHED/2	48v	110L	switched_110L	1B	110L_SWITCHED	20	vfd	Q11	O8
110L_SWITCHED/3	36V_X1	110L	switched_110L	2A	110L_SWITCHED	20	vfd	Q3	N8
110L_SWITCHED/4	36V_X2	110L	switched_110L	2B	110L_SWITCHED	20	vfd	Q7	O8
110N/4	wall_plug	2	live_power_t	2A	110N	12	vfd	Y11	O9
110N/5	live_power_t	2B	transformer	110N	110N	20	vfd	O9	V6
110N/2	live_power_t	4A	contactor_110	T3	110N	20	vfd	O9	M7
110N/1	24v	110N	live_power_t	4B	110N	20	dc_power, vfd	M8	O9
110N/3	5v	110N	live_power_t	6A	110N	20	dc_power, vfd	M10	O10
110N_SWITCHED/1	contactor_110	L3	switched_110N	1A	110N_SWITCHED	20	vfd	K7	N9
110N_SWITCHED/2	36V_X1	110N	switched_110N	1B	110N_SWITCHED	20	vfd	Q3	O9
110N_SWITCHED/3	36V_X2	110N	switched_110N	2A	110N_SWITCHED	20	vfd	Q7	N8
110N_SWITCHED/4	48v	110N	switched_110N	2B	110N_SWITCHED	20	vfd	Q11	O8
24V/1	estop_panel	estop+	cnc_terminals	57A	24V	20	terminals	B10	C6
24V/2	cnc_terminals	57B	terminals_24v	1A	24V	20	terminals	C6	B13
24V/3	estop_panel	light+	cnc_terminals	59A	24V	20	terminals	B10	C6
24V/4	cnc_terminals	59B	terminals_24v	1B	24V	20	terminals	C6	C13
24V/14	24v	24V	dc_power_24v	1A	24V	20	dc_power	M9	L13
24V/13	dc_power_24v	1B	safety_24v	1A	24V	20	dc_power, safe?	L13	J13
24V/12	safety_24v	1B	control_24v	1A	24V	20	safety, control	I13	F14
24V/5	control_24v	1B	terminals_24v	2A	24V	20	control, termi?	G14	B13
24V/6	control_24v	2A	axbb-e	I1+	24V	20	control	F14	E10
24V/7	control_24v	2B	axbb-e	I2+	24V	20	control	G14	E10
24V/8	control_24v	3A	axbb-e	I3+	24V	20	control	F14	E10
24V/9	control_24v	3B	axbb-e	I4+	24V	20	control	G14	E10
24V/10	control_24v	4A	axbb-e	I5+	24V	20	control	F13	E9
24V/11	axbb-e	IN-24V+	control_24v	4B	24V	20	control	G11	G13
24V0/7	24v	24V0	dc_power_24v0	1A	24V0	20	dc_power	M9	L13
24V0/6	dc_power_24v0	1B	safety_24v0	1A	24V0	20	dc_power, safe?	L13	I14
24V0/3	safety_24v0	1B	control_24v0	1A	24V0	20	safety, control	J14	F14
24V0/1	control_24v0	1B	terminals_24v0	1A	24V0	20	control, termi?	G14	B13
24V0/2	axbb-e	IN-24V0	control_24v0	2A	24V0	20	control	G11	F14
24V0/4	run_relay	COM	safety_24v0	2A	24V0	20	safety	J6	I13
24V0/5	upper_limits_ok_relay	COM	safety_24v0	2B	24V0	20	safety	J5	J13

Wire	From	Pin	To	Pin	Net	AWG	Tags	From Ref	To Ref
36V0_X1/3	36V_X1	36V0_X1	driver_power	2A	36V0_X1	20	vfd	Q3	O11
36V0_X1/1	x1_motor	M-	cnc_terminals	30A	36V0_X1	16	terminals	A6	C8
36V0_X1/2	cnc_terminals	30B	driver_power	2B	36V0_X1	16	terminals, vfd	C8	O11
36V0_X2/3	36V_X2	36V0_X2	driver_power	4A	36V0_X2	20	vfd	Q7	O11
36V0_X2/1	x2_motor	M-	cnc_terminals	42A	36V0_X2	16	terminals	A8	C7
36V0_X2/2	cnc_terminals	42B	driver_power	4B	36V0_X2	16	terminals, vfd	C7	O11
36V_X1/3	36V_X1	36V_X1	driver_power	1A	36V_X1	20	vfd	Q3	O11
36V_X1/1	x1_motor	M+	cnc_terminals	29A	36V_X1	16	terminals	A6	C8
36V_X1/2	cnc_terminals	29B	driver_power	1B	36V_X1	16	terminals, vfd	C8	O11
36V_X2/3	36V_X2	36V_X2	driver_power	3A	36V_X2	20	vfd	Q7	O11
36V_X2/1	x2_motor	M+	cnc_terminals	41A	36V_X2	16	terminals	A8	C7
36V_X2/2	cnc_terminals	41B	driver_power	3B	36V_X2	16	terminals, vfd	C7	O11
5V/1	z_limits	5v	cnc_terminals	11A	5V	20	terminals	B2	C10
5V/2	cnc_terminals	11B	terminals_5v	1A	5V	20	terminals	C10	C12
5V/3	y_limits	5v	cnc_terminals	25A	5V	20	terminals	B4	C8
5V/4	cnc_terminals	25B	terminals_5v	1B	5V	20	terminals	C8	C12
5V/5	x1_limits	5v	cnc_terminals	37A	5V	20	terminals	B6	C7
5V/6	cnc_terminals	37B	terminals_5v	2A	5V	20	terminals	C7	C12
5V/7	x2_limits	5v	cnc_terminals	49A	5V	20	terminals	B8	C6
5V/8	cnc_terminals	49B	terminals_5v	2B	5V	20	terminals	C6	C12
5V/17	run_relay	DC+	safety_5v	1A	5V	20	safety	I6	I12
5V/18	upper_limits_ok_relay	DC+	safety_5v	1B	5V	20	safety	I5	J12
5V/20	5v	5V	dc_power_5v	1A	5V	20	dc_power	M10	L12
5V/19	dc_power_5v	1B	safety_5v	2A	5V	20	dc_power, safe?	L12	I12
5V/11	safety_5v	2B	control_5v	1A	5V	20	safety, control	J12	F13
5V/9	control_5v	1B	terminals_5v	3A	5V	20	control, termi?	G13	C12
5V/10	axbb-e	IN-5V+	control_5v	2A	5V	20	control	G10	F12
5V/16	alarm_limit_board	5V	safety_5v	3A	5V	20	safety	I11	I12
5V/12	opto_board	5+	safety_5v	3B	5V	20	safety	H8	J12
5V/13	opto_board	6+	safety_5v	4A	5V	20	safety	H8	I12
5V/14	opto_board	7+	safety_5v	4B	5V	20	safety	H8	J12
5V/15	opto_board	8+	safety_5v	5A	5V	20	safety	H8	I12
5V0/1	z_limits	5v0	cnc_terminals	14A	5V0	20	terminals	B2	C9
5V0/2	cnc_terminals	14B	terminals_5v0	1A	5V0	20	terminals	C9	C12
5V0/3	y_limits	5v0	cnc_terminals	28A	5V0	20	terminals	B4	C8
5V0/4	cnc_terminals	28B	terminals_5v0	1B	5V0	20	terminals	C8	B12
5V0/5	x1_control	alrm-	cnc_terminals	32A	5V0	20	terminals	A6	C8
5V0/6	cnc_terminals	32B	terminals_5v0	2A	5V0	20	terminals	C8	C13
5V0/7	x1_control	dir-	cnc_terminals	34A	5V0	20	terminals	A6	C8
5V0/8	cnc_terminals	34B	terminals_5v0	2B	5V0	20	terminals	C8	B13
5V0/9	x1_control	pul-	cnc_terminals	36A	5V0	20	terminals	A6	C7
5V0/10	cnc_terminals	36B	terminals_5v0	3A	5V0	20	terminals	C7	C13
5V0/11	x1_limits	5v0	cnc_terminals	40A	5V0	20	terminals	B6	C7
5V0/12	cnc_terminals	40B	terminals_5v0	3B	5V0	20	terminals	C7	B13
5V0/13	x2_control	alrm-	cnc_terminals	44A	5V0	20	terminals	A8	C7

Wire	From	Pin	To	Pin	Net	AWG	Tags	From Ref	To Ref
5V0/14	cnc_terminals	44B	terminals_5v0	4A	5V0	20	terminals	C7	C13
5V0/15	x2_control	dir-	cnc_terminals	46A	5V0	20	terminals	A8	C7
5V0/16	cnc_terminals	46B	terminals_5v0	4B	5V0	20	terminals	C7	B13
5V0/17	x2_control	pul-	cnc_terminals	48A	5V0	20	terminals	A8	C6
5V0/18	cnc_terminals	48B	terminals_5v0	5A	5V0	20	terminals	C6	C13
5V0/19	x2_limits	5v0	cnc_terminals	52A	5V0	20	terminals	B8	C6
5V0/20	cnc_terminals	52B	terminals_5v0	5B	5V0	20	terminals	C6	B13
5V0/21	estop_panel	reset_sw+	cnc_terminals	55A	5V0	20	terminals	B10	C6
5V0/22	cnc_terminals	55B	terminals_5v0	6A	5V0	20	terminals	C6	C13
5V0/37	run_relay	DC-	safety_5v0	1A	5V0	20	safety	I6	I13
5V0/38	upper_limits_ok_relay	DC-	safety_5v0	1B	5V0	20	safety	I5	J13
5V0/40	5v	5V0	dc_power_5v0	1A	5V0	20	dc_power	M10	L12
5V0/39	dc_power_5v0	1B	safety_5v0	2A	5V0	20	dc_power, safe?	L12	I13
5V0/31	safety_5v0	2B	control_5v0	1A	5V0	20	safety, control	J13	F13
5V0/23	control_5v0	1B	terminals_5v0	6B	5V0	20	control, termi?	G13	B13
5V0/28	y_cl57s	PUL-	control_5v0	2A	5V0	20	control	H6	F13
5V0/29	y_cl57s	DIR-	control_5v0	2B	5V0	20	control	H6	G13
5V0/30	y_cl57s	COM-	control_5v0	3A	5V0	20	control	H5	F13
5V0/24	Z_cl57s	PUL-	control_5v0	3B	5V0	20	control	E4	G13
5V0/25	Z_cl57s	DIR-	control_5v0	4A	5V0	20	control	E5	F13
5V0/26	Z_cl57s	COM-	control_5v0	4B	5V0	20	control	E5	G13
5V0/27	axbb-e	IN-5V0	control_5v0	5A	5V0	20	control	G11	F13
5V0/36	alarm_limit_board	5V0	safety_5v0	3A	5V0	20	safety	I11	I13
5V0/32	opto_board	1-	safety_5v0	3B	5V0	20	safety	H9	J13
5V0/33	opto_board	2-	safety_5v0	4A	5V0	20	safety	H9	I13
5V0/34	opto_board	3-	safety_5v0	4B	5V0	20	safety	H9	J13
5V0/35	opto_board	4-	safety_5v0	5A	5V0	20	safety	H9	I13
COIL+/5	contactor_110	A1	coil_t	1A	COIL+	20	vfd	K7	L4
COIL+/4	contactor_220	A1	coil_t	1B	COIL+	20	vfd	K6	K4
COIL+/1	secondary_estop	estop-	cnc_terminals	64A	COIL+	20	terminals	B12	C5
COIL+/2	cnc_terminals	64B	coil_t	2A	COIL+	20	terminals, vfd	C5	L4
COIL+/3	axbb-e	I6+	coil_t	2B	COIL+	20	control, vfd	E9	K4
COIL-/4	contactor_110	A2	coil_t	3A	COIL-	20	vfd	M7	L4
COIL-/3	contactor_220	A2	coil_t	3B	COIL-	20	vfd	M6	K4
COIL-/1	axbb-e	I6-	coil_t	4A	COIL-	20	control, vfd	E9	L4
COIL-/2	run_relay	NO	coil_t	4B	COIL-	20	safety, vfd	J6	K4
DRIVER_48V/3	48v	48V	driver_power	5A	DRIVER_48V	20	vfd	Q11	O11
DRIVER_48V/2	y_cl57s	+VDC	driver_power	5B	DRIVER_48V	20	control, vfd	H4	O11
DRIVER_48V/1	Z_cl57s	+VDC	driver_power	6A	DRIVER_48V	20	control, vfd	E6	O12
DRIVER_GND/7	48v	48V0	driver_power	7A	DRIVER_GND	20	vfd	Q11	O12
DRIVER_GND/1	z_control	gnd	cnc_terminals	10A	DRIVER_GND	20	terminals	A2	C10
DRIVER_GND/2	cnc_terminals	10B	Z_cl57s	GND	DRIVER_GND	20	terminals, con?	C10	E6
DRIVER_GND/3	y_control	gnd	cnc_terminals	24A	DRIVER_GND	20	terminals	A4	C8
DRIVER_GND/4	cnc_terminals	24B	y_cl57s	GND	DRIVER_GND	20	terminals, con?	C8	H4
DRIVER_GND/6	y_cl57s	GND	driver_power	7B	DRIVER_GND	20	control, vfd	H4	O12

Wire	From	Pin	To	Pin	Net	AWG	Tags	From Ref	To Ref
DRIVER_GND/5	Z_cl57s	GND	driver_power	8A	DRIVER_GND	20	control, vfd	E6	O12
RESET_SW/1	estop_panel	reset_sw-	cnc_terminals	56A	RESET_SW	20	terminals	B10	C6
RESET_SW/2	cnc_terminals	56B	alarm_limit_board	D12	RESET_SW	20	terminals, saf?	C6	I10
RUN_RELAY_CTL/1	alarm_limit_board	D10	run_relay	IN	RUN_RELAY_CTL	20	safety	I11	I7
UL1/1	upper_limits_ok_relay	NC	axbb-e	I1-	UL1	20	safety, control	J6	E10
UPPER_LIMITS_OK_RE/1	alarm_limit_board	D11	upper_limits_ok_relay	IN	UPPER_LIMITS_OK_RE/1	20	safety	I10	I6
VFD_FWD/1	axbb-e	O3	vfd	FOR	VFD_FWD	20	control, vfd	E11	O15
VFD_REV/1	axbb-e	O2	vfd	REV	VFD_REV	20	control, vfd	E11	O15
VFD_V1/1	axbb-e	A01	vfd	VI	VFD_V1	20	control, vfd	G10	P18
X1DIR/1	x1_control	dir+	cnc_terminals	33A	X1DIR	20	terminals	A6	C8
X1DIR/2	cnc_terminals	33B	axbb-e	O12	X1DIR	20	terminals, con?	C8	G10
X1LL/1	x1_limits	ll	cnc_terminals	39A	X1LL	20	terminals	B6	C7
X1LL/2	cnc_terminals	39B	axbb-e	I3-	X1LL	20	terminals, con?	C7	E10
X1STEP/1	x1_control	pul+	cnc_terminals	35A	X1STEP	20	terminals	A6	C8
X1STEP/2	cnc_terminals	35B	axbb-e	O11	X1STEP	20	terminals, con?	C8	G9
X1UL_OK/1	alarm_limit_board	D2	opto_board	O1	X1UL_OK	20	safety	I11	J9
X1_ALM_OK/1	alarm_limit_board	D6	opto_board	O5	X1_ALM_OK	20	safety	I11	J8
X2DIR/1	x2_control	dir+	cnc_terminals	45A	X2DIR	20	terminals	A8	C7
X2DIR/2	cnc_terminals	45B	axbb-e	O14	X2DIR	20	terminals, con?	C7	G10
X2LL/1	x2_limits	ll	cnc_terminals	51A	X2LL	20	terminals	B8	C6
X2LL/2	cnc_terminals	51B	axbb-e	I4-	X2LL	20	terminals, con?	C6	E10
X2STEP/1	x2_control	pul+	cnc_terminals	47A	X2STEP	20	terminals	A8	C7
X2STEP/2	cnc_terminals	47B	axbb-e	O13	X2STEP	20	terminals, con?	C7	G10
X2UL_OK/1	alarm_limit_board	D3	opto_board	O2	X2UL_OK	20	safety	I11	J9
X2_ALM_OK/1	alarm_limit_board	D7	opto_board	O6	X2_ALM_OK	20	safety	I11	J8
YDIR/1	y_cl57s	DIR+	axbb-e	O10	YDIR	20	control	H6	G9
YLL/1	y_limits	ll	cnc_terminals	27A	YLL	20	terminals	B4	C8
YLL/2	cnc_terminals	27B	axbb-e	I2-	YLL	20	terminals, con?	C8	E10
YSTEP/1	y_cl57s	PUL+	axbb-e	O9	YSTEP	20	control	H6	G9
YUL_OK/1	alarm_limit_board	D4	opto_board	O3	YUL_OK	20	safety	I11	J9
Y_ALM_OK/1	alarm_limit_board	D8	opto_board	O7	Y_ALM_OK	20	safety	I11	J8
ZDIR/1	Z_cl57s	DIR+	axbb-e	O16	ZDIR	20	control	E4	G10
ZLL/1	z_limits	ll	cnc_terminals	13A	ZLL	20	terminals	B2	C9
ZLL/2	cnc_terminals	13B	axbb-e	I5-	ZLL	20	terminals, con?	C9	E9
ZSTEP/1	Z_cl57s	PUL+	axbb-e	O15	ZSTEP	20	control	E4	G10
ZUL_OK/1	alarm_limit_board	D5	opto_board	O4	ZUL_OK	20	safety	I11	J9
Z_ALM_OK/1	alarm_limit_board	D9	opto_board	O8	Z_ALM_OK	20	safety	I11	J8
Z_cl57s.ALM/1	Z_cl57s	ALM	opto_board	8-	Z_cl57s.ALM	20	control, safety	E5	H8
earth/8	wall_plug	GND	vfd_earth	1A	earth	12	vfd	Y11	N12
earth/9	transformer	GND	vfd_earth	1B	earth	20	vfd	V6	O12
earth/10	48v	GND	vfd_earth	2A	earth	20	vfd	Q12	N12
earth/4	24v	GND	dc_power_earth	1A	earth	20	dc_power	M8	L13
earth/5	5v	GND	dc_power_earth	1B	earth	20	dc_power	M10	M13
earth/11	36V_X1	GND	vfd_earth	2B	earth	20	vfd	Q3	O12
earth/12	36V_X2	GND	vfd_earth	3A	earth	20	vfd	Q7	N12

Wire	From	Pin	To	Pin	Net	AWG	Tags	From Ref	To Ref
earth/7	vfd	GND	vfd_earth	3B	earth	20	vfd	O21	O12
earth/6	vfd_earth	4A	dc_power_earth	2A	earth	20	vfd, dc_power	N12	L13
earth/3	dc_power_earth	2B	safety_earth	1A	earth	20	dc_power, safe?	M13	I14
earth/2	safety_earth	1B	control_earth	1A	earth	20	safety, control	J14	F14
earth/1	control_earth	1B	terminals_earth	1A	earth	20	control, termi?	G14	C12
estop_panel.estop?	estop_panel	estop-	cnc_terminals	58A	estop_panel.estop-	20	terminals	B10	C6
estop_panel.estop?	cnc_terminals	58B	secondary_estop	estop+	estop_panel.estop-	20	terminals	C6	B12
estop_panel.light?	estop_panel	light-	cnc_terminals	60A	estop_panel.light-	20	terminals	B10	C5
estop_panel.light?	cnc_terminals	60B	run_relay	NC	estop_panel.light-	20	terminals, saf?	C5	J7
probe.probe+/1	probe	probe+	cnc_terminals	53A	probe.probe+	20	terminals	A10	C6
probe.probe-/1	probe	probe-	cnc_terminals	54A	probe.probe-	20	terminals	A10	C6
shield/2	z_motor	shield	connector_earth	1A	shield	20	terminals	A2	C14
shield/8	z_control	shield	connector_earth	1B	shield	20	terminals	A2	C14
shield/12	z_limits	shield	connector_earth	2A	shield	20	terminals	B2	C14
shield/1	y_motor	shield	connector_earth	2B	shield	20	terminals	A4	C14
shield/6	y_control	shield	connector_earth	3A	shield	20	terminals	A4	C14
shield/11	y_limits	shield	connector_earth	3B	shield	20	terminals	B4	C14
shield/3	x1_motor	shield	connector_earth	4A	shield	20	terminals	A6	C14
shield/10	x1_limits	shield	connector_earth	4B	shield	20	terminals	B6	C14
shield/5	x2_motor	shield	connector_earth	5A	shield	20	terminals	A8	C14
shield/9	x2_limits	shield	connector_earth	5B	shield	20	terminals	B8	C14
shield/7	probe	shield	connector_earth	6A	shield	20	terminals	A10	C14
shield/4	spindle	shield	connector_earth	6B	shield	20	terminals	A10	C14
spindle.u/1	spindle	u	cnc_terminals	61A	spindle.u	16	terminals	A10	C5
spindle.u/2	cnc_terminals	61B	vfd	U	spindle.u	16	terminals, vfd	C5	O21
spindle.v/1	spindle	v	cnc_terminals	62A	spindle.v	16	terminals	A10	C5
spindle.v/2	cnc_terminals	62B	vfd	V	spindle.v	16	terminals, vfd	C5	O21
spindle.w/1	spindle	w	cnc_terminals	63A	spindle.w	16	terminals	A10	C5
spindle.w/2	cnc_terminals	63B	vfd	W	spindle.w	16	terminals, vfd	C5	O21
transformer.220L/1	transformer	220L	contactor_220	T1	transformer.220L	20	vfd	V6	M5
transformer.220N/1	transformer	220N	contactor_220	T2	transformer.220N	20	vfd	V6	M5
vfd.R/1	vfd	R	contactor_220	L1	vfd.R	20	vfd	O21	K5
vfd.T/1	vfd	T	contactor_220	L2	vfd.T	20	vfd	O21	K5
x1_control.alrm+/1	x1_control	alrm+	cnc_terminals	31A	x1_control.alrm+	20	terminals	A6	C8
x1_control.alrm+/2	cnc_terminals	31B	opto_board	5-	x1_control.alrm+	20	terminals, saf?	C8	H8
x1_limits.ul/1	x1_limits	ul	cnc_terminals	38A	x1_limits.ul	20	terminals	B6	C7
x1_limits.ul/2	cnc_terminals	38B	opto_board	1+	x1_limits.ul	20	terminals, saf?	C7	H9
x2_control.alrm+/1	x2_control	alrm+	cnc_terminals	43A	x2_control.alrm+	20	terminals	A8	C7
x2_control.alrm+/2	cnc_terminals	43B	opto_board	6-	x2_control.alrm+	20	terminals, saf?	C7	H8
x2_limits.ul/1	x2_limits	ul	cnc_terminals	50A	x2_limits.ul	20	terminals	B8	C6
x2_limits.ul/2	cnc_terminals	50B	opto_board	2+	x2_limits.ul	20	terminals, saf?	C6	H9
y_cl57s.ALM/1	y_cl57s	ALM	opto_board	7-	y_cl57s.ALM	20	control, safety	H5	H8
y_control.ea+/1	y_control	ea+	cnc_terminals	21A	y_control.ea+	20	terminals	A4	C9
y_control.ea+/2	cnc_terminals	21B	y_cl57s	EA+	y_control.ea+	20	terminals, con?	C9	H5
y_control.ea-/1	y_control	ea-	cnc_terminals	22A	y_control.ea-	20	terminals	A4	C9

WIRE LIST

PanelViz Wiring Sc?

FILE

mycnc.yml

PRINTED

2026-06-13

Wire	From	Pin	To	Pin	Net	AWG	Tags	From Ref	To Ref
y_control.ea-/2	cnc_terminals	22B	y_cl57s	EA-	y_control.ea-	20	terminals, con?	C9	H5
y_control.eb+/1	y_control	eb+	cnc_terminals	19A	y_control.eb+	20	terminals	A4	C9
y_control.eb+/2	cnc_terminals	19B	y_cl57s	EB+	y_control.eb+	20	terminals, con?	C9	H5
y_control.eb-/1	y_control	eb-	cnc_terminals	20A	y_control.eb-	20	terminals	A4	C9
y_control.eb-/2	cnc_terminals	20B	y_cl57s	EB-	y_control.eb-	20	terminals, con?	C9	H5
y_control.vcc/1	y_control	vcc	cnc_terminals	23A	y_control.vcc	20	terminals	A4	C9
y_control.vcc/2	cnc_terminals	23B	y_cl57s	VCC	y_control.vcc	20	terminals, con?	C9	H5
y_limits.ul/1	y_limits	ul	cnc_terminals	26A	y_limits.ul	20	terminals	B4	C8
y_limits.ul/2	cnc_terminals	26B	opto_board	3+	y_limits.ul	20	terminals, saf?	C8	H9
y_motor.ma+/1	y_motor	ma+	cnc_terminals	15A	y_motor.ma+	16	terminals	A4	C9
y_motor.ma+/2	cnc_terminals	15B	y_cl57s	A+	y_motor.ma+	16	terminals, con?	C9	H5
y_motor.ma-/1	y_motor	ma-	cnc_terminals	16A	y_motor.ma-	16	terminals	A4	C9
y_motor.ma-/2	cnc_terminals	16B	y_cl57s	A-	y_motor.ma-	16	terminals, con?	C9	H5
y_motor.mb+/1	y_motor	mb+	cnc_terminals	17A	y_motor.mb+	16	terminals	A4	C9
y_motor.mb+/2	cnc_terminals	17B	y_cl57s	B+	y_motor.mb+	16	terminals, con?	C9	H4
y_motor.mb-/1	y_motor	mb-	cnc_terminals	18A	y_motor.mb-	16	terminals	A4	C9
y_motor.mb-/2	cnc_terminals	18B	y_cl57s	B-	y_motor.mb-	16	terminals, con?	C9	H4
z_control.ea+/1	z_control	ea+	cnc_terminals	7A	z_control.ea+	20	terminals	A2	C10
z_control.ea+/2	cnc_terminals	7B	Z_cl57s	EA+	z_control.ea+	20	terminals, con?	C10	E5
z_control.ea-/1	z_control	ea-	cnc_terminals	8A	z_control.ea-	20	terminals	A2	C10
z_control.ea-/2	cnc_terminals	8B	Z_cl57s	EA-	z_control.ea-	20	terminals, con?	C10	E5
z_control.eb+/1	z_control	eb+	cnc_terminals	5A	z_control.eb+	20	terminals	A2	C10
z_control.eb+/2	cnc_terminals	5B	Z_cl57s	EB+	z_control.eb+	20	terminals, con?	C10	E5
z_control.eb-/1	z_control	eb-	cnc_terminals	6A	z_control.eb-	20	terminals	A2	C10
z_control.eb-/2	cnc_terminals	6B	Z_cl57s	EB-	z_control.eb-	20	terminals, con?	C10	E5
z_control.vcc/1	z_control	vcc	cnc_terminals	9A	z_control.vcc	20	terminals	A2	C10
z_control.vcc/2	cnc_terminals	9B	Z_cl57s	VCC	z_control.vcc	20	terminals, con?	C10	E5
z_limits.ul/1	z_limits	ul	cnc_terminals	12A	z_limits.ul	20	terminals	B2	C9
z_limits.ul/2	cnc_terminals	12B	opto_board	4+	z_limits.ul	20	terminals, saf?	C9	H9
z_motor.ma+/1	z_motor	ma+	cnc_terminals	1A	z_motor.ma+	16	terminals	A2	C10
z_motor.ma+/2	cnc_terminals	1B	Z_cl57s	A+	z_motor.ma+	16	terminals, con?	C10	E6
z_motor.ma-/1	z_motor	ma-	cnc_terminals	2A	z_motor.ma-	16	terminals	A2	C10
z_motor.ma-/2	cnc_terminals	2B	Z_cl57s	A-	z_motor.ma-	16	terminals, con?	C10	E6
z_motor.mb+/1	z_motor	mb+	cnc_terminals	3A	z_motor.mb+	16	terminals	A2	C10
z_motor.mb+/2	cnc_terminals	3B	Z_cl57s	B+	z_motor.mb+	16	terminals, con?	C10	E6
z_motor.mb-/1	z_motor	mb-	cnc_terminals	4A	z_motor.mb-	16	terminals	A2	C10
z_motor.mb-/2	cnc_terminals	4B	Z_cl57s	B-	z_motor.mb-	16	terminals, con?	C10	E6