
Note: VCC = 5V
VS = 9V
DAN202K x5
FRONT PANEL DAUGHTER BOARD
PST529
HCU04
C4699
X1 21.47727MHz
7805
ERZC05DK220
(POWER SW)
PB1100
F1 1.5A
ZJYS5102-2P
+10V (Nominal) for NTSC
DC Jack
AV MULTI-OUT
RF MODULATOR
RF Video Out
S-CPU (Ricoh 5A22)
65C816 Main CPU
S-PPU1 (Ricoh 5C77)
Picture Processing Unit
32Kx8 SRAM
Video RAM
S-PPU2 (Ricoh 5C78)
Picture Processing Unit
S-ENC (BA6592F)
Video Encoder
S-WRAM (128Kx8 DRAM)
Work RAM
CARTRIDGE SLOT
Pin Pitch = 2.5mm (not 2.54mm)
PCB Thickness = 1.2mm (not 1.5mm)
EXPANSION PORT (EXT)
UPD6376
16-bit Stereo DAC
Pre-Amplifier
LM324
(Transistor Inverts Pol)
(RIGHT)
(LEFT)
Post-Amplifier
24.576MHz
S-SMP
Sony SPC700 Sub CPU
S-DSP
Sony Sound Chip
32Kx8 PSRAM
Audio RAM
Analog Mixer
Mixes main audio from APU with audio from cartridge and expansion port.
F411 CIC
SHVC-SOUND Connector

(Exists only on 1st revision SNES)

NOTE: 1st revision SNES has two LM2904 (Dual Op-Amps) chips instead of one LM324 (Quad Op-Amp).
One 2904 chip is on the SHVC-SOUND daughterboard (for the pre-amplifier)
and one is on the motherboard (for the post-amplifier).

Latest version of this schematic can be found at any of the following URLs:
https://rm-rfroot.net/snes_fpga/
https://dl.dropboxusercontent.com/u/36237540/SNES/jwdonal/schematics/snes_schematic.zip
http://forums.nesdev.com/viewtopic.php?f=12&t=10470
http://wiki.superfamicom.org/

Title Super Nintendo (NTSC) Revision 2 Motherboard (w/ Revision 1 SHVC-SOUND connector) Revision 2 Boards: SNS-CPU-GPM-01 (1992), SNS-CPU-GPM-02 (1993) SNS-CPU-RGB-01 (1994), SNS-CPU-RGB-02 (1995)		
Size A1	Number	Revision 1.5
Date: 2/24/2014		Sheet 1 of 1
File: C:\MyDocuments\..\snes_mobo.SchDoc		Drawn By: Jonathon W. Donaldson