ARRANGE J2, J3 AND J4
IN 3X3 JUMPER BLOCK

J2,J4,J3 JUMPER TABLE

RC2014 Z8 CTC & DS1302 RTC V2
BOARD ADDRESSING
J2=ADDRESS
J3=ADDRESS INVERTED
J4=COMMON

	J2	J4	J3		
A5	0	---	0		
A6	0	---	0		
A7	0	---	0	=	0xE0-0xFF
	J2	J4	J3		
A5	0	0	---		
A6	0	---	0		
A7	0	---	0	=	0xC0-0xDF
	J2	J4	J3		
A5	0	---	0		
A6	0	0	---		
A7	0	---	0	=	0xA0-0xBF
	J2	J4	J3		
A5	0	0	---		
A6	0	0	---		
A7	0	---	0	=	0x80-0x9F
	J2	J4	J3		
A5	0	---	0		
A6	0	---	0		
A7	0	0	---	=	0x60-0x7F
	J2	J4	J3		
A5	0	0	---		
A6	0	---	0		
A7	0	0	---	=	0x40-0x5F
	J2	J4	J3		
A5	0	---	0		
A6	0	0	---		
A7	0	---	0	=	0x20-0x3F
	J2	J4	J3		
A5	0	0	---		
A6	0	0	---		
A7	0	---	0	=	0x00-0x1F

OF THE 32 I/O ADDRESSES SELECTED
BY J2, J4, J3 THEN J5 SELECTS
ADDRESS BLOCKS OF 4 I/O ADDRESSES
SELECT 1 FOR THE CTC AND 1 FOR THE RTC

WIRE JUMPERS CAN BREAK THE LIMITS
PLACED BY STRAIGHT ACROSS JUMPERS

EXAMPLE IF 0x80 IS BASE
SELECTED BY J2,J4,J3
Y0 = 0x80
Y1 = 0x84
Y2 = 0x88
Y3 = 0x8C
Y4 = 0x90
Y5 = 0x94
Y6 = 0x98
Y7 = 0x9C

J2, J4, J3 SELECT 1 OF 8
32 I/O ADDRESS BLOCKS
SEE THE TABLE ON THE RIGHT

RTC COMMAND LATCH

Z84C30 CTC IS SET UP TO TRIGGER
PERIODIC INTERRUPTS. FREQ IS
COMPATIBLE WITH ZETA2 TO GENERATE
AN INTERRUPT EVERY 20 MSEC.

CLOCK IS PICKED OFF
THE RC2014 BUS. MUST
BE THE CPU CLOCK.

CTC CLOCK SPEC WILL
LIMIT SYSTEM SPEED.
LOOK FOR CTC FAILING
"IS PRESENT" TEST IF
NOT GETTING PERIODIC
INTERRUPTS.

JUMPER ONE

DEVICE BY TWO TO BE ZETA2 COMPATIBLE

EXTERNAL INTERUUPT ROUTING

CX_IN CAN BE USED
TO TRIGGER EXTERNAL
INTERRUPTS FROM OTHER
DEVICES

JUMPER J3 1-2 IF THIS
IS THE FIRST DEVICE IN
AN INTERRUPT CHAIN

32768HZ
Y2
DS1302S+ SPEC IS 6pF

Sheet:	/
File:	RC2014-CTC-DS1302-TIMER-V21.kicad_sch
Title:	**RC2014 Z80 CTC & DS1302 RTC V2.1**
Size: B	Date: 2026-01-01
KiCad E.D.A. 9.0.6	**Rev: 2.1**
	Id: 1/1