

## ASSIGNMENT IV

Write code and connections in wokwi for the ultrasonic sensor. Whenever the distance is less than 100 cms send an "alert" to the IBM cloud and display in the device recent events.

### CODE:

sketch.ino

```
#include <WiFi.h>
#include<PubSubClient.h>
WiFiClient wifiClient;
String data3;
#define ORG "x7ay23"
#define DEVICE_TYPE "ESP32"
#define DEVICE_ID "assignment4"
#define TOKEN "1123581321"
#define speed 0.034
#define led 14
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/data/fmt/json";
char topic[] = "iot-2/cmd/command/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
PubSubClient client(server, 1883, wifiClient);

const int trigpin=5;
const int echopin=18;
String command;
String data="";
long duration;
float dist;

void setup()
{
  Serial.begin(115200);
  pinMode(led, OUTPUT);
  pinMode(trigpin, OUTPUT);
  pinMode(echopin, INPUT);
  wifiConnect();
  mqttConnect();
}
```

```

void loop() {
bool isNearby = dist < 100;
digitalWrite(led, isNearby);
publishData();
delay(500);
if (!client.loop()) {
mqttConnect();
}
}

void wifiConnect() {
Serial.print("Connecting to "); Serial.print("Wifi");
WiFi.begin("Wokwi-GUEST", "", 6);
while (WiFi.status() != WL_CONNECTED) {
delay(500);
Serial.print(".");
}
Serial.print("WiFi connected, IP address: ");
Serial.println(WiFi.localIP()); }

void mqttConnect() {
if (!client.connected()) {
Serial.print("Reconnecting MQTT client to ");
Serial.println(server); while (!client.connect(clientId, authMethod,
token)) {
Serial.print(".");
delay(500);
}
}
initManagedDevice();
Serial.println();
}

void initManagedDevice() {
if (client.subscribe(topic)) {
// Serial.println(client.subscribe(topic));
Serial.println("IBM subscribe to cmd OK");
} else {
Serial.println("subscribe to cmd FAILED");
}
}

void publishData()
{
digitalWrite(trigpin, LOW);
digitalWrite(trigpin, HIGH);

delayMicroseconds(10);
digitalWrite(trigpin, LOW);
duration=pulseIn(echopin, HIGH);
dist=duration*speed/2;
if(dist<100){

```

```

String payload = "{\"Alert Distance\":\"";
payload += dist;
payload += "}";
Serial.print("\n");
Serial.print("Sending payload: ");
Serial.println(payload);
if (client.publish(publishTopic, (char*) payload.c_str()))
{ Serial.println("Publish OK");
}
}
if(dist>100){
String payload = "{\"Distance\":\"";
payload += dist;
payload += "}";
Serial.print("\n");
Serial.print("Sending payload: ");
Serial.println(payload);
if(client.publish(publishTopic, (char*) payload.c_str()))
{ Serial.println("Publish OK");
}else {
Serial.println("Publish FAILED");
}
}
}
}

```

diagram.json

```

{
  "version": 1,
  "author": "MARY DERLIN TANYA X 19CS016",
  "editor": "wokwi",
  "parts": [
    { "type": "wokwi-esp32-devkit-v1", "id": "esp", "top": -13.33, "left": -70,
"attrs": { } },
    { "type": "wokwi-hc-sr04", "id": "ultrasonic1", "top": -35.57, "left": 84.83,
"attrs": { } }
  ],
  "connections": [
    [ "esp:TX0", "$serialMonitor:RX", "", [ ] ],
    [ "esp:RX0", "$serialMonitor:TX", "", [ ] ],
    [ "ultrasonic1:VCC", "esp:VIN", "red", [ "v154.01", "h-243.35", "v-67.77" ] ],
    [ "ultrasonic1:GND", "esp:GND.1", "black", [ "v0" ] ],
    [ "ultrasonic1:TRIG", "esp:D5", "green", [ "v0" ] ],
    [ "ultrasonic1:ECHO", "esp:D18", "green", [ "v0" ] ]
  ]
}

```

## CONNECTION DIAGRAM:

```
1 #include <WiFi.h>
2 #include<PubSubClient.h>
3 WiFiClient wifiClient;
4 String data3;
5 #define ORG "x7ay23"
6 #define DEVICE_TYPE "ESP32"
7 #define DEVICE_ID "assignment4"
8 #define TOKEN "1123581321"
9 #define speed 0.034
10 #define led 14
11 char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
12 char publishTopic[] = "iot-2/evt/data/fmt/json";
13 char topic[] = "iot-2/cmd/command/fmt/string";
14 char authMethod[] = "use-token-auth";
15 char token[] = TOKEN;
16 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
17 PubSubClient client(server, 1883, wifiClient);
18
19 const int trigpin=5;
20 const int echopin=18;
21 String command;
22 String data="";
23 long duration;
24 float dist;
25
26 void setup()
27 {
28   Serial.begin(115200);
29   pinMode(led, OUTPUT);
30   pinMode(trigpin, OUTPUT);
31   pinMode(echopin, INPUT);
32   wifiConnect();
33   mqttConnect();
34 }
35
```

Simulation

Publish OK

Sending payload: {"Alert Distance":41.94}

Publish OK

Sending payload: {"Alert Distance":41.94}

Publish OK

## IBM CLOUD SCREENSHOT:

Browse Action Device Types Interfaces Add Device

Search by Device ID Device Simulator

Device ID	Status	Device Type	Class ID	Date Added	Descriptive Location
assignment4	Disconnected	ESP32	Device	18 Nov 2022 20:20	

Identity Device Information Recent Events State Logs

The recent events listed show the live stream of data that is coming and going from this device.

Event	Value	Format	Last Received
data	{"Alert Distance":41.94}	json	a few seconds ago
data	{"Alert Distance":41.94}	json	a few seconds ago
data	{"Alert Distance":41.97}	json	a few seconds ago
data	{"Distance":123.98}	json	a few seconds ago
data	{"Distance":123.98}	json	a few seconds ago

**WOKWI LINK:** <https://wokwi.com/projects/348677162727899730>