This page is a full-page electronic schematic (KiCad) titled "RISCDUINO". It contains the following labelled functional blocks and component annotations.

Caravell SPI FLASH

Flash memory

U1 W25Q32JVSSIQ
+3.3V
C1 0.1uF

MEM_CS_C — CS
MEM_SO_C — SO(D1) / VCC
MEM_SO_C / MEM_WP_C — WP(D2) / HOLD(D3)
GND — GND / SCK / SI(D0)

MEM_HOLD_C
MEM_SCK_C
MEM_SI_C
GND

R1 10K Ohm R2 10K Ohm R3 10K Ohm R4 10K Ohm R5 10K Ohm R6 10K Ohm
+3.3V

Flash memory interface with Caravel

MEM_SO_C — Caravel_D1
MEM_SI_C — Caravel_D0
MEM_SCK_C — Caravel_SCK
MEM_CS_C — Caravel_CSB

User SPI FLASH

Flash memory

U5 W25Q32JVSSIQ
+3.3V
C21 0.1uF

MEM_CS_U — CS
MEM_SO_U — SO(D1) / VCC
MEM_WP_U — WP(D2) / HOLD(D3)
GND — GND / SCK / SI(D0)

MEM_HOLD_U
MEM_SCK_U
MEM_SI_U
GND

R9 10K Ohm R10 10K Ohm R11 10K Ohm R12 10K Ohm R13 10K Ohm R14 10K Ohm
+3.3V

Flash memory interface with Riscduino

MEM_SCK_U — mprj_io[28]
MEM_CS_U — mprj_io[29]
MEM_SI_U — mprj_io[33]
MEM_SO_U — mprj_io[34]
MEM_WP_U — mprj_io[35]
MEM_HOLD_U — mprj_io[36]

User SPI FLASH

Flash memory

U6 23LC1024
+3.3V
C22 0.1uF

SRAM_CS_U — CS
SRAM_SO_U — SO / VCC
SRAM_NU — NU / HOLD
GND — GND / SCK / SI

SRAM_HOLD_U
SRAM_SCK_U
SRAM_SI_U

R15 10K Ohm
+3.3V

Flash memory interface with Riscduino

SRAM_SCK_U — mprj_io[28]
SRAM_CS_U — mprj_io[31]
SRAM_SI_U — mprj_io[33]
SRAM_SO_U — mprj_io[34]
SRAM_NU — mprj_io[35]
SRAM_HOLD_U — mprj_io[36]

Caravell 64QFN

U2 Caravel
C11 0.1uf C14 0.1uf C9 0.1uf C8 0.1uf C10 0.1uf C13 0.1uf C16 0.1uf C15 0.1uf
GND vccd vdda vdda1 vccd1 vccd2

Signals: mprj_io[1]_SDO, mprj_io[0]_JTAG, flash_io0, flash_io1, flash_clk, flash_csb, clock, resetb, gpio, vccd, vssio, vddio

mprj_io[2]_SDI — mprj_io[2]_SDI
mprj_io[3]_CSB — mprj_io[3]_CSB
mprj_io[4]_SCK — mprj_io[4]_SCK
mprj_io[5]_ser_rx — mprj_io[5]_ser_rx
mprj_io[6]_ser_tx — mprj_io[6]_ser_tx
mprj_io[7] ... mprj_io[13]
vssa1 / vssd1 / vdda1 / vccd1
vdda1 / vddio

mprj_io[37] ... mprj_io[25]
vssd2 / vdda2 / vccd2 / vddio

ThermalPad
mprj_io[14] ... mprj_io[24]
vccd1 / vssa1 / vssd1 / vccd2 / vdda2 / vddio / vssd2 / vccd2

Arduino Pins

J1 Power
+5V / +5V / +3.3V / +1VB / DEBUG
RST

J2 Digital/PWM
Arduino_A5
Arduino_A4
mprj_io[5]_ser_rx
Arduino_13
Arduino_12
Arduino_11
Arduino_10
Arduino_9
Arduino_8

J3 Analog
Arduino_A0
Arduino_A1
Arduino_A2
Arduino_A3
Arduino_A4
Arduino_A5

J4 Digital/PWM
Arduino_7
Arduino_6
Arduino_5
Arduino_4
Arduino_3
Arduino_2
Arduino_1
Arduino_0
GND

Arduino IO to 64QFN

Arduino_0 — mprj_io[6]_ser_tx
Arduino_1 — mprj_io[7]
Arduino_2 — mprj_io[8]
Arduino_3 — mprj_io[9]
Arduino_4 — mprj_io[10]
Arduino_5 — mprj_io[13]
Arduino_6 — mprj_io[14]
Arduino_7 — mprj_io[15]

Arduino_8 — mprj_io[16]
Arduino_9 — mprj_io[17]
Arduino_10 — mprj_io[18]
Arduino_11 — mprj_io[19]
Arduino_12 — mprj_io[20]
Arduino_13 — mprj_io[21]

Arduino_A0 — mprj_io[22]
Arduino_A1 — mprj_io[23]
Arduino_A2 — mprj_io[24]
Arduino_A3 — mprj_io[25]
Arduino_A4 — mprj_io[26]
Arduino_A5 — mprj_io[27]

DEBUG — mprj_io[37]

Power

U3 LM1117MP-1.8
+5V +1V8
C2 0.1uF C3 10uF C4 22uF C5 0.1uF
VI / GND / VO
GND

U4 LM1117MP-3.3
+5V +3.3V
C6 0.1uF C7 10uF C17 22uF C18 0.1uF
VI / GND / VO
GND

+1V8 — vccd, vccd1, vccd2
+3.3V — vdda, vddio, vdda1, vdda2

MEMS Oscillator

+3.3V
C20 0.1uF
J6 Conn_01x02_Male
EN / OUT
GND
X1 10Mhz
xclk
GND

USB Module

J5 USB_B_Micro
C19 0.1uF
VBUS — +5V
D+ — USB_D+
D- — USB_D-
Shield / GND / ID
GND

Power on Reset

+3.3V
U8
RST / VDD
VSS / WB
MR
C23 0.1uF
SW1 SW_SPST
MR
GND

Caravel programming header

Connector_PinHeader_2.54mm:PinHeader_2x04_P2.54mm_Vertical
J7 Conn_02x04_Counter_ClockWise
+3.3V

mprj_io[1]_SDO — 1 2
mprj_io[4]_SCK — 3 4
RST — 5 6
mprj_io[3]_CSB — 7 8
mprj_io[2]_SDI
xclk
GND

LEDS

POWER LED

R8 470 Ohm PWR1 LED_R
+3.3V — GND

R17 470 Ohm PWR2 LED_R
+1V8 — GND

GPIO LED

R16 470 Ohm GPIO2 LED_R
+3.3VA — gpio

R7 470 Ohm GPIO1 LED_R
+3.3VA — Arduino_3

R18 470 Ohm GPIO3 LED_R
+3.3VA — Arduino_2

R20 470 Ohm GPIO4 LED_R
+3.3VA — Arduino_1

R21 470 Ohm GPIO5 LED_R
+3.3VA — Arduino_0

CP2102 USB TO UART

U7 CP2102N-Axx-xQFN20
+3.3VA
C26 4.7uF C27 0.1uF
GND
+5V
C25 1uF C24 0.1uF
GND
R22 10K Ohm
RST

VREGIN / VDD
TXD — Arduino_0
RXD — Arduino_1
RTS / CTS / DSR / DTR / DCD / RI/CLK
VBUS
D- — USB_D-
D+ — USB_D+
SUSPEND / SUSPEND
TXT/GPIO.0
RXT/GPIO.1
RS485/GPIO.3
WAKEUP/GPIO.4
GPIO.5 / GPIO.6
CHREN / CHRO / CHR1
GND